

# Specifications



## Eaton 174332

Eaton DE1 Variable speed starter, Rated operational voltage 230 V AC, 1-phase, Ie 9.6 A, 2.2 kW, 3 HP, Radio interference suppression filter

### General specifications

<b>PRODUCT NAME</b>	Eaton DE1 Variable speed starter
<b>CATALOG NUMBER</b>	174332
<b>MODEL CODE</b>	DE1-129D6FN-N20N
<b>EAN</b>	4015081707942
<b>PRODUCT LENGTH/DEPTH</b>	169 mm
<b>PRODUCT HEIGHT</b>	230 mm
<b>PRODUCT WIDTH</b>	90 mm
<b>PRODUCT WEIGHT</b>	1.68 kg

<b>CERTIFICATIONS</b>	Certified by UL for use in Canada RCM Safety requirements: IEC/EN 61800-5-1 UL UL report applies to both US and Canada IEC/EN61800-3 CUL UL Category Control No.: NMMS, NMMS7 IEC/EN 61800-3 IEC/EN61800-5 UL File No.: E172143 Specification for general requirements: IEC/EN 61800-2 CSA-C22.2 No. 14 RoHS, ISO 9001 CE UL 508C
-----------------------	---

<b>CATALOG NOTES</b>	Overload cycle for 60 s every 600 s
----------------------	-------------------------------------

## Features & Functions

### FEATURES

Parameterization:  
drivesConnect  
Parameterization:  
drivesConnect mobile  
(App)  
Parameterization: Fieldbus

Parameterization: Keypad

### FITTED WITH:

PC connection  
Radio interference  
suppression filter

### FITTED WITH:

PC connection  
Radio interference  
suppression filter

## General

### CABLE LENGTH

C2 ≤ 10 m, Radio  
interference level,  
maximum motor cable  
length  
C1 ≤ 5 m, Radio  
interference level,  
maximum motor cable  
length  
C3 ≤ 25 m, Radio  
interference level,  
maximum motor cable  
length

### COMMUNICATION INTERFACE

Modbus RTU, built in  
OP-Bus (RS485), built in

### CONNECTION TO SMARTWIRE-DT

In conjunction with DX-  
NET-SWD3 SmartWire DT  
module  
Yes

### DEGREE OF PROTECTION

IP20  
NEMA Other

### ELECTROMAGNETIC COMPATIBILITY

1st and 2nd environments  
(according to EN 61800-3)

### FRAME SIZE

FS2

### PRODUCT CATEGORY

Variable speed starter

### PROTECTION

Finger and back-of-hand  
proof, Protection against  
direct contact (BGV A3,  
VBG4)

### PROTOCOL

Other bus systems  
EtherNet/IP  
MODBUS

### RADIO INTERFERENCE CLASS

C1: for conducted  
emissions only  
C2, C3: depending on the  
motor cable length, the  
connected load, and  
ambient conditions.  
External radio interference  
suppression filters  
(optional) may be  
necessary.  
Optional external radio  
interference suppression  
filter for longer motor  
cable lengths and for use  
in different EMC  
environments

### SHOCK RESISTANCE

15 g, Mechanical,  
According to IEC/EN  
60068-2-27, 11 ms

## Climatic environmental conditions

<b>ALTITUDE</b>	Max. 2000 m Above 1000 m with 1 % derating per 100 m
<b>AMBIENT OPERATING TEMPERATURE - MIN</b>	-10 °C
<b>AMBIENT OPERATING TEMPERATURE - MAX</b>	60 °C
<b>AMBIENT OPERATING TEMPERATURE AT 150% OVERLOAD - MIN</b>	-10 °C
<b>AMBIENT OPERATING TEMPERATURE AT 150% OVERLOAD - MAX</b>	60 °C
<b>AMBIENT STORAGE TEMPERATURE - MIN</b>	-40 °C
<b>AMBIENT STORAGE TEMPERATURE - MAX</b>	70 °C
<b>CLIMATIC PROOFING</b>	< 95 average relative humidity (RH), no condensation, no corrosion

<b>SUITABLE FOR</b>	Branch circuits, (UL/CSA)
<b>VIBRATION</b>	Resistance: According to EN 61800-5-1

## Main circuit

<b>INPUT CURRENT ILN AT 150% OVERLOAD</b>	23.2 A
<b>LEAKAGE CURRENT AT GROUND IPE - MAX</b>	< 3.5 mA (AC-operated) < 10 mA (DC-operated)
<b>MAINS SWITCH-ON FREQUENCY</b>	Maximum of one time every 30 seconds
<b>MAINS VOLTAGE - MIN</b>	200 V
<b>MAINS VOLTAGE - MAX</b>	240 V
<b>OPERATING MODE</b>	Speed control with slip compensation U/f control
<b>OUTPUT FREQUENCY - MIN</b>	0 Hz
<b>OUTPUT FREQUENCY - MAX</b>	300 Hz
<b>OUTPUT VOLTAGE (U2)</b>	240 V AC, 3-phase 230 V AC, 3-phase
<b>OVERLOAD CURRENT IL AT 150% OVERLOAD</b>	14.4 A
<b>RATED CONTROL SUPPLY VOLTAGE</b>	10 V DC (Us, max. 0.2 mA)
<b>RATED FREQUENCY - MIN</b>	45 Hz
<b>RATED FREQUENCY - MAX</b>	66 Hz
<b>RATED OPERATIONAL CURRENT (IE)</b>	9.6 A at 150% overload (at an operating frequency of 16 kHz and an ambient air temperature of +50 °C)
<b>RATED OPERATIONAL VOLTAGE</b>	230 V AC, 1-phase 240 V AC, 1-phase
<b>RESOLUTION</b>	0.025 Hz (Frequency resolution, setpoint value)
<b>SHORT-CIRCUIT PROTECTION RATING</b>	35 A, UL (Class CC or J), Safety device (fuse or miniature circuit-breaker), Power Wiring
<b>STARTING CURRENT - MAX</b>	200 %, IH, max. starting current (High Overload), For 1.875 seconds every 600 seconds, Power section
<b>SUPPLY FREQUENCY</b>	50/60 Hz

## Motor rating

**ASSIGNED MOTOR  
CURRENT IM AT 220 - 240  
V, 60 HZ, 150%  
OVERLOAD** 9.6 A

**ASSIGNED MOTOR  
CURRENT IM AT 230 V, 50  
HZ, 150% OVERLOAD** 8.7 A

## Braking function

**BRAKING TORQUE** Adjustable to 100 %, DC -  
Main circuit  
Max. 30 % MN, Standard -  
Main circuit

### SWITCHING FREQUENCY

16 kHz, 4 - 32 kHz  
adjustable (audible),  
fPWM, Power section,  
Main circuit

### VOLTAGE RATING - MAX

240 V

## Apparent power

**APPARENT POWER AT  
230 V** 3.82 kVA

**APPARENT POWER AT  
240 V** 3.99 kVA

## Control circuit

**NUMBER OF INPUTS  
(ANALOG)** 1 (parameterizable, 0 - 10  
V DC, 0/4 - 20 mA)

**NUMBER OF INPUTS  
(DIGITAL)** 4 (parameterizable, 10 - 30  
V DC)

**NUMBER OF OUTPUTS  
(ANALOG)** 0

**NUMBER OF OUTPUTS  
(DIGITAL)** 0

**NUMBER OF RELAY  
OUTPUTS** 1 (parameterizable, N/O, 6  
A (250 V, AC-1) / 5 A (30 V,  
DC-1))

## Design verification

**EQUIPMENT HEAT DISSIPATION, CURRENT-DEPENDENT PVID** 105 W

**HEAT DISSIPATION CAPACITY PDISS** 0 W

**HEAT DISSIPATION PER POLE, CURRENT-DEPENDENT PVID** 0 W

**RATED OPERATIONAL CURRENT FOR SPECIFIED HEAT DISSIPATION (IN)** 9.6 A

**STATIC HEAT DISSIPATION, NON-CURRENT-DEPENDENT PVS** 0 W

**10.2.2 CORROSION RESISTANCE** Meets the product standard's requirements.

**10.2.3.1 VERIFICATION OF THERMAL STABILITY OF ENCLOSURES** Meets the product standard's requirements.

**10.2.3.2 VERIFICATION OF RESISTANCE OF INSULATING MATERIALS TO NORMAL HEAT** Meets the product standard's requirements.

**10.2.3.3 RESIST. OF INSUL. MAT. TO ABNORMAL HEAT/FIRE BY INTERNAL ELECT. EFFECTS** Meets the product standard's requirements.

**10.2.4 RESISTANCE TO ULTRA-VIOLET (UV) RADIATION** Meets the product standard's requirements.

**10.2.5 LIFTING** Does not apply, since the entire switchgear needs to be evaluated.

**10.2.6 MECHANICAL IMPACT** Does not apply, since the entire switchgear needs to be evaluated.

**10.2.7 INSCRIPTIONS** Meets the product standard's requirements.

**10.3 DEGREE OF PROTECTION OF ASSEMBLIES** Does not apply, since the entire switchgear needs to be evaluated.

**10.4 CLEARANCES AND CREEPAGE DISTANCES** Meets the product standard's requirements.

**10.5 PROTECTION AGAINST ELECTRIC SHOCK** Does not apply, since the entire switchgear needs to be evaluated.

## Resources

[How does the internal motor protection work?](#)

[Electromagnetic compatibility \(EMC\)](#)

[eaton-powerxl-de1-accesslevel2-parameterlock-ap040020-en-us.pdf](#)

[eaton-powerxl-de1-motor-vf-curves-ap040017-en-us.pdf](#)

[eaton-powerxl-de1-io-configuration-ap040036-en-us.pdf](#)

[eaton-powerxl-de1-starting-stopping-operation-ap040029-en-us.pdf](#)

[eaton-powerxl-de1-setpoint-setting-ap040042-en-us.pdf](#)

[eaton-powerxl-dx-com-stick-3-ap040190-en-us.pdf](#)

[eaton-powerxl-vfd-dual-rating-ap040114-en-us.pdf](#)

[The OP System Bus - Parameterizing - Control](#)

[eaton-powerxl-de1-fire-mode-ap040181-en-us.pdf](#)

[eaton-powerxl-da1-dc1-de1-conformal-coating-ap040182-en-us.pdf](#)

[eaton-powerxl-da1-dc1-db1-de1-rapidlink5-firmware-update-ap040214-en-us.pdf](#)

[eaton-powerxl-da1-dc1-de1-system-bus-ap040022-en-us.pdf](#)

[eaton-powerxl-da1-dc1-de1-internal-motor-protection-ap040016-en-us.pdf](#)

## APPLICATION NOTES

<b>10.6 INCORPORATION OF SWITCHING DEVICES AND COMPONENTS</b>	Does not apply, since the entire switchgear needs to be evaluated.
<b>10.7 INTERNAL ELECTRICAL CIRCUITS AND CONNECTIONS</b>	Is the panel builder's responsibility.
<b>10.8 CONNECTIONS FOR EXTERNAL CONDUCTORS</b>	Is the panel builder's responsibility.
<b>10.9.2 POWER-FREQUENCY ELECTRIC STRENGTH</b>	Is the panel builder's responsibility.
<b>10.9.3 IMPULSE WITHSTAND VOLTAGE</b>	Is the panel builder's responsibility.
<b>10.9.4 TESTING OF ENCLOSURES MADE OF INSULATING MATERIAL</b>	Is the panel builder's responsibility.
<b>10.10 TEMPERATURE RISE</b>	The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
<b>10.11 SHORT-CIRCUIT RATING</b>	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
<b>10.12 ELECTROMAGNETIC COMPATIBILITY</b>	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
<b>10.13 MECHANICAL FUNCTION</b>	The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

	<a href="#">Start, Stopp und Betrieb</a>
	<a href="#">DX-COM-STICK3 Connection</a>
<b>BROCHURES</b>	<a href="#">eaton-powerxl-de1-variable-speed-starter-brochure-br040003en-en-us.pdf</a> <a href="#">eaton-powerxl-variable-frequency-drives-hvac-brochure-br040012en-en-us.pdf</a>
<b>CATALOGUES</b>	<a href="#">Product Range Catalog Drives Engineering</a>
<b>DECLARATIONS OF CONFORMITY</b>	<a href="#">DA-DC-00004551.pdf</a> <a href="#">DA-DC-00004556.pdf</a>
<b>DRAWINGS</b>	<a href="#">eaton-frequency-inverter-dimensions-010.eps</a> <a href="#">eaton-frequency-inverter-3d-drawing-018.eps</a>
<b>ECAD MODEL</b>	<a href="#">DA-CE-ETN.DE1-129D6FN-N20N</a>
<b>INSTALLATION INSTRUCTIONS</b>	<a href="#">IL040005ZU</a>
<b>INSTALLATION VIDEOS</b>	<a href="#">PowerXL DE1 variable speed starter</a>
	<a href="#">eaton-de1-variable-speed-starter-manual-mn040011-hu-hu.pdf</a>
	<a href="#">eaton-de1-variable-speed-starter-manual-mn040011-en-us.pdf</a>
<b>MANUALS AND USER GUIDES</b>	<a href="#">MN040003_EN</a> <a href="#">MN040018_EN</a> <a href="#">eaton-canopen-communication-manual-for-variable-frequency-drives-variable-speed-starters-da1-db1-dc1-de11-mn040019-en-us.pdf</a>
<b>MCAD MODEL</b>	<a href="#">DA-CD-de1 fs2 ip20</a> <a href="#">DA-CS-de1 fs2 ip20</a>
<b>PRODUCT NOTIFICATIONS</b>	<a href="#">eaton-drives-ecodesign-directive-mz040046en-en.pdf</a>

**SOFTWARE, FIRMWARE,  
AND APPLICATIONS**

[eaton-powerxl-dc1-de1-  
swd-codesys-v3-library.zip](#)

[eaton-powerxl-de1-dc1-  
profinet-gsdml-v240.zip](#)

[eaton-powerxl-dx-cbl-pc-  
1m5-usb-driver.zip](#)

[eaton-powerxl-dx-  
comstick3-ble-drivers.zip](#)

[eaton-powerxl-dx-cbl-pc-  
3m0-usb-driver.zip](#)

[eaton-powerxl-de1-  
firmware-release-note-  
mz040043en-us.pdf](#)

[eaton-powerxl-de1-dc1-  
ethernetip-eds-v120.zip](#)

[eaton-powerxl-  
pcsoftware-drivesconnect-  
v1501.zip](#)

**PROJECT NAME:**

**PROJECT NUMBER:**

**PREPARED BY:**

**DATE:**



**Eaton Corporation plc**

Eaton House  
30 Pembroke Road  
Dublin 4, Ireland  
Eaton.com

© 2025 Eaton. All Rights Reserved.

Follow us on social media to get the latest product and support information.

