

# Specifications



## Eaton 197171

Eaton Moeller® series EMS2 Reversing starter, 230 V AC, 1,5 - 6,5 (AC-53a), 9 (AC-51) A, Screw terminals

### General specifications

<b>PRODUCT NAME</b>	Eaton Moeller® series EMS2 Reversing starter
<b>CATALOG NUMBER</b>	197171
<b>MODEL CODE</b>	EMS2-RO-Z-9-230VAC
<b>EAN</b>	4015080896128
<b>PRODUCT LENGTH/DEPTH</b>	114.5 mm
<b>PRODUCT HEIGHT</b>	99 mm
<b>PRODUCT WIDTH</b>	22.5 mm
<b>PRODUCT WEIGHT</b>	0.287 kg
<b>CERTIFICATIONS</b>	IEC/EN 60947-4-2 UL508 UL File No.: E29096 UL Category Control No.: NLDX, NLDX7 UL 60947-4-1 CSA-C22.2 No. 60947-4-1- 14 CE marking UL listed Certified by UL for use in Canada UL report applies to both US and Canada

## Features & Functions

FUNCTIONS	Temperature
	compensated overload
	protection
	Reversing start
	DOL starting
	Motor protection

## Climatic environmental conditions

AMBIENT OPERATING TEMPERATURE - MIN	-25 °C
--	--------

AMBIENT OPERATING TEMPERATURE - MAX	70 °C
--	-------

AMBIENT STORAGE TEMPERATURE - MIN	40 °C
--------------------------------------	-------

AMBIENT STORAGE TEMPERATURE - MAX	80 °C
--------------------------------------	-------

## General

CLASS	CLASS 10 A
-------	------------

CONNECTION TO SMARTWIRE-DT	No
-------------------------------	----

DEGREE OF PROTECTION	IP20 NEMA Other
----------------------	--------------------

MODEL	Reversing starter
-------	-------------------

MOUNTING METHOD	Top-hat rail fixing (according to IEC/EN 60715, 35 mm) Rail mounting possible
-----------------	--

MOUNTING POSITION	Motor feeder at bottom Vertical
-------------------	------------------------------------

OVERLOAD RELEASE CURRENT SETTING - MIN	1.5 A
---	-------

OVERLOAD RELEASE CURRENT SETTING - MAX	9 A
---	-----

PRODUCT CATEGORY	Electronic motor starter
------------------	--------------------------

TERMINAL CAPACITY	0.14 - 2.5 mm <sup>2</sup> , Control circuit cables 0.2 - 2.5 mm <sup>2</sup> , Main cables
-------------------	---

TERMINAL CAPACITY (AWG)	24 - 14, Main cables 26 - 14, Control circuit cables
----------------------------	--

TYPE	Reversing starter (complete device)
------	--

VOLTAGE TYPE	AC
--------------	----

## Electro magnetic compatibility

RADIO INTERFERENCE CLASS	Class A (EN 61000-6-3, emitted interference, radiated) EN 55011
-----------------------------	--

## Electrical rating

**RATED ACTUATING  
CURRENT (IC)** 7 mA

**RATED CONDITIONAL  
SHORT-CIRCUIT CURRENT  
(IQ), TYPE 2, 380 V, 400 V,  
415 V** 0 A

**RATED CONTROL SUPPLY  
CURRENT IS** 4 mA

**RATED CONTROL SUPPLY  
VOLTAGE** 85 - 253 V AC

**RATED CONTROL  
VOLTAGE (UC)** 230 V (Actuating circuit  
ON, L, R)

**RATED CONTROL SUPPLY  
VOLTAGE (US) AT AC, 50  
HZ - MIN** 230 V

**RATED CONTROL SUPPLY  
VOLTAGE (US) AT AC, 50  
HZ - MAX** 230 V

**RATED CONTROL SUPPLY  
VOLTAGE (US) AT AC, 60  
HZ - MIN** 0 V

**RATED CONTROL SUPPLY  
VOLTAGE (US) AT AC, 60  
HZ - MAX** 0 V

**RATED CONTROL SUPPLY  
VOLTAGE (US) AT DC -  
MIN** 0 V

**RATED CONTROL SUPPLY  
VOLTAGE (US) AT DC -  
MAX** 0 V

**RATED OPERATIONAL  
CURRENT (IE)** 9 A

**RATED OPERATIONAL  
CURRENT (IE) AT AC-15,  
220 V, 230 V, 240 V** 3 A

**RATED OPERATIONAL  
CURRENT (IE) AT AC-3,  
380 V, 400 V, 415 V** 6.5 A

**RATED OPERATIONAL  
CURRENT (IE) AT AC-51** 9 A

**RATED OPERATIONAL  
CURRENT (IE) AT AC-53A -  
MAX** 6.5 A

**RATED OPERATIONAL  
CURRENT (IE) AT DC-13,  
24 V** 2 A

**RATED OPERATIONAL  
POWER AT AC-3, 220/230** 1.5 kW

## Contacts

**NUMBER OF AUXILIARY  
CONTACTS (NORMALLY  
CLOSED CONTACTS)** 1

**NUMBER OF AUXILIARY  
CONTACTS (NORMALLY  
OPEN CONTACTS)** 1

**NUMBER OF CONTACTS  
(CHANGE-OVER  
CONTACTS)** 1

<b>V, 50 HZ</b>	
<b>RATED OPERATIONAL POWER AT AC-3, 380/400 V, 50 HZ</b>	3 kW
<b>RATED OPERATIONAL POWER AT AC-53A, 380/400 V, 50 HZ</b>	3 kW
<b>RATED OPERATIONAL VOLTAGE</b>	42 - 550 V 500 V AC
<b>SWITCHING LEVEL</b>	85 - 253 V AC, Switching level "High", Actuating circuit (ON, L, R) 0 - 44 V AC, Switching level "Low", Actuating circuit (ON, L, R)

## Design verification

**EQUIPMENT HEAT DISSIPATION, CURRENT-DEPENDENT PVID** 16.1 W

**HEAT DISSIPATION CAPACITY PDISS** 0 W

**HEAT DISSIPATION PER POLE, CURRENT-DEPENDENT PVID** 0 W

**RATED OPERATIONAL CURRENT FOR SPECIFIED HEAT DISSIPATION (IN)** 9 A

**STATIC HEAT DISSIPATION, NON-CURRENT-DEPENDENT PVS** 1 W

**HEAT DISSIPATION DETAILS** If necessary, Allow for derating

**10.2.2 CORROSION RESISTANCE** Meets the product standard's requirements.

**10.2.3.1 VERIFICATION OF THERMAL STABILITY OF ENCLOSURES** Meets the product standard's requirements.

**10.2.3.2 VERIFICATION OF RESISTANCE OF INSULATING MATERIALS TO NORMAL HEAT** Meets the product standard's requirements.

**10.2.3.3 RESIST. OF INSUL. MAT. TO ABNORMAL HEAT/FIRE BY INTERNAL ELECT. EFFECTS** Meets the product standard's requirements.

**10.2.4 RESISTANCE TO ULTRA-VIOLET (UV) RADIATION** Meets the product standard's requirements.

**10.2.5 LIFTING** Does not apply, since the entire switchgear needs to be evaluated.

**10.2.6 MECHANICAL IMPACT** Does not apply, since the entire switchgear needs to be evaluated.

**10.2.7 INSCRIPTIONS** Meets the product standard's requirements.

**10.3 DEGREE OF PROTECTION OF ASSEMBLIES** Does not apply, since the entire switchgear needs to be evaluated.

**10.4 CLEARANCES AND CREEPAGE DISTANCES** Meets the product standard's requirements.

**10.5 PROTECTION** Does not apply, since the

## Resources

**APPLICATION NOTES** [eaton-motor-starter-ems2-setting-motor-protection-twincat3-ap034001-en-us.pdf](#)

**BROCHURES** [eaton-ems2-electronic-motorstarter-brochure-br034001en-en-us.pdf](#)

[eaton-contactors-ems2-reversing-starter-characteristic-curve-002.eps](#)

**CHARACTERISTIC CURVE** [eaton-contactors-ems2-reversing-starter-characteristic-curve.eps](#)

[eaton-contactors-ems2-reversing-starter-characteristic-curve-004.eps](#)

**DECLARATIONS OF CONFORMITY** [DA-DC-00003980.pdf](#)  
[DA-DC-00004192.pdf](#)

[eaton-contactors-ems2-reversing-starter-dimensions-002.eps](#)

**DRAWINGS** [eaton-contactors-ems2-reversing-starter-3d-drawing-002.eps](#)

**ECAD MODEL** [DA-CE-ETN.EMS2-RO-Z-9-230VAC](#)

**INSTALLATION INSTRUCTIONS** [IL034064ZU](#)

**INSTALLATION VIDEOS** [Eaton's electronic motor starter EMS2](#)

**MANUALS AND USER GUIDES** [eaton-electronic-motor-starter-ems2-manual-mn034003en-us.pdf](#)

**MCAD MODEL** [DA-CD-ems2\\_dos\\_ros\\_z\\_24\\_230v](#)  
[DA-CS-ems2\\_dos\\_ros\\_z\\_24\\_230v](#)

**SALES NOTES** [eaton-ems2-electronic-motorstarter-flyer-fl034007en-en-us.pdf](#)

<b>AGAINST ELECTRIC SHOCK</b>	entire switchgear needs to be evaluated.
<b>10.6 INCORPORATION OF SWITCHING DEVICES AND COMPONENTS</b>	Does not apply, since the entire switchgear needs to be evaluated.
<b>10.7 INTERNAL ELECTRICAL CIRCUITS AND CONNECTIONS</b>	Is the panel builder's responsibility.
<b>10.8 CONNECTIONS FOR EXTERNAL CONDUCTORS</b>	Is the panel builder's responsibility.
<b>10.9.2 POWER-FREQUENCY ELECTRIC STRENGTH</b>	Is the panel builder's responsibility.
<b>10.9.3 IMPULSE WITHSTAND VOLTAGE</b>	Is the panel builder's responsibility.
<b>10.9.4 TESTING OF ENCLOSURES MADE OF INSULATING MATERIAL</b>	Is the panel builder's responsibility.
<b>10.10 TEMPERATURE RISE</b>	The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
<b>10.11 SHORT-CIRCUIT RATING</b>	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
<b>10.12 ELECTROMAGNETIC COMPATIBILITY</b>	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
<b>10.13 MECHANICAL FUNCTION</b>	The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

PROJECT NAME:
PROJECT NUMBER:
PREPARED BY:
DATE:



**Eaton Corporation plc**  
Eaton House  
30 Pembroke Road  
Dublin 4, Ireland  
Eaton.com

© 2025 Eaton. All Rights Reserved.

Follow us on social media to get the latest product and support information.

