

Specifications

Photo is representative

Eaton 198520

Eaton Moeller® series Rapid Link - DOL starter, 6.6 A, Sensor input 2, 230/277 V AC, AS-Interface®, S-7.4 for 31 modules, HAN Q5, with manual override switch

General specifications

PRODUCT NAME	Eaton Rapid Link DOL starter
CATALOG NUMBER	198520
EAN	4015081963959
PRODUCT LENGTH/DEPTH	120 mm
PRODUCT HEIGHT	270 mm
PRODUCT WIDTH	220 mm
PRODUCT WEIGHT	1.8 kg
CERTIFICATIONS	CCC CE RoHS UL 60947-4-2 UL approval IEC/EN 60947-4-2 UL 60947-4-2
CATALOG NOTES	Assigned motor rating: for normal internally and externally ventilated 4 pole, three-phase asynchronous motors with 1500 rpm at 50 Hz or 1800 min at 60 Hz
MODEL CODE	RAMO5-D202A31-512RS1

Features & Functions

FEATURES

Parameterization: Fieldbus

Parameterization: Keypad
Diagnostics and reset on device and via AS-Interface

Parameterization:
drivesConnect
Parameterization:
drivesConnect mobile
(App)

FITTED WITH:

Key switch position AUTO
Key switch position HAND
Manual override switch
Short-circuit release
Thermo-click
Electronic motor protection
Key switch position OFF/RESET
Thermistor monitoring PTC
Two sensor inputs through M12 sockets (max. 150 mA) for quick stop and interlocked manual operation

FUNCTIONS

External reset possible
For actuation of motors with mechanical brake
Temperature compensated overload protection

General

CLASS CLASS 10 A

DEGREE OF PROTECTION IP65
NEMA 12

ELECTROMAGNETIC COMPATIBILITY Class A

LIFESPAN, ELECTRICAL 10,000,000 Operations (at AC-3)

LIFESPAN, MECHANICAL 10,000,000 Operations (at AC-3)

MODEL Direct starter

OVERLOAD RELEASE CURRENT SETTING - MIN 0.3 A

OVERLOAD RELEASE CURRENT SETTING - MAX 6.6 A

OVERVOLTAGE CATEGORY III

PRODUCT CATEGORY Motor starter

PROTOCOL AS-Interface profile cable: S-7.4 for 31 modules
ASI

RATED IMPULSE WITHSTAND VOLTAGE (UIMP) 4000 V

SYSTEM CONFIGURATION TYPE Phase-earthed AC supply systems are not permitted.
AC voltage
Center-point earthed star network (TN-S network)

TYPE DOL starter

VOLTAGE TYPE DC

Ambient conditions, mechanical

MOUNTING POSITION	Vertical
SHOCK RESISTANCE	15 g, Mechanical, According to IEC/EN 60068-2-27, 11 ms, Half- sinusoidal shock 11 ms, 1000 shocks per shaft
VIBRATION	Resistance: 10 - 150 Hz, Oscillation frequency Resistance: According to IEC/EN 60068-2-6 Resistance: 6 Hz, Amplitude 0.15 mm Resistance: 57 Hz, Amplitude transition frequency on acceleration

Climatic environmental conditions

ALTITUDE	Max. 2000 m Above 1000 m with 1 % performance reduction per 100 m Max. 1000 m
AMBIENT OPERATING TEMPERATURE - MIN	-10 °C
AMBIENT OPERATING TEMPERATURE - MAX	55 °C
AMBIENT STORAGE TEMPERATURE - MIN	-40 °C
AMBIENT STORAGE TEMPERATURE - MAX	70 °C
CLIMATIC PROOFING	In accordance with IEC/EN 50178 < 95 %, no condensation

Main circuit

CURRENT LIMITATION	0.3 - 6.6 A, motor, main circuit Adjustable, motor, main circuit
INPUT CURRENT	6.6 A (at 150 % Overload)
MAINS SWITCH-ON FREQUENCY	Maximum of one time every 60 seconds
MAINS VOLTAGE TOLERANCE	380 - 480 V (-15 %/+10 %, at 50/60 Hz)
OFF-DELAY	20 - 35 ms
ON-DELAY	20 - 35 ms
OUTPUT FREQUENCY	50/60 Hz
OVERLOAD CYCLE	AC-53a
RATED FREQUENCY - MIN	47 Hz
RATED FREQUENCY - MAX	63 Hz
RATED OPERATIONAL CURRENT (IE)	6.6 A
RATED OPERATIONAL CURRENT (IE) AT 150% OVERLOAD	6.6 A
RATED OPERATIONAL CURRENT (IE) AT AC-3, 380 V, 400 V, 415 V	6.6 A
RATED OPERATIONAL POWER AT 380/400 V, 50 HZ - MIN	0.09 kW
RATED OPERATIONAL POWER AT 380/400 V, 50 HZ - MAX	3 kW
RATED OPERATIONAL POWER AT AC-3, 220/230 V, 50 HZ	0 kW
RATED OPERATIONAL POWER AT AC-3, 380/400 V, 50 HZ	3 kW
RATED OPERATIONAL VOLTAGE	480 V AC, 3-phase 400 V AC, 3-phase
SUPPLY FREQUENCY	50/60 Hz, fLN, Main circuit
SYSTEM CONFIGURATION TYPE	Phase-earthed AC supply systems are not permitted. AC voltage Center-point earthed star network (TN-S network)

Motor rating

ASSIGNED MOTOR

POWER AT 460/480 V, 60 HZ, 3-PHASE 3 HP

Braking function

BRAKING CURRENT	≤ 0.6 A (max. 6 A for 120 ms), Actuator for external motor brake
BRAKING VOLTAGE	230/277 V AC -15 % / +10 %, Actuator for external motor brake

Control circuit

RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 50 HZ - MIN	0 V
---	-----

RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 50 HZ - MAX	0 V
---	-----

RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 60 HZ - MIN	0 V
---	-----

RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 60 HZ - MAX	0 V
---	-----

RATED CONTROL SUPPLY VOLTAGE (US) AT DC - MIN	0 V
--	-----

RATED CONTROL SUPPLY VOLTAGE (US) AT DC - MAX	0 V
--	-----

RATED CONTROL VOLTAGE (UC)	24 V DC (-15 %/+20 %, external via AS-Interface® plug) 230/277 V AC (external brake 50/60 Hz)
-----------------------------------	--

Contacts

NUMBER OF AUXILIARY CONTACTS (NORMALLY CLOSED CONTACTS)	0
--	---

NUMBER OF AUXILIARY CONTACTS (NORMALLY OPEN CONTACTS)	0
--	---

Short-circuit rating

RATED CONDITIONAL SHORT-CIRCUIT CURRENT (IQ)	10 kA
---	-------

RATED CONDITIONAL SHORT-CIRCUIT CURRENT (IQ), TYPE 2, 380 V, 400 V, 415 V	0 A
--	-----

SHORT-CIRCUIT PROTECTION (EXTERNAL OUTPUT CIRCUITS)	Type 1 coordination via the power bus' feeder unit, Main circuit
--	--

Communication

CONNECTION	Connections pluggable in power section
-------------------	--

INTERFACES	Specification: S-7.4 (AS-Interface®) Number of slave addresses: 31 (AS-Interface®) Max. total power consumption from AS-Interface® power supply unit (30 V): 190 mA
-------------------	---

Cable

CABLE LENGTH	10 m, Radio interference level, maximum motor cable length
---------------------	--

Design verification

10.2.2 CORROSION RESISTANCE Meets the product standard's requirements.

10.2.3.1 VERIFICATION OF THERMAL STABILITY OF ENCLOSURES Meets the product standard's requirements.

10.2.3.2 VERIFICATION OF RESISTANCE OF INSULATING MATERIALS TO NORMAL HEAT Meets the product standard's requirements.

10.2.3.3 RESIST. OF INSUL. MAT. TO ABNORMAL HEAT/FIRE BY INTERNAL ELECT. EFFECTS Meets the product standard's requirements.

10.2.4 RESISTANCE TO ULTRA-VIOLET (UV) RADIATION Meets the product standard's requirements.

10.2.5 LIFTING Does not apply, since the entire switchgear needs to be evaluated.

10.2.6 MECHANICAL IMPACT Does not apply, since the entire switchgear needs to be evaluated.

10.2.7 INSCRIPTIONS Meets the product standard's requirements.

10.3 DEGREE OF PROTECTION OF ASSEMBLIES Does not apply, since the entire switchgear needs to be evaluated.

10.4 CLEARANCES AND CREEPAGE DISTANCES Meets the product standard's requirements.

10.5 PROTECTION AGAINST ELECTRIC SHOCK Does not apply, since the entire switchgear needs to be evaluated.

10.6 INCORPORATION OF SWITCHING DEVICES AND COMPONENTS Does not apply, since the entire switchgear needs to be evaluated.

10.7 INTERNAL ELECTRICAL CIRCUITS AND CONNECTIONS Is the panel builder's responsibility.

10.8 CONNECTIONS FOR EXTERNAL CONDUCTORS Is the panel builder's responsibility.

10.9.2 POWER-FREQUENCY ELECTRIC STRENGTH Is the panel builder's responsibility.

10.9.3 IMPULSE WITHSTAND VOLTAGE Is the panel builder's responsibility.

10.9.4 TESTING OF ENCLOSURES MADE OF Is the panel builder's responsibility.

Resources

[eaton-powerxl-dx-com-stick-3-ap040190-en-us.pdf](#)

[eaton-rapid-link-generation-change-rasp4-to-rasp5-ap040197-en-us.pdf](#)

[eaton-rapid-link-5-configuration-rockwell-plc-ap040195-en-us.pdf](#)

[Electromagnetic compatibility \(EMC\)](#)

[eaton-rapid-link-firmware-update-rasp4-ap040219-en-us.pdf](#)

[eaton-powerxl-da1-dc1-db1-de1-rapidlink5-firmware-update-ap040214-en-us.pdf](#)

[eaton-rapid-link-generation-change-ra-sp-to-rasp4-ap040080-en-us.pdf](#)

[eaton-powerxl-da1-dc1-de1-internal-motor-protection-ap040016-en-us.pdf](#)

[eaton-rapid-link-generation-change-ra-mo-to-ramo4-ap040081-en-us.pdf](#)

[eaton-rapid-link-generation-change-ra-sp-to-rasp5-ap040196-en-us.pdf](#)

[eaton-rapid-link-generation-change-ramo4-to-ramo5-ap040198-en-us.pdf](#)

[eaton-rapid-link-5-rasp5-profinet-communication-ap040215-en-us.pdf](#)

[eaton-rapid-link-5-brochure-br040014en-en-us.pdf](#)

APPLICATION NOTES

BROCHURES

INSULATING MATERIAL	
10.10 TEMPERATURE RISE	The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 SHORT-CIRCUIT RATING	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.12 ELECTROMAGNETIC COMPATIBILITY	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.13 MECHANICAL FUNCTION	The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

	eaton-powerxl-variable-frequency-drives-material-handling-brochure-br040017en-en-us.pdf
CATALOGUES	eaton-rapid-link-5-drive-system-catalog-ca040002en-en-us Product Range Catalog Drives Engineering
DECLARATIONS OF CONFORMITY	DA-DC-00003964.pdf DA-DC-00004523.pdf DA-DC-00004184.pdf DA-DC-00004525.pdf
DRAWINGS	eaton-bus-adapter-rapidlink-reversing-starter-dimensions-002.eps eaton-bus-adapter-rapidlink-reversing-starter-dimensions-003.eps
ECAD MODEL	ETN.RAMO5-D202A31-512RS1.edz
INSTALLATION INSTRUCTIONS	IL034084ZU
INSTALLATION VIDEOS	Rapid Link 5
MANUALS AND USER GUIDES	eaton-rapid-link-5-mn034004en-us.pdf
MCAD MODEL	ramo5_v4.dwg ramo5_v4.stp
SOFTWARE, FIRMWARE, AND APPLICATIONS	eaton-rapidlink5-firmware-release-note-mz034006en-us.pdf

PROJECT NAME:
PROJECT NUMBER:
PREPARED BY:
DATE:



Eaton Corporation plc
Eaton House
30 Pembroke Road
Dublin 4, Ireland
Eaton.com

Follow us on social media to get the latest product and support information.



© 2025 Eaton. All Rights Reserved.