

# Specifications

Photo is representative

## Eaton 199112

Eaton Moeller® series Rapid Link - Reversing starter, 6.6 A, Sensor input 2, 400/480 V AC, AS-Interface®, S-7.A.E. for 62 modules, HAN Q4/2, with manual override switch

### General specifications

<b>PRODUCT NAME</b>	Eaton Rapid Link Reversing starter
<b>CATALOG NUMBER</b>	199112
<b>EAN</b>	4015081971701
<b>PRODUCT LENGTH/DEPTH</b>	120 mm
<b>PRODUCT HEIGHT</b>	270 mm
<b>PRODUCT WIDTH</b>	220 mm
<b>PRODUCT WEIGHT</b>	1.8 kg
<b>CERTIFICATIONS</b>	RoHS UL approval UL 60947-4-2 CCC CE IEC/EN 60947-4-2 UL 60947-4-2
<b>CATALOG NOTES</b>	Assigned motor rating: for normal internally and externally ventilated 4 pole, three-phase asynchronous motors with 1500 rpm at 50 Hz or 1800 min at 60 Hz
<b>MODEL CODE</b>	RAMO5-W204A32-412RS1

## Features & Functions

### FEATURES

Parameterization:  
drivesConnect  
Parameterization:  
drivesConnect mobile  
(App)  
Parameterization: Keypad  
Diagnostics and reset on  
device and via AS-Interface

Parameterization: Fieldbus

### FITTED WITH:

Key switch position AUTO  
Two sensor inputs through  
M12 sockets (max. 150  
mA) for quick stop and  
interlocked manual  
operation  
Thermistor monitoring  
PTC  
Thermo-click  
Manual override switch  
Key switch position  
OFF/RESET  
Electronic motor  
protection  
Key switch position HAND  
Short-circuit release

### FUNCTIONS

For actuation of motors  
with mechanical brake  
External reset possible  
Temperature  
compensated overload  
protection

## General

**CLASS** CLASS 10 A

**DEGREE OF PROTECTION** NEMA 12  
IP65

**ELECTROMAGNETIC  
COMPATIBILITY** Class A

**LIFESPAN, ELECTRICAL** 10,000,000 Operations (at  
AC-3)

**LIFESPAN, MECHANICAL** 10,000,000 Operations (at  
AC-3)

**MODEL** Reversing starter

**OVERLOAD RELEASE  
CURRENT SETTING - MIN** 0.3 A

**OVERLOAD RELEASE  
CURRENT SETTING - MAX** 6.6 A

**OVERVOLTAGE  
CATEGORY** III

**PRODUCT CATEGORY** Motor starter

**PROTOCOL** AS-Interface profile cable:  
S-7.4 for 62 modules  
ASI

**RATED IMPULSE  
WITHSTAND VOLTAGE  
(UIMP)** 4000 V

**SYSTEM  
CONFIGURATION TYPE** Center-point earthed star  
network (TN-S network)  
Phase-earthed AC supply  
systems are not  
permitted.  
AC voltage

**TYPE** Reversing starter

**VOLTAGE TYPE** DC

## Ambient conditions, mechanical

<b>MOUNTING POSITION</b>	Vertical
<b>SHOCK RESISTANCE</b>	15 g, Mechanical, According to IEC/EN 60068-2-27, 11 ms, Half- sinusoidal shock 11 ms, 1000 shocks per shaft
<b>VIBRATION</b>	Resistance: 10 - 150 Hz, Oscillation frequency Resistance: 6 Hz, Amplitude 0.15 mm Resistance: According to IEC/EN 60068-2-6 Resistance: 57 Hz, Amplitude transition frequency on acceleration

## Climatic environmental conditions

<b>ALTITUDE</b>	Max. 2000 m Above 1000 m with 1 % performance reduction per 100 m Max. 1000 m
<b>AMBIENT OPERATING TEMPERATURE - MIN</b>	-10 °C
<b>AMBIENT OPERATING TEMPERATURE - MAX</b>	55 °C
<b>AMBIENT STORAGE TEMPERATURE - MIN</b>	-40 °C
<b>AMBIENT STORAGE TEMPERATURE - MAX</b>	70 °C
<b>CLIMATIC PROOFING</b>	< 95 %, no condensation In accordance with IEC/EN 50178

## Main circuit

<b>CURRENT LIMITATION</b>	0.3 - 6.6 A, motor, main circuit Adjustable, motor, main circuit
<b>INPUT CURRENT</b>	6.6 A (at 150 % Overload)
<b>MAINS SWITCH-ON FREQUENCY</b>	Maximum of one time every 60 seconds
<b>MAINS VOLTAGE TOLERANCE</b>	380 - 480 V (-15 %/+10 %, at 50/60 Hz)
<b>OFF-DELAY</b>	20 - 35 ms
<b>ON-DELAY</b>	20 - 35 ms
<b>OUTPUT FREQUENCY</b>	50/60 Hz
<b>OVERLOAD CYCLE</b>	AC-53a
<b>RATED FREQUENCY - MIN</b>	47 Hz
<b>RATED FREQUENCY - MAX</b>	63 Hz
<b>RATED OPERATIONAL CURRENT (IE)</b>	6.6 A
<b>RATED OPERATIONAL CURRENT (IE) AT 150% OVERLOAD</b>	6.6 A
<b>RATED OPERATIONAL CURRENT (IE) AT AC-3, 380 V, 400 V, 415 V</b>	6.6 A
<b>RATED OPERATIONAL POWER AT 380/400 V, 50 HZ - MIN</b>	0.09 kW
<b>RATED OPERATIONAL POWER AT 380/400 V, 50 HZ - MAX</b>	3 kW
<b>RATED OPERATIONAL POWER AT AC-3, 220/230 V, 50 HZ</b>	0 kW
<b>RATED OPERATIONAL POWER AT AC-3, 380/400 V, 50 HZ</b>	3 kW
<b>RATED OPERATIONAL VOLTAGE</b>	400 V AC, 3-phase 480 V AC, 3-phase
<b>SUPPLY FREQUENCY</b>	50/60 Hz, fLN, Main circuit
<b>SYSTEM CONFIGURATION TYPE</b>	Center-point earthed star network (TN-S network) Phase-earthed AC supply systems are not permitted. AC voltage

## Motor rating

### ASSIGNED MOTOR

**POWER AT 460/480 V, 60** 3 HP

**HZ, 3-PHASE**

## Braking function

<b>BRAKING CURRENT</b>	≤ 0.6 A (max. 6 A for 120 ms), Actuator for external motor brake
<b>BRAKING VOLTAGE</b>	400/480 V AC -15 % / +10 %, Actuator for external motor brake

## Control circuit

<b>RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 50 HZ - MIN</b>	0 V
-------------------------------------------------------------	-----

<b>RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 50 HZ - MAX</b>	0 V
-------------------------------------------------------------	-----

<b>RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 60 HZ - MIN</b>	0 V
-------------------------------------------------------------	-----

<b>RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 60 HZ - MAX</b>	0 V
-------------------------------------------------------------	-----

<b>RATED CONTROL SUPPLY VOLTAGE (US) AT DC - MIN</b>	0 V
------------------------------------------------------	-----

<b>RATED CONTROL SUPPLY VOLTAGE (US) AT DC - MAX</b>	0 V
------------------------------------------------------	-----

<b>RATED CONTROL VOLTAGE (UC)</b>	24 V DC (-15 %/+20 %, external via AS-Interface® plug) 400/480 V AC (external brake 50/60 Hz)
-----------------------------------	--------------------------------------------------------------------------------------------------

## Contacts

<b>NUMBER OF AUXILIARY CONTACTS (NORMALLY CLOSED CONTACTS)</b>	0
----------------------------------------------------------------	---

<b>NUMBER OF AUXILIARY CONTACTS (NORMALLY OPEN CONTACTS)</b>	0
--------------------------------------------------------------	---

## Short-circuit rating

<b>RATED CONDITIONAL SHORT-CIRCUIT CURRENT (IQ)</b>	10 kA
-----------------------------------------------------	-------

<b>RATED CONDITIONAL SHORT-CIRCUIT CURRENT (IQ), TYPE 2, 380 V, 400 V, 415 V</b>	0 A
----------------------------------------------------------------------------------	-----

<b>SHORT-CIRCUIT PROTECTION (EXTERNAL OUTPUT CIRCUITS)</b>	Type 1 coordination via the power bus' feeder unit, Main circuit
------------------------------------------------------------	------------------------------------------------------------------

## Communication

<b>CONNECTION</b>	Connections pluggable in power section
-------------------	----------------------------------------

<b>INTERFACES</b>	Specification: S-7.A.E. (AS-Interface®) Number of slave addresses: 62 (AS-Interface®) Max. total power consumption from AS-Interface® power supply unit (30 V): 190 mA
-------------------	------------------------------------------------------------------------------------------------------------------------------------------------------------------------------

## Cable

<b>CABLE LENGTH</b>	10 m, Radio interference level, maximum motor cable length
---------------------	------------------------------------------------------------

## Design verification

**10.2.2 CORROSION RESISTANCE** Meets the product standard's requirements.

**10.2.3.1 VERIFICATION OF THERMAL STABILITY OF ENCLOSURES** Meets the product standard's requirements.

**10.2.3.2 VERIFICATION OF RESISTANCE OF INSULATING MATERIALS TO NORMAL HEAT** Meets the product standard's requirements.

**10.2.3.3 RESIST. OF INSUL. MAT. TO ABNORMAL HEAT/FIRE BY INTERNAL ELECT. EFFECTS** Meets the product standard's requirements.

**10.2.4 RESISTANCE TO ULTRA-VIOLET (UV) RADIATION** Meets the product standard's requirements.

**10.2.5 LIFTING** Does not apply, since the entire switchgear needs to be evaluated.

**10.2.6 MECHANICAL IMPACT** Does not apply, since the entire switchgear needs to be evaluated.

**10.2.7 INSCRIPTIONS** Meets the product standard's requirements.

**10.3 DEGREE OF PROTECTION OF ASSEMBLIES** Does not apply, since the entire switchgear needs to be evaluated.

**10.4 CLEARANCES AND CREEPAGE DISTANCES** Meets the product standard's requirements.

**10.5 PROTECTION AGAINST ELECTRIC SHOCK** Does not apply, since the entire switchgear needs to be evaluated.

**10.6 INCORPORATION OF SWITCHING DEVICES AND COMPONENTS** Does not apply, since the entire switchgear needs to be evaluated.

**10.7 INTERNAL ELECTRICAL CIRCUITS AND CONNECTIONS** Is the panel builder's responsibility.

**10.8 CONNECTIONS FOR EXTERNAL CONDUCTORS** Is the panel builder's responsibility.

**10.9.2 POWER-FREQUENCY ELECTRIC STRENGTH** Is the panel builder's responsibility.

**10.9.3 IMPULSE WITHSTAND VOLTAGE** Is the panel builder's responsibility.

**10.9.4 TESTING OF ENCLOSURES MADE OF** Is the panel builder's responsibility.

## Resources

[eaton-rapid-link-generation-change-ramo4-to-ramo5-ap040198-en-us.pdf](#)

[eaton-rapid-link-5-rasp5-profinet-communication-ap040215-en-us.pdf](#)

[eaton-powerxl-dx-com-stick-3-ap040190-en-us.pdf](#)

[eaton-rapid-link-generation-change-rasp4-to-rasp5-ap040197-en-us.pdf](#)

[Electromagnetic compatibility \(EMC\)](#)

[eaton-rapid-link-5-configuration-rockwell-plc-ap040195-en-us.pdf](#)

[eaton-rapid-link-firmware-update-rasp4-ap040219-en-us.pdf](#)

[eaton-powerxl-da1-dc1-db1-de1-rapidlink5-firmware-update-ap040214-en-us.pdf](#)

[eaton-rapid-link-generation-change-ra-sp-to-rasp4-ap040080-en-us.pdf](#)

[eaton-powerxl-da1-dc1-de1-internal-motor-protection-ap040016-en-us.pdf](#)

[eaton-rapid-link-generation-change-ra-mo-to-ramo4-ap040081-en-us.pdf](#)

[eaton-rapid-link-generation-change-ra-sp-to-rasp5-ap040196-en-us.pdf](#)

[eaton-rapid-link-5-brochure-br040014en-en-us.pdf](#)

## APPLICATION NOTES

## BROCHURES

## INSULATING MATERIAL

### 10.10 TEMPERATURE RISE

The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.

### 10.11 SHORT-CIRCUIT RATING

Is the panel builder's responsibility. The specifications for the switchgear must be observed.

### 10.12 ELECTROMAGNETIC COMPATIBILITY

Is the panel builder's responsibility. The specifications for the switchgear must be observed.

### 10.13 MECHANICAL FUNCTION

The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

[eaton-powerxl-variable-frequency-drives-material-handling-brochure-br040017en-en-us.pdf](#)

## CATALOGUES

[eaton-rapid-link-5-drive-system-catalog-ca040002en-en-us](#)

[Product Range Catalog Drives Engineering](#)

## DECLARATIONS OF CONFORMITY

[DA-DC-00003964.pdf](#)

[DA-DC-00004523.pdf](#)

[DA-DC-00004184.pdf](#)

[DA-DC-00004525.pdf](#)

## DRAWINGS

[eaton-bus-adapter-rapidlink-reversing-starter-dimensions-002.eps](#)

[eaton-bus-adapter-rapidlink-reversing-starter-dimensions-003.eps](#)

## ECAD MODEL

[ETN.RAMO5-W204A32-412RS1.edz](#)

## INSTALLATION INSTRUCTIONS

[IL034084ZU](#)

## INSTALLATION VIDEOS

[Rapid Link 5](#)

## MCAD MODEL

[ramo5\\_v11.dwg](#)

[ramo5\\_v11.stp](#)

## SOFTWARE, FIRMWARE, AND APPLICATIONS

[eaton-rapidlink5-firmware-release-note-mz034006en-us.pdf](#)

PROJECT NAME:

PROJECT NUMBER:

PREPARED BY:

DATE:



### Eaton Corporation plc

Eaton House  
30 Pembroke Road  
Dublin 4, Ireland  
Eaton.com

© 2025 Eaton. All Rights Reserved.

Follow us on social media to get the latest product and support information.

