

Specifications



Photo is representative

Eaton 284400

Eaton Moeller series NZM Undervoltage release, 208-240VAC +2early N/O, for NZM1

General specifications

PRODUCT NAME	Eaton Moeller series NZM Undervoltage release
CATALOG NUMBER	284400
MODEL CODE	NZM1-XUHV20KL208-240AC
EAN	4015082844004
PRODUCT LENGTH/DEPTH	37 mm
PRODUCT HEIGHT	66 mm
PRODUCT WIDTH	32 mm
PRODUCT WEIGHT	0.056 kg
WARRANTY	Eaton Selling Policy 25-000, one (1) year from the date of installation of the Product or eighteen (18) months from the date of shipment of the Product, whichever occurs first.
COMPLIANCES	UL/CSA IEC RoHS conform
CERTIFICATIONS	IEC60947 CSA (Class No. 1437-01) UL489 UL listed UL (Category Control Number DIHS) CSA-C22.2 No. 5-09 CSA (File No. 22086) UL (File No. E140305) CE marking CSA certified
GLOBAL CATALOG	284400

Product specifications

USED WITH	NZM1(-4), N(S)1(-4)
10.10 TEMPERATURE RISE	The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 SHORT-CIRCUIT RATING	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.12 ELECTROMAGNETIC COMPATIBILITY	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.13 MECHANICAL FUNCTION	The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.
10.2.2 CORROSION RESISTANCE	Meets the product standard's requirements.
10.2.3.1 VERIFICATION OF THERMAL STABILITY OF ENCLOSURES	Meets the product standard's requirements.
10.2.3.2 VERIFICATION OF RESISTANCE OF INSULATING MATERIALS TO NORMAL HEAT	Meets the product standard's requirements.
10.2.3.3 RESIST. OF INSUL. MAT. TO ABNORMAL HEAT/FIRE BY INTERNAL ELECT. EFFECTS	Meets the product standard's requirements.
10.2.4 RESISTANCE TO ULTRA-VIOLET (UV) RADIATION	Meets the product standard's requirements.
10.2.5 LIFTING	Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 MECHANICAL IMPACT	Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 INSCRIPTIONS	Meets the product standard's requirements.
10.3 DEGREE OF PROTECTION OF	Does not apply, since the entire switchgear needs to

Resources

BROCHURES

[eaton-digital-nzm-brochure-br013003en-en-us.pdf](#)

[eaton-feerum-the-whole-grain-solution-success-story-en-us.pdf](#)

CATALOGS

[eaton-digital-nzm-catalog-ca013003en-en-us.pdf](#)

[eaton-circuit-breaker-release-nzm-mccb-dimensions.eps](#)

DRAWINGS

[eaton-circuit-breaker-contact-nzm-mccb-3d-drawing-004.eps](#)

ECAD MODEL

[ETN.NZM1-XUHIV20KL208-240AC](#)

INSTALLATION INSTRUCTIONS

[eaton-circuit-breaker-nzm1-xa-xahiv-xhiv-xuhiv-il01203002z.pdf](#)

INSTALLATION VIDEOS

[Introduction of the new digital circuit breaker NZM](#)

[The new digital NZM Range](#)

TECHNICAL DATA SHEETS

[eaton-nzm-technical-information-sheet](#)

ASSEMBLIES	be evaluated.
10.4 CLEARANCES AND CREEPAGE DISTANCES	Meets the product standard's requirements.
10.5 PROTECTION AGAINST ELECTRIC SHOCK	Does not apply, since the entire switchgear needs to be evaluated.
10.6 INCORPORATION OF SWITCHING DEVICES AND COMPONENTS	Does not apply, since the entire switchgear needs to be evaluated.
10.7 INTERNAL ELECTRICAL CIRCUITS AND CONNECTIONS	Is the panel builder's responsibility.
10.8 CONNECTIONS FOR EXTERNAL CONDUCTORS	Is the panel builder's responsibility.
10.9.2 POWER-FREQUENCY ELECTRIC STRENGTH	Is the panel builder's responsibility.
10.9.3 IMPULSE WITHSTAND VOLTAGE	Is the panel builder's responsibility.
10.9.4 TESTING OF ENCLOSURES MADE OF INSULATING MATERIAL	Is the panel builder's responsibility.
ELECTRIC CONNECTION TYPE	Screw connection
FITTED WITH:	Two separate early-make auxiliary contacts
FRAME	NZM1
MINIMUM COMMAND TIME - MAX	15 ms
MINIMUM COMMAND TIME - MIN	10 ms
NUMBER OF CONTACTS (NORMALLY OPEN CONTACTS)	2
REACTION TIME	19 ms
PICK-UP POWER CONSUMPTION AT AC (UNDERVOLTAGE RELEASE)	1.5 VA
PICK-UP POWER CONSUMPTION AT DC (UNDERVOLTAGE RELEASE)	0.8 W
VOLTAGE TOLERANCE - MAX	1.1
VOLTAGE TOLERANCE - MIN	.85
RATED CONTROL SUPPLY	208 - 240 V 50/60 Hz

VOLTAGE	
RATED CONTROL SUPPLY	
VOLTAGE (US) AT AC, 50	240 V
Hz - MAX	
RATED CONTROL SUPPLY	
VOLTAGE (US) AT AC, 50	208 V
Hz - MIN	
RATED CONTROL SUPPLY	
VOLTAGE (US) AT AC, 60	240 V
Hz - MAX	
RATED CONTROL SUPPLY	
VOLTAGE (US) AT AC, 60	208 V
Hz - MIN	
SUITABLE FOR	Off-load switch
CONNECTION TYPE	Auxiliary contact terminals with 3 m of loose connection cables Coil terminals wired to terminal block
CONNECTION	Screw
VOLTAGE TYPE	AC
DROP-OUT VOLTAGE OF UNDERRVOLTAGE RELEASE 0.7 x Us	
AC/DC - MAX	
DROP-OUT VOLTAGE OF UNDERRVOLTAGE RELEASE 0.35 x Us	
AC/DC - MIN	
TERMINAL CAPACITY (SOLID/FLEXIBLE CONDUCTOR)	18 - 14 AWG (1x) at shunt release 0.75 mm ² - 2.5 mm ² (2x) at shunt release with ferrule 18 - 14 AWG (2x) for undervoltage releases, off-delayed 0.75 mm ² - 2.5 mm ² (2x) for undervoltage releases, off-delayed with ferrule 18 - 14 AWG (2x) at shunt release 18 - 14 AWG (1x) for undervoltage releases, off-delayed 0.75 mm ² - 2.5 mm ² (1x) for undervoltage releases, off-delayed with ferrule 0.75 mm ² - 2.5 mm ² (1x) at shunt release with ferrule
TYPE	<ul style="list-style-type: none"> Accessory Undervoltage release with early-

make auxiliary contact

- Undervoltage release with 2 early-make auxiliary contacts, e.g., for early-make connection of undervoltage release in main switch applications, as well as for interlock and load shedding circuits.
- For use with emergency-stop devices in connection with an emergency-stop button.
- When the undervoltage trip is switched off, accidental contact with the circuit breaker's primary contacts is prevented when switched on.
- Early make of auxiliary contacts on switching on and off (manual operation): approx. 20 ms
- Cannot be used in conjunction with NZM...-XR... remote operator.
- Undervoltage releases cannot be installed simultaneously with NZM...-XHIV... early-make auxiliary contact or NZM...-XA... shunt release.

SPECIAL FEATURES

POWER CONSUMPTION

0.8 W (sealing DC)
1.5 VA (sealing AC)

RATED CONTROL SUPPLY

VOLTAGE (US) AT DC - MAX 0 V

RATED CONTROL SUPPLY**VOLTAGE (US) AT DC -** 0 V**MIN****NUMBER OF CONTACTS****(NORMALLY CLOSED
CONTACTS)** 0**NUMBER OF CONTACTS****(CHANGE-OVER
CONTACTS)** 0**UNDELAYED SHORT-
CIRCUIT RELEASE - MIN** 0 A**UNDELAYED SHORT-
CIRCUIT RELEASE - MAX** 0 A**RATED CONTROL****VOLTAGE (RELAY
CONTACTS)** 240 V AC

208 V AC

PROJECT NAME:**PROJECT NUMBER:****PREPARED BY:****DATE:****Eaton Corporation plc**

Eaton House
30 Pembroke Road
Dublin 4, Ireland
Eaton.com

© 2025 Eaton. All Rights Reserved.

Follow us on social media to get the latest product and support information.

