

Panelboards

Warehouse Stock/Unassembled

Selection

11
PANELBOARDS

Main Breaker Mounting Kits w/Breakers for P1 panels

Catalog Number	Description	Ratings	
		240V	480V
MBKED3100	Kit w/3-pole ED4 100A breaker	65KA	18KA
MBKED3125	Kit w/3-pole ED4 125A breaker	65KA	18KA
MBKQJ1125	Kit w/2-pole QJ2 125A breaker	10KA	—
MBKQJ1150	Kit w/2-pole QJ2 150A breaker	10KA	—
MBKQJ1175	Kit w/2-pole QJ2 175A breaker	10KA	—
MBKQJ1200	Kit w/2-pole QJ2 200A breaker	10KA	—
MBKQJ1225	Kit w/2-pole QJ2 225A breaker	10KA	—
MBKQJ3125	Kit w/3-pole QJ2 125A breaker	10KA	—
MBKQJ3150	Kit w/3-pole QJ2 150A breaker	10KA	—
MBKQJ3175	Kit w/3-pole QJ2 175A breaker	10KA	—
MBKQJ3200	Kit w/3-pole QJ2 200A breaker	10KA	—
MBKQJ3225	Kit w/3-pole QJ2 225A breaker	10KA	—
MBKQJ1125H	Kit w/2-pole QJ2H 125A breaker	42KA	—
MBKQJ1150H	Kit w/2-pole QJ2H 150A breaker	42KA	—
MBKQJ1175H	Kit w/2-pole QJ2H 175A breaker	42KA	—
MBKQJ1200H	Kit w/2-pole QJ2H 200A breaker	42KA	—
MBKQJ1225H	Kit w/2-pole QJ2H 225A breaker	42KA	—
MBKQJ3125H	Kit w/3-pole QJ2H 125A breaker	42KA	—
MBKQJ3150H	Kit w/3-pole QJ2H 150A breaker	42KA	—
MBKQJ3175H	Kit w/3-pole QJ2H 175A breaker	42KA	—
MBKQJ3200H	Kit w/3-pole QJ2H 200A breaker	42KA	—
MBKQJ3225H	Kit w/3-pole QJ2H 225A breaker	42KA	—
MBKFD3150	Kit w/3-pole FXD6 150A breaker	65KA	35KA
MBKFD3175	Kit w/3-pole FXD6 175A breaker	65KA	35KA
MBKFD3200	Kit w/3-pole FXD6 200A breaker	65KA	35KA
MBKFD3225	Kit w/3-pole FXD6 225A breaker	65KA	35KA
MBKFD3250	Kit w/3-pole FXD6 250A breaker	65KA	35KA
MBKJD1300	Kit w/2-pole JXD6 300A breaker	65KA	—
MBKJD3300	Kit w/3-pole JXD6 300A breaker	65KA	35KA
MBKJD1400 [Ⓞ]	Kit w/2-pole JXD6 400A breaker	65KA	35KA
MBKJD3400 [Ⓞ]	Kit w/3-pole JXD6 400A breaker	65KA	35KA

Branch Breakers Selection for P1

Selection Guide

1. Select breaker type.
2. Select required amperage.
3. Select number of poles.
4. Select branch breaker catalog numbers.
5. Select ground bar and filler plates. (See replacement parts & accessories on Page 11-11.)

AFCI – Combination Type Arc Fault Circuit Interrupter

Breaker Type	Ampere Rating	Catalog Number	Interrupting Ratings (kA) RMS Symmetrical Amperes		
			Volts AC		
			120	120/240	240
BAFC 1-pole	15	B115AFC	10	—	—
	20	B120AFC	10	—	—
BAFCH 1-pole	15	B115AFCH	22	—	—
	20	B120AFCH	22	—	—

AFCI – Branch Feeder Type Arc Fault Circuit Interrupter

Breaker Type	Ampere Rating	Catalog Number	Interrupting Ratings (kA) RMS Symmetrical Amperes		
			Volts AC		
			120	120/240	240
BAF 1-Pole	15	B115AF	10	—	—
	20	B120AF	10	—	—
BAFH 1-Pole	15	B115AFH	22	—	—
	20	B120AFH	22	—	—

Switching Neutrals

Breaker Type	Ampere Rating	Catalog Number	Interrupting Ratings (kA) RMS Symmetrical Amperes		
			Volts AC		
			120	120/240	240
BG 2-Wire Common Trip	15	BG215■	10	—	—
	20	BG220■	10	—	—
	30	BG230■	10	—	—
BG 3-Wire Common Trip	15	BG315■	—	10	—
	20	BG320■	—	10	—
	30	BG330■	—	10	—

■ Built to order.

Ⓞ 400 Amp Kit used as Main and for top feed application only. For bottom feed, order breaker, bracket and lugs separately.