


Specifications



Photo is representative



Eaton 073191

Eaton Moeller® series A-PKZ0 Shunt release (for power circuit breaker), 415 V 50 Hz, Standard voltage, AC, Screw terminals, For use with: Shunt release PKZ0(4), PKE

General specifications

PRODUCT NAME	Eaton Moeller® series PKZ Shunt release
CATALOG NUMBER	073191
MODEL CODE	A-PKZ0(415V50HZ)
EAN	4015080731917
PRODUCT LENGTH/DEPTH	68 mm
PRODUCT HEIGHT	90 mm
PRODUCT WIDTH	24 mm
PRODUCT WEIGHT	0.129 kg
CERTIFICATIONS	UL File No.: E36332 CE IEC/EN 60947-4-1 CSA CSA Class No.: 3211-05 UL CSA-C22.2 No. 14 CSA File No.: 165628 UL 508 UL Category Control No.: NLRV
GLOBAL CATALOG	073191

Product specifications

USED WITH	Motor protective circuit-breaker
10.10 TEMPERATURE RISE	The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 SHORT-CIRCUIT RATING	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.12 ELECTROMAGNETIC COMPATIBILITY	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.13 MECHANICAL FUNCTION	The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.
10.2.2 CORROSION RESISTANCE	Meets the product standard's requirements.
10.2.3.1 VERIFICATION OF THERMAL STABILITY OF ENCLOSURES	Meets the product standard's requirements.
10.2.3.2 VERIFICATION OF RESISTANCE OF INSULATING MATERIALS TO NORMAL HEAT	Meets the product standard's requirements.
10.2.3.3 RESIST. OF INSUL. MAT. TO ABNORMAL HEAT/FIRE BY INTERNAL ELECT. EFFECTS	Meets the product standard's requirements.
10.2.4 RESISTANCE TO ULTRA-VIOLET (UV) RADIATION	Meets the product standard's requirements.
10.2.5 LIFTING	Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 MECHANICAL IMPACT	Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 INSCRIPTIONS	Meets the product standard's requirements.
10.3 DEGREE OF	Does not apply, since the

Resources

BROCHURES

[eaton-motor-starters-system-xstart-brochure-br03407001en-en-us.pdf](#)
[eaton-motor-protective-circuit-breaker-pke-and-communication-modul-pke-brochure-w12107613en-en-us.pdf](#)

CATALOGS

[Product Range Catalog](#)
[Switching and protecting motors](#)
[eaton-product-overview-for-machinery-catalogue-ca08103003zen-en-us.pdf](#)

[DA-DC-00004993.pdf](#)
[DA-DC-00005002.pdf](#)
[DA-DC-00004915.pdf](#)
[DA-DC-00004919.pdf](#)
[DA-DC-00004997.pdf](#)
[DA-DC-00004961.pdf](#)
[DA-DC-00004960.pdf](#)

[DA-DC-00004545.pdf](#)
[DA-DC-00004992.pdf](#)

DECLARATIONS OF CONFORMITY

[DA-DC-00004881.pdf](#)
[DA-DC-00004937.pdf](#)
[DA-DC-00004230.pdf](#)
[DA-DC-00005041.pdf](#)
[DA-DC-00004914.pdf](#)
[DA-DC-00004882.pdf](#)
[DA-DC-00004880.pdf](#)
[DA-DC-00004244.pdf](#)
[DA-DC-00004917.pdf](#)
[DA-DC-00004885.pdf](#)
[DA-DC-00004976.pdf](#)
[DA-DC-00004601.pdf](#)
[DA-DC-00004945.pdf](#)

PROTECTION OF ASSEMBLIES	entire switchgear needs to be evaluated.
10.4 CLEARANCES AND CREEPAGE DISTANCES	Meets the product standard's requirements.
10.5 PROTECTION AGAINST ELECTRIC SHOCK	Does not apply, since the entire switchgear needs to be evaluated.
10.6 INCORPORATION OF SWITCHING DEVICES AND COMPONENTS	Does not apply, since the entire switchgear needs to be evaluated.
10.7 INTERNAL ELECTRICAL CIRCUITS AND CONNECTIONS	Is the panel builder's responsibility.
10.8 CONNECTIONS FOR EXTERNAL CONDUCTORS	Is the panel builder's responsibility.
10.9.2 POWER-FREQUENCY ELECTRIC STRENGTH	Is the panel builder's responsibility.
10.9.3 IMPULSE WITHSTAND VOLTAGE	Is the panel builder's responsibility.
10.9.4 TESTING OF ENCLOSURES MADE OF INSULATING MATERIAL	Is the panel builder's responsibility.
ELECTRIC CONNECTION TYPE	Screw connection
RATED OPERATIONAL VOLTAGE (UE) AT DC - MIN	24 V
STATIC HEAT DISSIPATION, NON-CURRENT-DEPENDENT PVS	0.5 W
UNDELAYED SHORT-CIRCUIT RELEASE - MAX	0 A
UNDELAYED SHORT-CIRCUIT RELEASE - MIN	0 A
PRODUCT CATEGORY	Accessories
AMBIENT OPERATING TEMPERATURE - MAX	55 °C
AMBIENT OPERATING TEMPERATURE - MIN	-25 °C
EQUIPMENT HEAT DISSIPATION, CURRENT-DEPENDENT PVID	0 W
HEAT DISSIPATION CAPACITY PDISS	0 W
HEAT DISSIPATION PER POLE, CURRENT-DEPENDENT PVID	0 W

[DA-DC-00004890.pdf](#)

[DA-DC-00005031.pdf](#)

[DA-DC-00005040.pdf](#)

[DA-DC-00004918.pdf](#)

[DA-DC-00004916.pdf](#)

[DA-DC-00004886.pdf](#)

[DA-DC-00004884.pdf](#)

[DA-DC-00004972.pdf](#)

[DA-DC-00004920.pdf](#)

[DA-DC-00004851.pdf](#)

[DA-DC-00004069.pdf](#)

[DA-DC-00004952.pdf](#)

[DA-DC-00004787.pdf](#)

[DA-DC-00004316.pdf](#)

[DA-DC-00004889.pdf](#)

[DA-DC-00004883.pdf](#)

[DA-DC-00004891.pdf](#)

[DA-DC-00004996.pdf](#)

[DA-DC-00005037.pdf](#)

[DA-DC-00004912.pdf](#)

[DA-DC-00004913.pdf](#)

[DA-DC-00004888.pdf](#)

[DA-DC-00004246.pdf](#)

[DA-DC-00004944.pdf](#)

[DA-DC-00004953.pdf](#)

[DA-DC-00004969.pdf](#)

[DA-DC-00004950.pdf](#)

[DA-DC-00004887.pdf](#)

DRAWINGS

[eaton-manual-motor-starters-release-u-pkz0-accessory-dimensions.eps](#)

[eaton-manual-motor-starters-shunt-releases-u-pkz0-accessory-3d-drawing.eps](#)

NUMBER OF CONTACTS (CHANGE-OVER CONTACTS)	0
NUMBER OF CONTACTS (NORMALLY CLOSED CONTACTS)	0
NUMBER OF CONTACTS (NORMALLY OPEN CONTACTS)	0
RATED CONTROL SUPPLY	
VOLTAGE (US) AT AC, 50 HZ - MAX	415 V
RATED CONTROL SUPPLY	
VOLTAGE (US) AT AC, 50 HZ - MIN	415 V
RATED CONTROL SUPPLY	
VOLTAGE (US) AT AC, 60 HZ - MAX	0 V
RATED CONTROL SUPPLY	
VOLTAGE (US) AT AC, 60 HZ - MIN	0 V
RATED CONTROL SUPPLY	
VOLTAGE (US) AT DC - MAX	0 V
RATED CONTROL SUPPLY	
VOLTAGE (US) AT DC - MIN	0 V
RATED OPERATIONAL CURRENT FOR SPECIFIED	0 A
HEAT DISSIPATION (IN)	
RATED OPERATIONAL VOLTAGE (UE) AT AC - MAX	480 V
RATED OPERATIONAL VOLTAGE (UE) AT AC - MIN	42 V
RATED OPERATIONAL VOLTAGE (UE) AT DC - MAX	250 V
VOLTAGE TYPE	AC
MOUNTING POSITION	Can be fitted to left side of the motor protection switch
SUITABLE FOR	Motor safety switch
OPERATIONAL VOLTAGE	0.7- 1.1 x Us (DC) 0.7- 1.1 x Us (alternating voltage) 0.7 - 1.1 x Us (AC)
POWER CONSUMPTION, PICK-UP, 50 HZ	5 VA, Pull-in power, Coil in a cold state and 1.0 x Us

ECAD MODEL	ETN.073191.edz
INSTALLATION INSTRUCTIONS	IL03402034Z
INSTALLATION VIDEOS	WIN-WIN with push-in technology
	Video Motor Protective Circuit Breaker PKE
MCAD MODEL	DA-CS-a_pkz DA-CD-a_pkz
SALES NOTES	eaton-pke-modbus-rtu- modul-flyer-f1034008en- en-us.pdf
WIRING DIAGRAMS	eaton-manual-motor- starters-release-a-pkz0- shunt-release-wiring- diagram.eps

POWER CONSUMPTION, PICK-UP, 60 HZ	5 VA, Pull-in power, Coil in a cold state and 1.0 x Us
POWER CONSUMPTION, SEALING, 50 HZ	3 VA, Coil in a cold state and 1.0 x Us
POWER CONSUMPTION, SEALING, 60 HZ	3 VA, Coil in a cold state and 1.0 x Us
TERMINAL CAPACITY (SOLID/FLEXIBLE WITH FERRULE)	2 x (0.75 - 2.5) mm ² 1 x (0.75 - 2.5) mm ²
TERMINAL CAPACITY (SOLID/STRANDED AWG)	1 x (18 - 14) 2 x (18 - 14)
POWER CONSUMPTION	0.5 W

PROJECT NAME:

PROJECT NUMBER:

PREPARED BY:

DATE:



Eaton Corporation plc

Eaton House
30 Pembroke Road
Dublin 4, Ireland
Eaton.com

© 2025 Eaton. All Rights Reserved.

Follow us on social media to get the latest product and support information.

