## Specifications



#### Photo is representative





### Eaton 073203

Eaton Moeller® series A-PKZ0 Shunt release (for power circuit breaker), 110 V DC, Standard voltage, DC, Screw terminals, For use with: Shunt release PKZ0(4), PKE

General specifications	
PRODUCT NAME	Eaton Moeller® series PKZ Shunt release
CATALOG NUMBER	073203
MODEL CODE	A-PKZ0(110VDC)
EAN	4015080732037
PRODUCT LENGTH/DEPTH	68 mm
PRODUCT HEIGHT	90 mm
PRODUCT WIDTH	24 mm
PRODUCT WEIGHT	0.126 kg
CERTIFICATIONS	CE UL Category Control No.: NLRV CSA CSA Class No.: 3211-05 CSA-C22.2 No. 14 CSA File No.: 165628 UL 508 UL File No.: E36332 IEC/EN 60947-4-1 UL



#### Features & Functions

ELECTRIC CONNECTION TYPE

Screw connection

# GeneralPRODUCT CATEGORYAccessoriesSUITABLE FORMotor safety switchUSED WITHMotor protective circuit-<br/>breakerVOLTAGE TYPEDC

#### Ambient conditions, mechanical

MOUNTING POSITION

Can be fitted to left side of the motor protection switch

#### Climatic environmental conditions

AMBIENT OPERATING TEMPERATURE - MIN	-25 °C
AMBIENT OPERATING TEMPERATURE - MAX	55 °C

Terminal capacities	
TERMINAL CAPACITY (SOLID/FLEXIBLE WITH FERRULE)	2 x (0.75 - 2.5) mm² 1 x (0.75 - 2.5) mm²
TERMINAL CAPACITY (SOLID/STRANDED AWG)	1 x (18 - 14) 2 x (18 - 14)

#### Electrical rating

OPERATIONAL VOLTAGE	0.7- 1.1 x Us (DC) Short-time operation 5 s 0.7 - 1.1 x Us (AC)
RATED OPERATIONAL VOLTAGE (UE) AT AC - MIN	42 V
RATED OPERATIONAL VOLTAGE (UE) AT AC - MAX	480 V
RATED OPERATIONAL VOLTAGE (UE) AT DC - MIN	24 V
RATED OPERATIONAL VOLTAGE (UE) AT DC - MAX	250 V

#### Magnet system

OPERATIONAL VOLTAGE	0.7- 1.1 x Us (DC) Short-time operation 5 s 0 7 - 1 1 x Us (AC)
RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 50 HZ - MIN	0 V
RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 50 HZ - MAX	0 V
RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 60 HZ - MIN	0 V
RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 60 HZ - MAX	0 V
RATED CONTROL SUPPLY VOLTAGE (US) AT DC - MIN	110 V
RATED CONTROL SUPPLY VOLTAGE (US) AT DC - MAX	110 V

Contacts	
NUMBER OF CONTACTS (CHANGE-OVER CONTACTS)	0
NUMBER OF CONTACTS (NORMALLY CLOSED CONTACTS)	0
NUMBER OF CONTACTS (NORMALLY OPEN CONTACTS)	0

Power consumption	
POWER CONSUMPTION (PICK-UP) AT DC	3 W
POWER CONSUMPTION (SEALING) AT DC	0.5 W

Design verification	
EQUIPMENT HEAT DISSIPATION, CURRENT- DEPENDENT PVID	0 W
HEAT DISSIPATION CAPACITY PDISS	0 W
HEAT DISSIPATION PER POLE, CURRENT- DEPENDENT PVID	0 W
RATED OPERATIONAL CURRENT FOR SPECIFIED HEAT DISSIPATION (IN)	0 A
STATIC HEAT DISSIPATION, NON- CURRENT-DEPENDENT PVS	0.5 W
10.2.2 CORROSION RESISTANCE	Meets the product standard's requirements.
10.2.3.1 VERIFICATION OF THERMAL STABILITY OF ENCLOSURES	Meets the product standard's requirements.
10.2.3.2 VERIFICATION OF RESISTANCE OF INSULATING MATERIALS TO NORMAL HEAT	Meets the product standard's requirements.

10.2.3.3 RESIST. OF INSUL. MAT. TO ABNORMAL HEAT/FIRE BY INTERNAL ELECT. EFFECTS	Meets the product standard's requirements.
10.2.4 RESISTANCE TO ULTRA-VIOLET (UV) RADIATION	Meets the product standard's requirements.
10.2.5 LIFTING	Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 MECHANICAL IMPACT	Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 INSCRIPTIONS	Meets the product standard's requirements.
10.3 DEGREE OF PROTECTION OF ASSEMBLIES	Does not apply, since the entire switchgear needs to be evaluated.
10.4 CLEARANCES AND CREEPAGE DISTANCES	Meets the product standard's requirements.
10.5 PROTECTION AGAINST ELECTRIC SHOCK	Does not apply, since the entire switchgear needs to be evaluated.
10.6 INCORPORATION OF SWITCHING DEVICES AND COMPONENTS	Does not apply, since the entire switchgear needs to be evaluated.
10.7 INTERNAL ELECTRICAL CIRCUITS AND CONNECTIONS	ls the panel builder's responsibility.
10.8 CONNECTIONS FOR EXTERNAL CONDUCTORS	ls the panel builder's responsibility.
10.9.2 POWER- FREQUENCY ELECTRIC STRENGTH	ls the panel builder's responsibility.
10.9.3 IMPULSE WITHSTAND VOLTAGE	ls the panel builder's responsibility.
10.9.4 TESTING OF ENCLOSURES MADE OF INSULATING MATERIAL	ls the panel builder's responsibility.
10.10 TEMPERATURE RISE	The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 SHORT-CIRCUIT RATING	ls the panel builder's responsibility. The specifications for the switchgear must be

	observed.
10.12 ELECTROMAGNETIC COMPATIBILITY	ls the panel builder's responsibility. The specifications for the switchgear must be observed.
10.13 MECHANICAL FUNCTION	The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

#### Resources

BROCHURES	eaton-motor-protective- circuit-breaker-pke-and- communication-modul- pke-brochure- w12107613en-en-us.pdf eaton-motor-starters- system-xstart-brochure- br03407001en-en-us.pdf eaton-product-overview- for-machinery-catalogue- ca08103003zen-en-us.pdf
	Product Range Catalog Switching and protecting motors
	DA-DC-00004545.pdf
	<u>DA-DC-00004915.pdf</u>
	DA-DC-00004914.pdf
	DA-DC-00004244.pdf
	DA-DC-00004880.pdf
	<u>DA-DC-00004919.pdf</u>
	DA-DC-00005002.pdf
	<u>DA-DC-00004961.pdf</u>
	DA-DC-00004960.pdf
	DA-DC-00005041.pdf
	DA-DC-00004997.pdf
DECLARATIONS OF CONFORMITY	DA-DC-00004882.pdf
	DA-DC-00004993.pdf
	DA-DC-00004230.pdf
	DA-DC-00004937.pdf
	DA-DC-00004976.pdf
	DA-DC-00004917.pdf
	DA-DC-00004885.pdf
	DA-DC-00004601.pdf
	DA-DC-00004945.pdf
	DA-DC-00004851.pdf
	DA-DC-00004972.pdf
	DA-DC-00004890.pdf

DA-DC-00004992.pdf DA-DC-00004888.pdf DA-DC-00004912.pdf DA-DC-00004913.pdf DA-DC-00005037.pdf DA-DC-00004944.pdf DA-DC-00004246.pdf DA-DC-00004891.pdf DA-DC-00004887.pdf DA-DC-00004969.pdf DA-DC-00004953.pdf DA-DC-00004950.pdf DA-DC-00004952.pdf DA-DC-00004883.pdf DA-DC-00005031.pdf DA-DC-00004069.pdf DA-DC-00004884.pdf DA-DC-00004996.pdf DA-DC-00004889.pdf DA-DC-00005040.pdf DA-DC-00004316.pdf DA-DC-00004787.pdf DA-DC-00004918.pdf DA-DC-00004920.pdf DA-DC-00004886.pdf DA-DC-00004916.pdf DA-DC-00004881.pdf eaton-manual-motorstarters-release-u-pkz0accessory-dimensions.eps eaton-manual-motor-

<u>starters-shunt-releases-u-</u> <u>pkz0-accessory-3d-</u> <u>drawing.eps</u>

DRAWINGS

	<u>eaton-manual-motor-</u> <u>starters-release-u-pkz0-</u> <u>accessory-3d-drawing.eps</u>
ECAD MODEL	ETN.073203.edz
INSTALLATION INSTRUCTIONS	<u>IL03402034Z</u>
INSTALLATION VIDEOS	<u>WIN-WIN with push-in</u> <u>technology</u>
	<u>Circuit Breaker PKE</u>
MCAD MODEL	DA-CS-a_pkz_DA-CD-a_pkz
SALES NOTES	<u>eaton-pke-modbus-rtu-</u> <u>modul-flyer-fl034008en-</u> <u>en-us.pdf</u>
WIRING DIAGRAMS	<u>eaton-manual-motor-</u> <u>starters-release-a-pkz0-</u> <u>shunt-release-wiring-</u> <u>diagram.eps</u>

#### **PROJECT NAME:**

**PROJECT NUMBER:** 

PREPARED BY:

DATE:



#### **Eaton Corporation plc** Eaton House 30 Pembroke Road Dublin 4, Ireland Eaton.com

© 2025 Eaton. All Rights Reserved.

Follow us on social media to get the latest product and support information.

