

# Specifications

Photo is representative

## Eaton 012309

Eaton Moeller® series T0 Step switches, T0, 20 A, centre mounting, 3 contact unit(s), Contacts: 6, 45 °, maintained, With 0 (Off) position, 0-6, Design number 145

### General specifications

<b>PRODUCT NAME</b>	Eaton Moeller® series T0 Step switch
<b>CATALOG NUMBER</b>	012309
<b>EAN</b>	4015080123095
<b>PRODUCT LENGTH/DEPTH</b>	115 mm
<b>PRODUCT HEIGHT</b>	48 mm
<b>PRODUCT WIDTH</b>	48 mm
<b>PRODUCT WEIGHT</b>	0.153 kg
<b>CERTIFICATIONS</b>	CSA File No.: 012528 UL Category Control No.: NLRV VDE 0660 IEC/EN 60947 IEC/EN 60947-3 CSA-C22.2 No. 60947-4-1-14 UL File No.: E36332 CSA Class No.: 3211-05 CE IEC/EN 60204 UL 60947-4-1 UL CSA CSA-C22.2 No. 94
<b>CATALOG NOTES</b>	Rated Short-time Withstand Current (I <sub>cw</sub> ) for a time of 1 second
<b>MODEL CODE</b>	T0-3-145/EZ

## Features & Functions

<b>FITTED WITH:</b>	Black thumb grip and front plate 0 (off) position
---------------------	--

<b>INSCRIPTION</b>	0-6
--------------------	-----

<b>NUMBER OF POLES</b>	Single-pole
------------------------	-------------

## General

<b>DEGREE OF PROTECTION</b>	NEMA 1 IP65 NEMA 12
-----------------------------	---------------------------

<b>DEGREE OF PROTECTION (FRONT SIDE)</b>	IP65 NEMA 12
--	-----------------

<b>LIFESPAN, MECHANICAL</b>	400,000 Operations
-----------------------------	--------------------

<b>MOUNTING METHOD</b>	Center mounting
------------------------	-----------------

<b>MOUNTING POSITION</b>	As required
--------------------------	-------------

<b>NUMBER OF CONTACT UNITS</b>	3
--------------------------------	---

<b>OPERATING FREQUENCY</b>	1200 Operations/h
----------------------------	-------------------

<b>OVERVOLTAGE CATEGORY</b>	III
-----------------------------	-----

<b>POLLUTION DEGREE</b>	3
-------------------------	---

<b>PRODUCT CATEGORY</b>	Control switches
-------------------------	------------------

<b>RATED IMPULSE WITHSTAND VOLTAGE (UIMP)</b>	6000 V AC
---	-----------

<b>SAFE ISOLATION</b>	440 V AC, Between the contacts, According to EN 61140
-----------------------	---

<b>SAFETY PARAMETER (EN ISO 13849-1)</b>	B10d values as per EN ISO 13849-1, table C.1
--	--

<b>SHOCK RESISTANCE</b>	15 g, Mechanical, According to IEC/EN 60068-2-27, Half-sinusoidal shock 20 ms
-------------------------	---

<b>SUITABLE FOR</b>	Branch circuits, suitable as motor disconnect, (UL/CSA) Front mounting
---------------------	---

<b>SWITCHING ANGLE</b>	45 °
------------------------	------

<b>TYPE</b>	Step switch
-------------	-------------

## Climatic environmental conditions

<b>AMBIENT OPERATING TEMPERATURE - MIN</b>	-25 °C
--	--------

<b>AMBIENT OPERATING TEMPERATURE - MAX</b>	50 °C
--	-------

<b>AMBIENT OPERATING TEMPERATURE (ENCLOSED) - MIN</b>	-25 °C
---	--------

<b>AMBIENT OPERATING TEMPERATURE (ENCLOSED) - MAX</b>	40 °C
---	-------

<b>CLIMATIC PROOFING</b>	Damp heat, constant, to IEC 60068-2-78 Damp heat, cyclic, to IEC 60068-2-30
--------------------------	--

## Terminal capacities

<b>TERMINAL CAPACITY (FLEXIBLE WITH FERRULE)</b>	1 x (0.75 - 2.5) mm <sup>2</sup> , ferrules to DIN 46228 2 x (0.75 - 2.5) mm <sup>2</sup> , ferrules to DIN 46228
--	--

<b>TERMINAL CAPACITY (SOLID/FLEXIBLE WITH FERRULE AWG)</b>	18 - 14
--	---------

<b>TERMINAL CAPACITY (SOLID/STRANDED)</b>	1 x (1 - 2.5) mm <sup>2</sup> 2 x (1 - 2.5) mm <sup>2</sup>
---	--

<b>SCREW SIZE</b>	M3.5, Terminal screw
-------------------	----------------------

<b>TIGHTENING TORQUE</b>	8.8 lb-in, Screw terminals 1 Nm, Screw terminals
--------------------------	---

## Electrical rating

**RATED BREAKING  
CAPACITY AT 220/230 V  
(COS PHI TO IEC 60947-3)** 100 A

**RATED BREAKING  
CAPACITY AT 400/415 V  
(COS PHI TO IEC 60947-3)** 110 A

**RATED BREAKING  
CAPACITY AT 500 V (COS  
PHI TO IEC 60947-3)** 80 A

**RATED BREAKING  
CAPACITY AT 660/690 V  
(COS PHI TO IEC 60947-3)** 60 A

**RATED OPERATING  
VOLTAGE (UE) AT AC -  
MAX** 690 V

**RATED OPERATIONAL  
CURRENT (IE) AT AC-3,  
220 V, 230 V, 240 V** 11.5 A

**RATED OPERATIONAL  
CURRENT (IE) AT AC-3,  
380 V, 400 V, 415 V** 11.5 A

**RATED OPERATIONAL  
CURRENT (IE) AT AC-3,  
500 V** 9 A

**RATED OPERATIONAL  
CURRENT (IE) AT AC-3,  
660 V, 690 V** 4.9 A

**RATED OPERATIONAL  
CURRENT (IE) AT AC-21,  
440 V** 20 A

**RATED OPERATIONAL  
CURRENT (IE) AT AC-23A,  
230 V** 13.3 A

**RATED OPERATIONAL  
CURRENT (IE) AT AC-23A,  
400 V, 415 V** 13.3 A

**RATED OPERATIONAL  
CURRENT (IE) AT AC-23A,  
500 V** 13.3 A

**RATED OPERATIONAL  
CURRENT (IE) AT AC-23A,  
690 V** 7.6 A

**RATED OPERATIONAL  
CURRENT (IE) AT DC-1,  
LOAD-BREAK SWITCHES  
L/R = 1 MS** 10 A

**RATED OPERATIONAL  
CURRENT (IE) AT DC-13,  
CONTROL SWITCHES L/R** 10 A

## Short-circuit rating

**RATED CONDITIONAL  
SHORT-CIRCUIT CURRENT  
(IQ)** 6 kA

**RATED SHORT-TIME  
WITHSTAND CURRENT  
(ICW)** 320 A, Contacts, 1 second

**SHORT-CIRCUIT CURRENT  
RATING (BASIC RATING)** 5 kA, SCCR (UL/CSA)  
50A, max. Fuse, SCCR  
(UL/CSA)

**SHORT-CIRCUIT CURRENT  
RATING (HIGH FAULT)** 20 A, Class J, max. Fuse,  
SCCR (UL/CSA)  
10 kA, SCCR (UL/CSA)

**SHORT-CIRCUIT  
PROTECTION RATING** 20 A gG/gL, Fuse, Contacts

<b>= 50 MS</b>	
<b>RATED OPERATIONAL CURRENT (IE) AT DC-21, 240 V</b>	1 A
<b>RATED OPERATIONAL CURRENT (IE) AT DC-23A, 24 V</b>	10 A
<b>RATED OPERATIONAL CURRENT (IE) AT DC-23A, 48 V</b>	10 A
<b>RATED OPERATIONAL CURRENT (IE) AT DC-23A, 60 V</b>	10 A
<b>RATED OPERATIONAL CURRENT (IE) AT DC-23A, 120 V</b>	5 A
<b>RATED OPERATIONAL CURRENT (IE) AT DC-23A, 240 V</b>	5 A
<b>RATED OPERATIONAL CURRENT (IE) STAR- DELTA AT AC-3, 230 V</b>	20 A
<b>RATED OPERATIONAL CURRENT (IE) STAR- DELTA AT AC-3, 400 V</b>	20 A
<b>RATED OPERATIONAL CURRENT (IE) STAR- DELTA AT AC-3, 500 V</b>	15.6 A
<b>RATED OPERATIONAL CURRENT (IE) STAR- DELTA AT AC-3, 690 V</b>	8.5 A
<b>RATED OPERATIONAL POWER AT AC-3, 415 V, 50 HZ</b>	5.5 kW
<b>RATED OPERATIONAL POWER AT AC-3, 690 V, 50 HZ</b>	4 kW
<b>RATED OPERATIONAL POWER AT AC-23A, 220/230 V, 50 HZ</b>	3 kW
<b>RATED OPERATIONAL POWER AT AC-23A, 400 V, 50 HZ</b>	5.5 kW
<b>RATED OPERATIONAL POWER AT AC-23A, 500 V, 50 HZ</b>	7.5 kW
<b>RATED OPERATIONAL POWER AT AC-23A, 690 V, 50 HZ</b>	5.5 kW
<b>RATED OPERATIONAL</b>	5.5 kW

<b>POWER STAR-DELTA AT 220/230 V, 50 HZ</b>	
<b>RATED OPERATIONAL POWER STAR-DELTA AT 380/400 V, 50 HZ</b>	7.5 kW
<b>RATED OPERATIONAL POWER STAR-DELTA AT 500 V, 50 HZ</b>	7.5 kW
<b>RATED OPERATIONAL POWER STAR-DELTA AT 690 V, 50 HZ</b>	5.5 kW
<b>RATED UNINTERRUPTED CURRENT (IU)</b>	20 A
<b>UNINTERRUPTED CURRENT</b>	Rated uninterrupted current I <sub>u</sub> is specified for max. cross-section.

## Switching capacity

LOAD RATING	2 x I <sub>e</sub> (with intermittent operation class 12, 25 % duty factor)
	1.3 x I <sub>e</sub> (with intermittent operation class 12, 60 % duty factor)
	1.6 x I <sub>e</sub> (with intermittent operation class 12, 40 % duty factor)

### NUMBER OF CONTACTS IN SERIES AT DC-21A, 240 V

1

### NUMBER OF CONTACTS IN SERIES AT DC-23A, 24 V

1

### NUMBER OF CONTACTS IN SERIES AT DC-23A, 48 V

2

### NUMBER OF CONTACTS IN SERIES AT DC-23A, 60 V

3

### NUMBER OF CONTACTS IN SERIES AT DC-23A, 120 V

3

### NUMBER OF CONTACTS IN SERIES AT DC-23A, 240 V

5

### SWITCHING CAPACITY (MAIN CONTACTS, GENERAL USE)

16 A, Rated uninterrupted current max. (UL/CSA)

### SWITCHING CAPACITY (AUXILIARY CONTACTS, GENERAL USE)

10A, IU, (UL/CSA)

### SWITCHING CAPACITY (AUXILIARY CONTACTS, PILOT DUTY)

P300 (UL/CSA)  
A600 (UL/CSA)

### RATED MAKING CAPACITY UP TO 690 V (COS PHI TO IEC/EN 60947-3)

130 A

### VOLTAGE PER CONTACT PAIR IN SERIES

60 V

## Contacts

CONTROL CIRCUIT RELIABILITY	1 failure per 100,000 switching operations statistically determined, at 24 V DC, 10 mA)
-----------------------------	---

### NUMBER OF CONTACTS

6

## Motor rating

### ASSIGNED MOTOR

POWER AT 115/120 V, 60 HZ, 1-PHASE 0.5 HP

### ASSIGNED MOTOR

POWER AT 200/208 V, 60 HZ, 1-PHASE 1 HP

### ASSIGNED MOTOR

POWER AT 200/208 V, 60 HZ, 3-PHASE 3 HP

### ASSIGNED MOTOR

POWER AT 230/240 V, 60 HZ, 1-PHASE 1.5 HP

### ASSIGNED MOTOR

POWER AT 230/240 V, 60 HZ, 3-PHASE 3 HP

### ASSIGNED MOTOR

POWER AT 460/480 V, 60 HZ, 3-PHASE 7.5 HP

### ASSIGNED MOTOR

POWER AT 575/600 V, 60 HZ, 3-PHASE 7.5 HP

## Actuator

ACTUATOR FUNCTION	Maintained With 0 (Off) position
-------------------	-------------------------------------

### ACTUATOR TYPE

Toggle

### NUMBER OF SWITCH POSITIONS

7

## Design verification

<b>EQUIPMENT HEAT DISSIPATION, CURRENT-DEPENDENT PVID</b>	0 W
---	-----

<b>HEAT DISSIPATION CAPACITY PDISS</b>	0 W
--	-----

<b>HEAT DISSIPATION PER POLE, CURRENT-DEPENDENT PVID</b>	0.6 W
--	-------

<b>RATED OPERATIONAL CURRENT FOR SPECIFIED HEAT DISSIPATION (IN)</b>	20 A
--	------

<b>STATIC HEAT DISSIPATION, NON-CURRENT-DEPENDENT PVS</b>	0 W
---	-----

<b>10.2.2 CORROSION RESISTANCE</b>	Meets the product standard's requirements.
------------------------------------	--

<b>10.2.3.1 VERIFICATION OF THERMAL STABILITY OF ENCLOSURES</b>	Meets the product standard's requirements.
---	--

<b>10.2.3.2 VERIFICATION OF RESISTANCE OF INSULATING MATERIALS TO NORMAL HEAT</b>	Meets the product standard's requirements.
---	--

<b>10.2.3.3 RESIST. OF INSUL. MAT. TO ABNORMAL HEAT/FIRE BY INTERNAL ELECT. EFFECTS</b>	Meets the product standard's requirements.
---	--

<b>10.2.4 RESISTANCE TO ULTRA-VIOLET (UV) RADIATION</b>	UV resistance only in connection with protective shield.
---	--

<b>10.2.5 LIFTING</b>	Does not apply, since the entire switchgear needs to be evaluated.
-----------------------	--

<b>10.2.6 MECHANICAL IMPACT</b>	Does not apply, since the entire switchgear needs to be evaluated.
---------------------------------	--

<b>10.2.7 INSCRIPTIONS</b>	Meets the product standard's requirements.
----------------------------	--

<b>10.3 DEGREE OF PROTECTION OF ASSEMBLIES</b>	Does not apply, since the entire switchgear needs to be evaluated.
--	--

<b>10.4 CLEARANCES AND CREEPAGE DISTANCES</b>	Meets the product standard's requirements.
---	--

<b>10.5 PROTECTION AGAINST ELECTRIC SHOCK</b>	Does not apply, since the entire switchgear needs to be evaluated.
---	--



<b>10.6 INCORPORATION OF SWITCHING DEVICES AND COMPONENTS</b>	Does not apply, since the entire switchgear needs to be evaluated.
<b>10.7 INTERNAL ELECTRICAL CIRCUITS AND CONNECTIONS</b>	Is the panel builder's responsibility.
<b>10.8 CONNECTIONS FOR EXTERNAL CONDUCTORS</b>	Is the panel builder's responsibility.
<b>10.9.2 POWER-FREQUENCY ELECTRIC STRENGTH</b>	Is the panel builder's responsibility.
<b>10.9.3 IMPULSE WITHSTAND VOLTAGE</b>	Is the panel builder's responsibility.
<b>10.9.4 TESTING OF ENCLOSURES MADE OF INSULATING MATERIAL</b>	Is the panel builder's responsibility.
<b>10.10 TEMPERATURE RISE</b>	The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
<b>10.11 SHORT-CIRCUIT RATING</b>	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
<b>10.12 ELECTROMAGNETIC COMPATIBILITY</b>	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
<b>10.13 MECHANICAL FUNCTION</b>	The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

## Resources

### BROCHURES

[Brochure - T Rotary Cam switch and P Switch-disconnector](#)

### CATALOGUES

[P Switch-disconnectors and T Rotary cam switches catalogue CA042001EN](#)

### DECLARATIONS OF CONFORMITY

[DA-DC-00004927.pdf](#) [DA-DC-00004895.pdf](#)

### DRAWINGS

[eaton-rotary-switches-mounting-t0-step-switch-dimensions-011.eps](#)

	<a href="#">eaton-general-rotary-switch-t0-step-switch-symbol-004.eps</a> <a href="#">eaton-rotary-switches-front-plate-t0-step-switch-symbol-012.eps</a>
ECAD MODEL	<a href="#">eaton-t0-step-switch-eplan-012309.edz</a>
INSTALLATION INSTRUCTIONS	<a href="#">IL03801020Z</a>
INSTALLATION VIDEOS	<a href="#">Eaton's P Switch-disconnectors used in a factory</a>
MCAD MODEL	<a href="#">DA-CD-t0 3 ez</a> <a href="#">DA-CS-t0 3 ez</a>
PRODUCT NOTIFICATIONS	<a href="#">MZ008006ZU Orderform Customized Switch.pdf</a> <a href="#">MZ008005ZU Orderform Customized Switch.pdf</a>
WIRING DIAGRAMS	<a href="#">eaton-rotary-switches-t0-step-switch-wiring-diagram-025.eps</a> <a href="#">eaton-rotary-switches-t0-step-switch-wiring-diagram-026.eps</a>

PROJECT NAME:

PROJECT NUMBER:

PREPARED BY:

DATE:



**Eaton Corporation plc**

Eaton House  
30 Pembroke Road  
Dublin 4, Ireland  
Eaton.com

© 2025 Eaton. All Rights Reserved.

Follow us on social media to get the latest product and support information.

