

Specifications



Photo is representative

Eaton 192385

Eaton Moeller® series EMS2 DOL starter, 24 V DC, 0,18 - 3 A, Push in terminals, SmartWire-DT slave, Controlled stop, PTB 19 ATEX 3000

General specifications

PRODUCT NAME	Eaton Moeller® series EMS2 DOL starter
CATALOG NUMBER	192385
MODEL CODE	EMS2-DOS-T-3-SWD
EAN	4015081930821
PRODUCT LENGTH/DEPTH	114.5 mm
PRODUCT HEIGHT	99 mm
PRODUCT WIDTH	22.5 mm
PRODUCT WEIGHT	0.297 kg
CERTIFICATIONS	EN ISO 13849 IEC 61508 IEC/EN 60947-4-2 UL508 UL File No.: E338590 UL Category Control No.: NLDX, NLDX7 PTB 19 ATEX 3000 UL 60947-4-1 CSA-C22.2 No. 60947-4-1- 14 CE marking UL listed Certified by UL for use in Canada UL report applies to both US and Canada

Features & Functions

FUNCTIONS	Controlled stop
	DOL starting
	For connecting to SmartWire-DT for expanded diagnostics
	Temperature compensated overload protection
	Motor protection
	Automatic reset
	Display of Device Type
	Display of Enable signal
	Manual reset
	Display of Motor current in %
	Display of Operating direction feedback
	Operating the motor starter
	Display of Operational readiness
	Display of Overload prewarning
	Display of Set short-circuit release value
	Display of Thermal motor image in %
	Display of Trip indications (overload, phase failure, etc.)

Climatic environmental conditions

AMBIENT OPERATING TEMPERATURE - MIN -5 °C

AMBIENT OPERATING TEMPERATURE - MAX 55 °C

AMBIENT STORAGE TEMPERATURE - MIN 40 °C

AMBIENT STORAGE TEMPERATURE - MAX 80 °C

General

CLASS CLASS 10

CONNECTION TO SMARTWIRE-DT Yes

DEGREE OF PROTECTION IP20
NEMA Other

MODEL Direct starter

MOUNTING METHOD Rail mounting possible
Top-hat rail fixing (according to IEC/EN 60715, 35 mm)

MOUNTING POSITION Vertical
Motor feeder at bottom

OVERLOAD RELEASE CURRENT SETTING - MIN 0.18 A

OVERLOAD RELEASE CURRENT SETTING - MAX 3 A

PRODUCT CATEGORY Electronic motor starter

PROTOCOL Other bus systems

RESIDUAL RIPPLE ≤ 5 % (input voltage)

TERMINAL CAPACITY 0.2 - 2.5 mm², Main cables, Push-in terminals

TERMINAL CAPACITY (AWG) 24 - 14, Push-in terminals

TYPE DOL starter (complete device)

VOLTAGE TYPE DC

Electro magnetic compatibility

RADIO INTERFERENCE CLASS EN 55011
Class A (EN 61000-6-3, emitted interference, radiated)

Electrical rating

INRUSH CURRENT 120 mA (draw)

RATED ACTUATING CURRENT (IC) 5 mA

RATED CONDITIONAL SHORT-CIRCUIT CURRENT (IQ), TYPE 2, 380 V, 400 V, 415 V 0 A

RATED CONTROL SUPPLY CURRENT IS 60 mA

RATED CONTROL SUPPLY VOLTAGE 19.2 - 30 V DC

RATED CONTROL VOLTAGE (UC) 24 V (Actuating circuit ON, L, R)

RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 50 HZ - MIN 0 V

RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 50 HZ - MAX 0 V

RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 60 HZ - MIN 0 V

RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 60 HZ - MAX 0 V

RATED CONTROL SUPPLY VOLTAGE (US) AT DC - MIN 24 V

RATED CONTROL SUPPLY VOLTAGE (US) AT DC - MAX 24 V

RATED OPERATIONAL CURRENT (IE) 3 A

RATED OPERATIONAL CURRENT (IE) AT AC-3, 380 V, 400 V, 415 V 3 A

RATED OPERATIONAL CURRENT (IE) AT AC-51 3 A

RATED OPERATIONAL CURRENT (IE) AT AC-53A - MAX 3 A

RATED OPERATIONAL POWER AT AC-3, 220/230 V, 50 HZ 0.55 kW

RATED OPERATIONAL POWER AT AC-3, 380/400 V, 50 HZ 1.1 kW

Contacts

NUMBER OF AUXILIARY CONTACTS (NORMALLY CLOSED CONTACTS) 0

NUMBER OF AUXILIARY CONTACTS (NORMALLY OPEN CONTACTS) 0

RATED OPERATIONAL POWER AT AC-53A, 380/400 V, 50 HZ	1.1 kW
RATED OPERATIONAL VOLTAGE	42 - 550 V 500 V AC
SWITCHING LEVEL	-3 - 9.6 V DC, Switching level "Low", Actuating circuit (ON, L, R) 19.2 - 30 V DC, Switching level "High", Actuating circuit (ON, L, R) < 5 V DC, Switching level "confirm Off", Actuating circuit (ON, L, R)

Safety	
EXPLOSION SAFETY CATEGORY FOR DUST	ATEX dust-ex-protection, II (2) G [Ex e] [Ex d] [Ex px] ATEX dust-ex-protection, II (2) D [Ex t] [Ex p]
SAFETY PARAMETER (EN ISO 13849-1)	3, Category PL e, Performance level 60 (safe switch off) / 82 (motor protection) years; MTTFD
SAFETY PARAMETER (IEC 62061)	Opening delay [ms]: 200 (safe switch off) / Class 10 (motor protection) 99 % (safe switch off) / 98 % (motor protection), DC

Design verification	
EQUIPMENT HEAT DISSIPATION, CURRENT-DEPENDENT PVID	2.5 W
HEAT DISSIPATION CAPACITY PDISS	0 W
HEAT DISSIPATION PER POLE, CURRENT-DEPENDENT PVID	0 W
RATED OPERATIONAL CURRENT FOR SPECIFIED HEAT DISSIPATION (IN)	3 A
STATIC HEAT DISSIPATION, NON-CURRENT-DEPENDENT PVS	2 W
HEAT DISSIPATION DETAILS	If necessary, Allow for derating
10.2.2 CORROSION RESISTANCE	Meets the product standard's requirements.
10.2.3.1 VERIFICATION OF THERMAL STABILITY OF ENCLOSURES	Meets the product standard's requirements.
10.2.3.2 VERIFICATION OF RESISTANCE OF INSULATING MATERIALS TO NORMAL HEAT	Meets the product standard's requirements.
10.2.3.3 RESIST. OF INSUL. MAT. TO ABNORMAL HEAT/FIRE BY INTERNAL ELECT. EFFECTS	Meets the product standard's requirements.
10.2.4 RESISTANCE TO ULTRA-VIOLET (UV)	Meets the product standard's requirements.

RADIATION	
10.2.5 LIFTING	Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 MECHANICAL IMPACT	Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 INSCRIPTIONS	Meets the product standard's requirements.
10.3 DEGREE OF PROTECTION OF ASSEMBLIES	Does not apply, since the entire switchgear needs to be evaluated.
10.4 CLEARANCES AND CREEPAGE DISTANCES	Meets the product standard's requirements.
10.5 PROTECTION AGAINST ELECTRIC SHOCK	Does not apply, since the entire switchgear needs to be evaluated.
10.6 INCORPORATION OF SWITCHING DEVICES AND COMPONENTS	Does not apply, since the entire switchgear needs to be evaluated.
10.7 INTERNAL ELECTRICAL CIRCUITS AND CONNECTIONS	Is the panel builder's responsibility.
10.8 CONNECTIONS FOR EXTERNAL CONDUCTORS	Is the panel builder's responsibility.
10.9.2 POWER-FREQUENCY ELECTRIC STRENGTH	Is the panel builder's responsibility.
10.9.3 IMPULSE WITHSTAND VOLTAGE	Is the panel builder's responsibility.
10.9.4 TESTING OF ENCLOSURES MADE OF INSULATING MATERIAL	Is the panel builder's responsibility.
10.10 TEMPERATURE RISE	The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 SHORT-CIRCUIT RATING	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.12 ELECTROMAGNETIC COMPATIBILITY	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.13 MECHANICAL	The device meets the

FUNCTION

requirements, provided the information in the instruction leaflet (IL) is observed.

Resources

APPLICATION NOTES	eaton-motor-starter-ems2-setting-motor-protection-twincat3-ap034001-en-us.pdf
BROCHURES	eaton-ems2-electronic-motorstarter-brochure-br034001en-en-us.pdf
CHARACTERISTIC CURVE	eaton-contactors-ems2-reversing-starter-characteristic-curve.eps eaton-contactors-ems2-reversing-starter-characteristic-curve-003.eps
DECLARATIONS OF CONFORMITY	DA-DC-00004949.pdf DA-DC-00004946.pdf DA-DC-00004126.pdf
DRAWINGS	eaton-contactors-ems2-reversing-starter-dimensions.eps eaton-contactors-ems2-reversing-starter-3d-drawing.eps
ECAD MODEL	DA-CE-ETN.EMS2-DOS-T-3-SWD
INSTALLATION INSTRUCTIONS	eaton-ems2-electronic-motor-starter-ems2-with-swd-instruction-leaflet-il120010ZU.pdf
INSTALLATION VIDEOS	Eaton's electronic motor starter EMS2
MANUALS AND USER GUIDES	eaton-electronic-motor-starter-ems2-swd-manual-mn120008en-us.pdf
MCAD MODEL	DA-CS-ems2_dos_ros_t_swd DA-CD-ems2_dos_ros_t_swd
SALES NOTES	eaton-ems2-electronic-motorstarter-flyer-fl034007en-en-us.pdf eaton-rmq-chemical-resistance-flyer-fl047011en-en-us.pdf

PROJECT NAME:
PROJECT NUMBER:
PREPARED BY:
DATE:



Eaton Corporation plc
Eaton House
30 Pembroke Road
Dublin 4, Ireland
Eaton.com

© 2025 Eaton. All Rights Reserved.

Follow us on social media to get the latest product and support information.

