

# Specifications

## Eaton 192393

Eaton Moeller® series EMS2 DOL starter, 24 V DC, 0,18 - 3 A, Push in terminals, Controlled stop, PTB 19 ATEX 3000

### General specifications

|                             |                                                                                                                                                                                                                                                                                                                  |
|-----------------------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| <b>PRODUCT NAME</b>         | Eaton Moeller® series<br>EMS2 DOL starter                                                                                                                                                                                                                                                                        |
| <b>CATALOG NUMBER</b>       | 192393                                                                                                                                                                                                                                                                                                           |
| <b>MODEL CODE</b>           | EMS2-DOS-T-3-24VDC                                                                                                                                                                                                                                                                                               |
| <b>EAN</b>                  | 4015081930906                                                                                                                                                                                                                                                                                                    |
| <b>PRODUCT LENGTH/DEPTH</b> | 114.5 mm                                                                                                                                                                                                                                                                                                         |
| <b>PRODUCT HEIGHT</b>       | 99 mm                                                                                                                                                                                                                                                                                                            |
| <b>PRODUCT WIDTH</b>        | 22.5 mm                                                                                                                                                                                                                                                                                                          |
| <b>PRODUCT WEIGHT</b>       | 0.287 kg                                                                                                                                                                                                                                                                                                         |
| <b>CERTIFICATIONS</b>       | UL508<br>EN ISO 13849<br>IEC 61508<br>IEC/EN 60947-4-2<br>UL File No.: E338590<br>UL Category Control No.:<br>NLDX, NLDX7<br>PTB 19 ATEX 3000<br>UL 60947-4-1<br>CSA-C22.2 No. 60947-4-1-<br>14<br>CE marking<br>UL listed<br>Certified by UL for use in<br>Canada<br>UL report applies to both<br>US and Canada |



Powering Business Worldwide

## Features & Functions

|                  |                      |
|------------------|----------------------|
| <b>FUNCTIONS</b> | DOL starting         |
|                  | Temperature          |
|                  | compensated overload |
|                  | protection           |
|                  | Controlled stop      |
|                  | Motor protection     |

## General

|                                               |                                                                                                                                                                    |
|-----------------------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| <b>CLASS</b>                                  | CLASS 10                                                                                                                                                           |
| <b>CONNECTION TO SMARTWIRE-DT</b>             | No                                                                                                                                                                 |
| <b>DEGREE OF PROTECTION</b>                   | IP20<br>NEMA Other                                                                                                                                                 |
| <b>MODEL</b>                                  | Direct starter                                                                                                                                                     |
| <b>MOUNTING METHOD</b>                        | Top-hat rail fixing<br>(according to IEC/EN 60715, 35 mm)<br>Rail mounting possible                                                                                |
| <b>MOUNTING POSITION</b>                      | Vertical<br>Motor feeder at bottom                                                                                                                                 |
| <b>OVERLOAD RELEASE CURRENT SETTING - MIN</b> | 0.18 A                                                                                                                                                             |
| <b>OVERLOAD RELEASE CURRENT SETTING - MAX</b> | 3 A                                                                                                                                                                |
| <b>PRODUCT CATEGORY</b>                       | Electronic motor starter                                                                                                                                           |
| <b>RESIDUAL RIPPLE</b>                        | ≤ 5 % (input voltage)                                                                                                                                              |
| <b>TERMINAL CAPACITY</b>                      | 0.2 - 2.5 mm <sup>2</sup> , Main cables<br>0.2 - 2.5 mm <sup>2</sup> , Main cables,<br>Push-in terminals<br>0.14 - 2.5 mm <sup>2</sup> , Control<br>circuit cables |
| <b>TERMINAL CAPACITY (AWG)</b>                | 24 - 14, Main cables, Push-<br>in terminals<br>24 - 14, Main cables<br>26 - 14, Control circuit<br>cables                                                          |
| <b>TYPE</b>                                   | DOL starter (complete<br>device)                                                                                                                                   |
| <b>VOLTAGE TYPE</b>                           | DC                                                                                                                                                                 |

## Climatic environmental conditions

|                                            |        |
|--------------------------------------------|--------|
| <b>AMBIENT OPERATING TEMPERATURE - MIN</b> | -25 °C |
|--------------------------------------------|--------|

|                                            |       |
|--------------------------------------------|-------|
| <b>AMBIENT OPERATING TEMPERATURE - MAX</b> | 70 °C |
|--------------------------------------------|-------|

|                                          |        |
|------------------------------------------|--------|
| <b>AMBIENT STORAGE TEMPERATURE - MIN</b> | -40 °C |
|------------------------------------------|--------|

|                                          |       |
|------------------------------------------|-------|
| <b>AMBIENT STORAGE TEMPERATURE - MAX</b> | 80 °C |
|------------------------------------------|-------|

## Electro magnetic compatibility

|                                 |                                                                          |
|---------------------------------|--------------------------------------------------------------------------|
| <b>RADIO INTERFERENCE CLASS</b> | EN 55011<br>Class A (EN 61000-6-3,<br>emitted interference,<br>radiated) |
|---------------------------------|--------------------------------------------------------------------------|

## Electrical rating

**RATED ACTUATING  
CURRENT (IC)** 5 mA

**RATED CONDITIONAL  
SHORT-CIRCUIT CURRENT  
(IQ), TYPE 2, 380 V, 400 V,  
415 V** 0 A

**RATED CONTROL SUPPLY  
CURRENT IS** 40 mA

**RATED CONTROL SUPPLY  
VOLTAGE** 19.2 - 30 V DC

**RATED CONTROL  
VOLTAGE (UC)** 24 V (Actuating circuit ON,  
L, R)

**RATED CONTROL SUPPLY  
VOLTAGE (US) AT AC, 50  
HZ - MIN** 0 V

**RATED CONTROL SUPPLY  
VOLTAGE (US) AT AC, 50  
HZ - MAX** 0 V

**RATED CONTROL SUPPLY  
VOLTAGE (US) AT AC, 60  
HZ - MIN** 0 V

**RATED CONTROL SUPPLY  
VOLTAGE (US) AT AC, 60  
HZ - MAX** 0 V

**RATED CONTROL SUPPLY  
VOLTAGE (US) AT DC -  
MIN** 24 V

**RATED CONTROL SUPPLY  
VOLTAGE (US) AT DC -  
MAX** 24 V

**RATED OPERATIONAL  
CURRENT (IE)** 3 A

**RATED OPERATIONAL  
CURRENT (IE) AT AC-15,  
220 V, 230 V, 240 V** 2 A

**RATED OPERATIONAL  
CURRENT (IE) AT AC-3,  
380 V, 400 V, 415 V** 3 A

**RATED OPERATIONAL  
CURRENT (IE) AT AC-51** 3 A

**RATED OPERATIONAL  
CURRENT (IE) AT AC-53A -  
MAX** 3 A

**RATED OPERATIONAL  
CURRENT (IE) AT DC-13,  
24 V** 2 A

**RATED OPERATIONAL  
POWER AT AC-3, 220/230** 0.55 kW

## Contacts

**NUMBER OF AUXILIARY  
CONTACTS (NORMALLY  
CLOSED CONTACTS)** 1

**NUMBER OF AUXILIARY  
CONTACTS (NORMALLY  
OPEN CONTACTS)** 1

**NUMBER OF CONTACTS  
(CHANGE-OVER  
CONTACTS)** 1

|                                                            |                                                                                                                                                                                                                     |
|------------------------------------------------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| <b>V, 50 HZ</b>                                            |                                                                                                                                                                                                                     |
| <b>RATED OPERATIONAL POWER AT AC-3, 380/400 V, 50 HZ</b>   | 1.1 kW                                                                                                                                                                                                              |
| <b>RATED OPERATIONAL POWER AT AC-53A, 380/400 V, 50 HZ</b> | 1.1 kW                                                                                                                                                                                                              |
| <b>RATED OPERATIONAL VOLTAGE</b>                           | 500 V AC<br>42 - 550 V                                                                                                                                                                                              |
| <b>SWITCHING LEVEL</b>                                     | 19.2 - 30 V DC, Switching level "High", Actuating circuit (ON, L, R)<br>< 5 V DC, Switching level "confirm Off", Actuating circuit (ON, L, R)<br>-3 - 9.6 V DC, Switching level "Low", Actuating circuit (ON, L, R) |

| Safety                                    |                                                                                                                                                                                                                                                                                                                                                                                                                                                 |
|-------------------------------------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| <b>EXPLOSION SAFETY CATEGORY FOR DUST</b> | ATEX dust-ex-protection, II (2) G [Ex e] [Ex d] [Ex px]<br>ATEX dust-ex-protection, II (2) D [Ex t] [Ex p]                                                                                                                                                                                                                                                                                                                                      |
| <b>SAFETY PARAMETER (EN ISO 13849-1)</b>  | PL e, Performance level (safe switch off)<br>3 (safe switch off), Category 60 (safe switch off) / 70 (motor protection) years; MTTFD                                                                                                                                                                                                                                                                                                            |
| <b>SAFETY PARAMETER (IEC 62061)</b>       | Opening delay [ms]: 200 (safe switch off) / Class 10 (motor protection)<br>Adu [FIT]: 2.3 (Safe switch off) / 11 (Motor protection)<br><br>99 % (safe switch off) / 98 % (motor protection), DC SIL 3 (Safe switch off) / SIL 2 (Motor protection)<br>PFHd [FIT]: 2.3 (Safe switch off)<br>Asd [FIT]: 0<br>Add [FIT]: 580 (Safe switch off) / 601 (Motor protection)<br>99 %, SFF<br>Asu [FIT]: 1072 (Safe switch off) / 969 (Motor protection) |

| Design verification                                                               |                                            |
|-----------------------------------------------------------------------------------|--------------------------------------------|
| <b>EQUIPMENT HEAT DISSIPATION, CURRENT-DEPENDENT PVID</b>                         | 2.5 W                                      |
| <b>HEAT DISSIPATION CAPACITY PDISS</b>                                            | 0 W                                        |
| <b>HEAT DISSIPATION PER POLE, CURRENT-DEPENDENT PVID</b>                          | 0 W                                        |
| <b>RATED OPERATIONAL CURRENT FOR SPECIFIED HEAT DISSIPATION (IN)</b>              | 3 A                                        |
| <b>STATIC HEAT DISSIPATION, NON-CURRENT-DEPENDENT PVS</b>                         | 2 W                                        |
| <b>HEAT DISSIPATION DETAILS</b>                                                   | If necessary, Allow for derating           |
| <b>10.2.2 CORROSION RESISTANCE</b>                                                | Meets the product standard's requirements. |
| <b>10.2.3.1 VERIFICATION OF THERMAL STABILITY OF ENCLOSURES</b>                   | Meets the product standard's requirements. |
| <b>10.2.3.2 VERIFICATION OF RESISTANCE OF INSULATING MATERIALS TO NORMAL HEAT</b> | Meets the product standard's requirements. |
| <b>10.2.3.3 RESIST. OF INSUL. MAT. TO ABNORMAL HEAT/FIRE</b>                      | Meets the product standard's requirements. |

|                                                                 |                                                                                                                                  |
|-----------------------------------------------------------------|----------------------------------------------------------------------------------------------------------------------------------|
| <b>BY INTERNAL ELECT. EFFECTS</b>                               |                                                                                                                                  |
| <b>10.2.4 RESISTANCE TO ULTRA-VIOLET (UV) RADIATION</b>         | Meets the product standard's requirements.                                                                                       |
| <b>10.2.5 LIFTING</b>                                           | Does not apply, since the entire switchgear needs to be evaluated.                                                               |
| <b>10.2.6 MECHANICAL IMPACT</b>                                 | Does not apply, since the entire switchgear needs to be evaluated.                                                               |
| <b>10.2.7 INSCRIPTIONS</b>                                      | Meets the product standard's requirements.                                                                                       |
| <b>10.3 DEGREE OF PROTECTION OF ASSEMBLIES</b>                  | Does not apply, since the entire switchgear needs to be evaluated.                                                               |
| <b>10.4 CLEARANCES AND CREEPAGE DISTANCES</b>                   | Meets the product standard's requirements.                                                                                       |
| <b>10.5 PROTECTION AGAINST ELECTRIC SHOCK</b>                   | Does not apply, since the entire switchgear needs to be evaluated.                                                               |
| <b>10.6 INCORPORATION OF SWITCHING DEVICES AND COMPONENTS</b>   | Does not apply, since the entire switchgear needs to be evaluated.                                                               |
| <b>10.7 INTERNAL ELECTRICAL CIRCUITS AND CONNECTIONS</b>        | Is the panel builder's responsibility.                                                                                           |
| <b>10.8 CONNECTIONS FOR EXTERNAL CONDUCTORS</b>                 | Is the panel builder's responsibility.                                                                                           |
| <b>10.9.2 POWER-FREQUENCY ELECTRIC STRENGTH</b>                 | Is the panel builder's responsibility.                                                                                           |
| <b>10.9.3 IMPULSE WITHSTAND VOLTAGE</b>                         | Is the panel builder's responsibility.                                                                                           |
| <b>10.9.4 TESTING OF ENCLOSURES MADE OF INSULATING MATERIAL</b> | Is the panel builder's responsibility.                                                                                           |
| <b>10.10 TEMPERATURE RISE</b>                                   | The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices. |
| <b>10.11 SHORT-CIRCUIT RATING</b>                               | Is the panel builder's responsibility. The specifications for the switchgear must be observed.                                   |
| <b>10.12 ELECTROMAGNETIC COMPATIBILITY</b>                      | Is the panel builder's responsibility. The                                                                                       |

|                                  |                                                                                                          |
|----------------------------------|----------------------------------------------------------------------------------------------------------|
|                                  | specifications for the switchgear must be observed.                                                      |
| <b>10.13 MECHANICAL FUNCTION</b> | The device meets the requirements, provided the information in the instruction leaflet (IL) is observed. |

## Resources

|                                   |                                                                                                                                                          |
|-----------------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------|
| <b>APPLICATION NOTES</b>          | <a href="#">eaton-motor-starter-ems2-setting-motor-protection-twincat3-ap034001-en-us.pdf</a>                                                            |
| <b>BROCHURES</b>                  | <a href="#">eaton-ems2-electronic-motorstarter-brochure-br034001en-en-us.pdf</a>                                                                         |
| <b>CHARACTERISTIC CURVE</b>       | <a href="#">eaton-contactors-ems2-reversing-starter-characteristic-curve.eps</a>                                                                         |
| <b>DECLARATIONS OF CONFORMITY</b> | <a href="#">DA-DC-00004126.pdf</a><br><a href="#">DA-DC-00004948.pdf</a><br><a href="#">DA-DC-00004947.pdf</a>                                           |
| <b>DRAWINGS</b>                   | <a href="#">eaton-contactors-ems2-reversing-starter-dimensions-003.eps</a><br><a href="#">eaton-contactors-ems2-reversing-starter-3d-drawing-003.eps</a> |
| <b>ECAD MODEL</b>                 | <a href="#">DA-CE-ETN.EMS2-DOS-T-3-24VDC</a>                                                                                                             |
| <b>INSTALLATION INSTRUCTIONS</b>  | <a href="#">IL034089ZU</a>                                                                                                                               |
| <b>INSTALLATION VIDEOS</b>        | <a href="#">Eaton's electronic motor starter EMS2</a>                                                                                                    |
| <b>MANUALS AND USER GUIDES</b>    | <a href="#">eaton-electronic-motor-starter-ems2-manual-mn034003en-us.pdf</a>                                                                             |
| <b>MCAD MODEL</b>                 | <a href="#">DA-CS-ems2_dos_ros_t_24vdc</a><br><a href="#">DA-CD-ems2_dos_ros_t_24vdc</a>                                                                 |
| <b>SALES NOTES</b>                | <a href="#">eaton-ems2-electronic-motorstarter-flyer-fl034007en-en-us.pdf</a>                                                                            |

|                 |
|-----------------|
| PROJECT NAME:   |
| PROJECT NUMBER: |
| PREPARED BY:    |
| DATE:           |



**Eaton Corporation plc**  
Eaton House  
30 Pembroke Road  
Dublin 4, Ireland  
Eaton.com

© 2025 Eaton. All Rights Reserved.

Follow us on social media to get the latest product and support information.

