

Specifications



Eaton 192394

Eaton Moeller® series EMS2 Reversing starter, 24 V DC, 0,18 - 3 A, Push in terminals, Controlled stop, PTB 19 ATEX 3000

General specifications

PRODUCT NAME	Eaton Moeller® series EMS2 Reversing starter
CATALOG NUMBER	192394
MODEL CODE	EMS2-ROS-T-3-24VDC
EAN	4015081930913
PRODUCT LENGTH/DEPTH	114.5 mm
PRODUCT HEIGHT	99 mm
PRODUCT WIDTH	22.5 mm
PRODUCT WEIGHT	0.287 kg
CERTIFICATIONS	IEC/EN 60947-4-2 EN ISO 13849 IEC 61508 UL508 UL File No.: E338590 UL Category Control No.: NLDX, NLDX7 PTB 19 ATEX 3000 UL 60947-4-1 CSA-C22.2 No. 60947-4-1-14 CE marking UL listed Certified by UL for use in Canada UL report applies to both US and Canada

Features & Functions

FUNCTIONS	Motor protection
	DOL starting
	Reversing start
	Temperature
	compensated overload protection
	Controlled stop

General

CLASS	CLASS 10
CONNECTION TO SMARTWIRE-DT	No
DEGREE OF PROTECTION	IP20 NEMA Other
MODEL	Reversing starter
MOUNTING METHOD	Rail mounting possible Top-hat rail fixing (according to IEC/EN 60715, 35 mm)
MOUNTING POSITION	Motor feeder at bottom Vertical
OVERLOAD RELEASE CURRENT SETTING - MIN	0.18 A
OVERLOAD RELEASE CURRENT SETTING - MAX	3 A
PRODUCT CATEGORY	Electronic motor starter
RESIDUAL RIPPLE	≤ 5 % (input voltage)
TERMINAL CAPACITY	0.2 - 2.5 mm ² , Main cables, Push-in terminals 0.2 - 2.5 mm ² , Main cables 0.14 - 2.5 mm ² , Control circuit cables
TERMINAL CAPACITY (AWG)	24 - 14, Main cables, Push-in terminals 26 - 14, Control circuit cables 24 - 14, Main cables
TYPE	Reversing starter (complete device)
VOLTAGE TYPE	DC

Climatic environmental conditions

AMBIENT OPERATING TEMPERATURE - MIN	-25 °C
--	--------

AMBIENT OPERATING TEMPERATURE - MAX	70 °C
--	-------

AMBIENT STORAGE TEMPERATURE - MIN	40 °C
--	-------

AMBIENT STORAGE TEMPERATURE - MAX	80 °C
--	-------

Electro magnetic compatibility

RADIO INTERFERENCE CLASS	EN 55011 Class A (EN 61000-6-3, emitted interference, radiated)
---------------------------------	--

Electrical rating

RATED ACTUATING CURRENT (IC)	5 mA
-------------------------------------	------

RATED CONDITIONAL SHORT-CIRCUIT CURRENT (IQ), TYPE 2, 380 V, 400 V, 415 V	0 A
--	-----

RATED CONTROL SUPPLY CURRENT IS	40 mA
--	-------

RATED CONTROL SUPPLY VOLTAGE	19.2 - 30 V DC
-------------------------------------	----------------

RATED CONTROL VOLTAGE (UC)	24 V (Actuating circuit ON, L, R)
-----------------------------------	-----------------------------------

RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 50 HZ - MIN	0 V
---	-----

RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 50 HZ - MAX	0 V
---	-----

RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 60 HZ - MIN	0 V
---	-----

RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 60 HZ - MAX	0 V
---	-----

RATED CONTROL SUPPLY VOLTAGE (US) AT DC - MIN	24 V
--	------

RATED CONTROL SUPPLY VOLTAGE (US) AT DC - MAX	24 V
--	------

RATED OPERATIONAL CURRENT (IE)	3 A
---------------------------------------	-----

RATED OPERATIONAL CURRENT (IE) AT AC-15, 220 V, 230 V, 240 V	2 A
---	-----

RATED OPERATIONAL CURRENT (IE) AT AC-3, 380 V, 400 V, 415 V	3 A
--	-----

RATED OPERATIONAL CURRENT (IE) AT AC-51	3 A
--	-----

RATED OPERATIONAL CURRENT (IE) AT AC-53A - MAX	3 A
---	-----

RATED OPERATIONAL CURRENT (IE) AT DC-13, 24 V	2 A
--	-----

RATED OPERATIONAL POWER AT AC-3, 220/230	0.55 kW
---	---------

Contacts

NUMBER OF AUXILIARY CONTACTS (NORMALLY CLOSED CONTACTS)	1
--	---

NUMBER OF AUXILIARY CONTACTS (NORMALLY OPEN CONTACTS)	1
--	---

NUMBER OF CONTACTS (CHANGE-OVER CONTACTS)	1
--	---

V, 50 HZ	
RATED OPERATIONAL POWER AT AC-3, 380/400 V, 50 HZ	1.1 kW
RATED OPERATIONAL POWER AT AC-53A, 380/400 V, 50 HZ	1.1 kW
RATED OPERATIONAL VOLTAGE	42 - 550 V 500 V AC
SWITCHING LEVEL	19.2 - 30 V DC, Switching level "High", Actuating circuit (ON, L, R) -3 - 9.6 V DC, Switching level "Low", Actuating circuit (ON, L, R) < 5 V DC, Switching level "confirm Off", Actuating circuit (ON, L, R)

Safety	
EXPLOSION SAFETY CATEGORY FOR DUST	ATEX dust-ex-protection, II (2) G [Ex e] [Ex d] [Ex px] ATEX dust-ex-protection, II (2) D [Ex t] [Ex p]
SAFETY PARAMETER (EN ISO 13849-1)	3 (safe switch off), Category PL e, Performance level (safe switch off) 60 (safe switch off) / 70 (motor protection) years; MTTFD
SAFETY PARAMETER (IEC 62061)	99 %, SFF PFHd [FIT]: 2.3 (Safe switch off) SIL 3 (Safe switch off) / SIL 2 (Motor protection) 99 % (safe switch off) / 98 % (motor protection), DC Adu [FIT]: 2.3 (Safe switch off) / 11 (Motor protection) Asd [FIT]: 0 Asu [FIT]: 1072 (Safe switch off) / 969 (Motor protection) Add [FIT]: 580 (Safe switch off) / 601 (Motor protection) Opening delay [ms]: 200 (safe switch off) / Class 10 (motor protection)

Design verification	
EQUIPMENT HEAT DISSIPATION, CURRENT-DEPENDENT PVID	2.5 W
HEAT DISSIPATION CAPACITY PDISS	0 W
HEAT DISSIPATION PER POLE, CURRENT-DEPENDENT PVID	0 W
RATED OPERATIONAL CURRENT FOR SPECIFIED HEAT DISSIPATION (IN)	3 A
STATIC HEAT DISSIPATION, NON-CURRENT-DEPENDENT PVS	2 W
HEAT DISSIPATION DETAILS	If necessary, Allow for derating
10.2.2 CORROSION RESISTANCE	Meets the product standard's requirements.
10.2.3.1 VERIFICATION OF THERMAL STABILITY OF ENCLOSURES	Meets the product standard's requirements.
10.2.3.2 VERIFICATION OF RESISTANCE OF INSULATING MATERIALS TO NORMAL HEAT	Meets the product standard's requirements.
10.2.3.3 RESIST. OF INSUL. MAT. TO ABNORMAL HEAT/FIRE	Meets the product standard's requirements.

BY INTERNAL ELECT. EFFECTS	
10.2.4 RESISTANCE TO ULTRA-VIOLET (UV) RADIATION	Meets the product standard's requirements.
10.2.5 LIFTING	Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 MECHANICAL IMPACT	Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 INSCRIPTIONS	Meets the product standard's requirements.
10.3 DEGREE OF PROTECTION OF ASSEMBLIES	Does not apply, since the entire switchgear needs to be evaluated.
10.4 CLEARANCES AND CREEPAGE DISTANCES	Meets the product standard's requirements.
10.5 PROTECTION AGAINST ELECTRIC SHOCK	Does not apply, since the entire switchgear needs to be evaluated.
10.6 INCORPORATION OF SWITCHING DEVICES AND COMPONENTS	Does not apply, since the entire switchgear needs to be evaluated.
10.7 INTERNAL ELECTRICAL CIRCUITS AND CONNECTIONS	Is the panel builder's responsibility.
10.8 CONNECTIONS FOR EXTERNAL CONDUCTORS	Is the panel builder's responsibility.
10.9.2 POWER-FREQUENCY ELECTRIC STRENGTH	Is the panel builder's responsibility.
10.9.3 IMPULSE WITHSTAND VOLTAGE	Is the panel builder's responsibility.
10.9.4 TESTING OF ENCLOSURES MADE OF INSULATING MATERIAL	Is the panel builder's responsibility.
10.10 TEMPERATURE RISE	The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 SHORT-CIRCUIT RATING	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.12 ELECTROMAGNETIC COMPATIBILITY	Is the panel builder's responsibility. The

	specifications for the switchgear must be observed.
10.13 MECHANICAL FUNCTION	The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

Resources

APPLICATION NOTES	eaton-motor-starter-ems2-setting-motor-protection-twincat3-ap034001-en-us.pdf
BROCHURES	eaton-ems2-electronic-motorstarter-brochure-br034001en-en-us.pdf
CHARACTERISTIC CURVE	eaton-contactors-ems2-reversing-starter-characteristic-curve.eps
DECLARATIONS OF CONFORMITY	DA-DC-00004948.pdf DA-DC-00004947.pdf DA-DC-00004126.pdf
DRAWINGS	eaton-contactors-ems2-reversing-starter-dimensions-003.eps eaton-contactors-ems2-reversing-starter-3d-drawing-003.eps
ECAD MODEL	DA-CE-ETN.EMS2-ROS-T-3-24VDC
INSTALLATION INSTRUCTIONS	IL034089ZU
INSTALLATION VIDEOS	Eaton's electronic motor starter EMS2
MANUALS AND USER GUIDES	eaton-electronic-motor-starter-ems2-manual-mn034003en-us.pdf
MCAD MODEL	DA-CS-ems2_dos_ros_t_24vdc DA-CD-ems2_dos_ros_t_24vdc
SALES NOTES	eaton-ems2-electronic-motorstarter-flyer-fl034007en-en-us.pdf

PROJECT NAME:
PROJECT NUMBER:
PREPARED BY:
DATE:



Eaton Corporation plc
Eaton House
30 Pembroke Road
Dublin 4, Ireland
Eaton.com

© 2025 Eaton. All Rights Reserved.

Follow us on social media to get the latest product and support information.

