

Specifications



Photo is representative



Eaton 192751

Eaton Moeller® series MSC-DM DOL starter,
380 V 400 V 415 V: 11 kW, I_r= 20 - 25 A, 24 V
DC, DC

General specifications

PRODUCT NAME	Eaton Moeller® series MSC-DM DOL starter
CATALOG NUMBER	192751
MODEL CODE	MSC-DM-25-M25(24VDC)
EAN	4015081934959
PRODUCT LENGTH/DEPTH	97.5 mm
PRODUCT HEIGHT	197 mm
PRODUCT WIDTH	45 mm
PRODUCT WEIGHT	0.85 kg
CERTIFICATIONS	VDE 0660 IEC/EN 60947-4-1

Features & Functions

FITTED WITH:	Short-circuit release
FUNCTIONS	Temperature compensated overload protection

Climatic environmental conditions

ALTITUDE	Max. 2000 m
AMBIENT OPERATING TEMPERATURE - MIN	-25 °C
AMBIENT OPERATING TEMPERATURE - MAX	55 °C

General

CLASS	CLASS 10 A
CONNECTION	Screw terminals
CONNECTION TO SMARTWIRE-DT	No
DEGREE OF PROTECTION	IP20 NEMA Other
MODEL	IEC starter
MOUNTING METHOD	DIN rail
NUMBER OF AUXILIARY CONTACTS (NORMALLY CLOSED CONTACTS)	0
NUMBER OF AUXILIARY CONTACTS (NORMALLY OPEN CONTACTS)	1
OVERLOAD RELEASE CURRENT SETTING - MIN	20 A
OVERLOAD RELEASE CURRENT SETTING - MAX	25 A
OVERVOLTAGE CATEGORY	III
POLLUTION DEGREE	3
RATED IMPULSE WITHSTAND VOLTAGE (UIMP)	6000 V AC
SUITABLE FOR	Also motors with efficiency class IE3
TYPE	Starter with Bi-Metal release
VOLTAGE TYPE	DC

Electrical rating

RATED OPERATIONAL CURRENT (IE)	21.7 A
RATED OPERATIONAL CURRENT (IE) AT AC-3, 380 V, 400 V, 415 V	25 A
RATED OPERATIONAL POWER AT AC-3, 220/230 V, 50 HZ	5.5 kW
RATED OPERATIONAL POWER AT AC-3, 380/400 V, 50 HZ	11 kW
RATED OPERATIONAL VOLTAGE	230 - 415 V AC

Short-circuit rating

RATED CONDITIONAL SHORT-CIRCUIT CURRENT (IQ), TYPE 2, 380 V, 400 V, 415 V	50000 A
--	---------

SHORT-CIRCUIT RELEASE (IRM) - MAX	388 A
--	-------

Magnet system

POWER CONSUMPTION (SEALING) AT DC	0.5 W
--	-------

RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 50 HZ - MIN	0 V
---	-----

RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 50 HZ - MAX	0 V
---	-----

RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 60 HZ - MIN	0 V
---	-----

RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 60 HZ - MAX	0 V
---	-----

RATED CONTROL SUPPLY VOLTAGE (US) AT DC - MIN	24 V
--	------

RATED CONTROL SUPPLY VOLTAGE (US) AT DC - MAX	24 V
--	------

Design verification

10.2.2 CORROSION RESISTANCE Meets the product standard's requirements.

10.2.3.1 VERIFICATION OF THERMAL STABILITY OF ENCLOSURES Meets the product standard's requirements.

10.2.3.2 VERIFICATION OF RESISTANCE OF INSULATING MATERIALS TO NORMAL HEAT Meets the product standard's requirements.

10.2.3.3 RESIST. OF INSUL. MAT. TO ABNORMAL HEAT/FIRE BY INTERNAL ELECT. EFFECTS Meets the product standard's requirements.

10.2.4 RESISTANCE TO ULTRA-VIOLET (UV) RADIATION Meets the product standard's requirements.

10.2.5 LIFTING Does not apply, since the entire switchgear needs to be evaluated.

10.2.6 MECHANICAL IMPACT Does not apply, since the entire switchgear needs to be evaluated.

10.2.7 INSCRIPTIONS Meets the product standard's requirements.

10.3 DEGREE OF PROTECTION OF ASSEMBLIES Does not apply, since the entire switchgear needs to be evaluated.

10.4 CLEARANCES AND CREEPAGE DISTANCES Meets the product standard's requirements.

10.5 PROTECTION AGAINST ELECTRIC SHOCK Does not apply, since the entire switchgear needs to be evaluated.

10.6 INCORPORATION OF SWITCHING DEVICES AND COMPONENTS Does not apply, since the entire switchgear needs to be evaluated.

10.7 INTERNAL ELECTRICAL CIRCUITS AND CONNECTIONS Is the panel builder's responsibility.

10.8 CONNECTIONS FOR EXTERNAL CONDUCTORS Is the panel builder's responsibility.

10.9.2 POWER-FREQUENCY ELECTRIC STRENGTH Is the panel builder's responsibility.

10.9.3 IMPULSE WITHSTAND VOLTAGE Is the panel builder's responsibility.

10.9.4 TESTING OF ENCLOSURES MADE OF Is the panel builder's responsibility.

Resources

BROCHURES

[eaton-motor-starters-system-xstart-brochure-br03407001en-en-us.pdf](#)

[eaton-msfs-motor-starter-feeder-system-brochure-br034005en-en-us.pdf](#)

CATALOGUES

[Product Range Catalog Switching and protecting motors](#)

[eaton-product-overview-for-machinery-catalogue-ca08103003zen-en-us.pdf](#)

DECLARATIONS OF CONFORMITY

[eaton-dol-starter-declaration-of-conformity-uk251159en.pdf](#)

[eaton-dol-starter-declaration-of-conformity-eu250676en.pdf](#)

DRAWINGS

[eaton-manual-motor-starters-msc-d-dol-starter-dimensions-003.eps](#)

[eaton-manual-motor-starters-msc-d-dol-starter-3d-drawing-004.eps](#)

[eaton-general-ie-ready-dilm-contactor-standards.eps](#)

[eaton-manual-motor-starters-mounting-msc-d-dol-starter-3d-drawing.eps](#)

ECAD MODEL

[ETN.192751.edz](#)

INSTALLATION INSTRUCTIONS

[IL034054ZU](#)

INSTALLATION VIDEOS

[WIN-WIN with push-in technology](#)

MCAD MODEL

[msc_dm_bg2.stp](#)

[msc_dm_bg2.dwg](#)

SALES NOTES

[eaton-link-module-for-motor-starters-pkz-flyer-fl034003en-en-us.pdf](#)

WIRING DIAGRAMS

[eaton-manual-motor-starters-device-msc-d-dol-starter-wiring-diagram.eps](#)

INSULATING MATERIAL

10.10 TEMPERATURE RISE

The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.

10.11 SHORT-CIRCUIT RATING

Is the panel builder's responsibility. The specifications for the switchgear must be observed.

10.12 ELECTROMAGNETIC COMPATIBILITY

Is the panel builder's responsibility. The specifications for the switchgear must be observed.

10.13 MECHANICAL FUNCTION

The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

PROJECT NAME:

PROJECT NUMBER:

PREPARED BY:

DATE:

**Eaton Corporation plc**

Eaton House
30 Pembroke Road
Dublin 4, Ireland
Eaton.com

© 2025 Eaton. All Rights Reserved.

Follow us on social media to get the latest product and support information.

