

Specifications

Eaton 197165

Eaton Moeller® series EMS2 Reversing starter, 24 V DC, 1,5 - 6,5 (AC-53a), 9 (AC-51) A, Screw terminals

General specifications

PRODUCT NAME	Eaton Moeller® series EMS2 Reversing starter
CATALOG NUMBER	197165
MODEL CODE	EMS2-RO-Z-9-24VDC
EAN	4015080896067
PRODUCT LENGTH/DEPTH	114.5 mm
PRODUCT HEIGHT	99 mm
PRODUCT WIDTH	22.5 mm
PRODUCT WEIGHT	0.287 kg
CERTIFICATIONS	UL508 IEC/EN 60947-4-2 UL File No.: E29096 UL Category Control No.: NLDX, NLDX7 UL 60947-4-1 CSA-C22.2 No. 60947-4-1- 14 CE marking UL listed Certified by UL for use in Canada UL report applies to both US and Canada

Features & Functions

FUNCTIONS	DOL starting
	Temperature
	compensated overload
	protection
	Reversing start
	Motor protection

Climatic environmental conditions

AMBIENT OPERATING TEMPERATURE - MIN	-25 °C
--	--------

AMBIENT OPERATING TEMPERATURE - MAX	70 °C
--	-------

AMBIENT STORAGE TEMPERATURE - MIN	40 °C
--	-------

AMBIENT STORAGE TEMPERATURE - MAX	80 °C
--	-------

General

CLASS	CLASS 10
--------------	----------

CONNECTION TO SMARTWIRE-DT	No
---------------------------------------	----

DEGREE OF PROTECTION	IP20
	NEMA Other

MODEL	Reversing starter
--------------	-------------------

MOUNTING METHOD	Rail mounting possible
	Top-hat rail fixing
	(according to IEC/EN 60715, 35 mm)

MOUNTING POSITION	Motor feeder at bottom Vertical
--------------------------	------------------------------------

OVERLOAD RELEASE CURRENT SETTING - MIN	1.5 A
---	-------

OVERLOAD RELEASE CURRENT SETTING - MAX	9 A
---	-----

PRODUCT CATEGORY	Electronic motor starter
-------------------------	--------------------------

RESIDUAL RIPPLE	≤ 5 % (input voltage)
------------------------	-----------------------

TERMINAL CAPACITY	0.2 - 2.5 mm ² , Main cables
	0.2 - 2.5 mm ² , Main cables,
	Push-in terminals
	0.14 - 2.5 mm ² , Control circuit cables

TERMINAL CAPACITY (AWG)	26 - 14, Control circuit cables
	24 - 14, Main cables

TYPE	Reversing starter (complete device)
-------------	--

VOLTAGE TYPE	DC
---------------------	----

Electro magnetic compatibility

RADIO INTERFERENCE CLASS	EN 55011
	Class A (EN 61000-6-3,
	emitted interference, radiated)

Electrical rating

RATED ACTUATING CURRENT (IC)	5 mA
-------------------------------------	------

RATED CONDITIONAL SHORT-CIRCUIT CURRENT (IQ), TYPE 2, 380 V, 400 V, 415 V	0 A
--	-----

RATED CONTROL SUPPLY CURRENT IS	40 mA
--	-------

RATED CONTROL SUPPLY VOLTAGE	19.2 - 30 V DC
-------------------------------------	----------------

RATED CONTROL VOLTAGE (UC)	24 V (Actuating circuit ON, L, R)
-----------------------------------	-----------------------------------

RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 50 HZ - MIN	0 V
---	-----

RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 50 HZ - MAX	0 V
---	-----

RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 60 HZ - MIN	0 V
---	-----

RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 60 HZ - MAX	0 V
---	-----

RATED CONTROL SUPPLY VOLTAGE (US) AT DC - MIN	24 V
--	------

RATED CONTROL SUPPLY VOLTAGE (US) AT DC - MAX	24 V
--	------

RATED OPERATIONAL CURRENT (IE)	9 A
---------------------------------------	-----

RATED OPERATIONAL CURRENT (IE) AT AC-15, 220 V, 230 V, 240 V	3 A
---	-----

RATED OPERATIONAL CURRENT (IE) AT AC-3, 380 V, 400 V, 415 V	6.5 A
--	-------

RATED OPERATIONAL CURRENT (IE) AT AC-51	9 A
--	-----

RATED OPERATIONAL CURRENT (IE) AT AC-53A - MAX	6.5 A
---	-------

RATED OPERATIONAL CURRENT (IE) AT DC-13, 24 V	2 A
--	-----

RATED OPERATIONAL POWER AT AC-3, 220/230	1.5 kW
---	--------

Contacts

NUMBER OF AUXILIARY CONTACTS (NORMALLY CLOSED CONTACTS)	1
--	---

NUMBER OF AUXILIARY CONTACTS (NORMALLY OPEN CONTACTS)	1
--	---

NUMBER OF CONTACTS (CHANGE-OVER CONTACTS)	1
--	---

V, 50 HZ	
RATED OPERATIONAL POWER AT AC-3, 380/400 V, 50 HZ	3 kW
RATED OPERATIONAL POWER AT AC-53A, 380/400 V, 50 HZ	3 kW
RATED OPERATIONAL VOLTAGE	500 V AC 42 - 550 V
SWITCHING LEVEL	-3 - 9.6 V DC, Switching level "Low", Actuating circuit (ON, L, R) 19.2 - 30 V DC, Switching level "High", Actuating circuit (ON, L, R)

Design verification

EQUIPMENT HEAT DISSIPATION, CURRENT-DEPENDENT PVID 14.6 W

HEAT DISSIPATION CAPACITY PDISS 0 W

HEAT DISSIPATION PER POLE, CURRENT-DEPENDENT PVID 0 W

RATED OPERATIONAL CURRENT FOR SPECIFIED HEAT DISSIPATION (IN) 9 A

STATIC HEAT DISSIPATION, NON-CURRENT-DEPENDENT PVS 1 W

HEAT DISSIPATION DETAILS If necessary, Allow for derating

10.2.2 CORROSION RESISTANCE Meets the product standard's requirements.

10.2.3.1 VERIFICATION OF THERMAL STABILITY OF ENCLOSURES Meets the product standard's requirements.

10.2.3.2 VERIFICATION OF RESISTANCE OF INSULATING MATERIALS TO NORMAL HEAT Meets the product standard's requirements.

10.2.3.3 RESIST. OF INSUL. MAT. TO ABNORMAL HEAT/FIRE BY INTERNAL ELECT. EFFECTS Meets the product standard's requirements.

10.2.4 RESISTANCE TO ULTRA-VIOLET (UV) RADIATION Meets the product standard's requirements.

10.2.5 LIFTING Does not apply, since the entire switchgear needs to be evaluated.

10.2.6 MECHANICAL IMPACT Does not apply, since the entire switchgear needs to be evaluated.

10.2.7 INSCRIPTIONS Meets the product standard's requirements.

10.3 DEGREE OF PROTECTION OF ASSEMBLIES Does not apply, since the entire switchgear needs to be evaluated.

10.4 CLEARANCES AND CREEPAGE DISTANCES Meets the product standard's requirements.

10.5 PROTECTION Does not apply, since the

Resources

APPLICATION NOTES [eaton-motor-starter-ems2-setting-motor-protection-twincat3-ap034001-en-us.pdf](#)

BROCHURES [eaton-ems2-electronic-motorstarter-brochure-br034001en-en-us.pdf](#)

[eaton-contactors-ems2-reversing-starter-characteristic-curve.eps](#)

CHARACTERISTIC CURVE [eaton-contactors-ems2-reversing-starter-characteristic-curve-004.eps](#)

[eaton-contactors-ems2-reversing-starter-characteristic-curve-002.eps](#)

DECLARATIONS OF CONFORMITY [DA-DC-00004192.pdf](#)
[DA-DC-00003980.pdf](#)

[eaton-contactors-ems2-reversing-starter-dimensions-002.eps](#)

DRAWINGS [eaton-contactors-ems2-reversing-starter-3d-drawing-002.eps](#)

ECAD MODEL [DA-CE-ETN.EMS2-RO-Z-9-24VDC](#)

INSTALLATION INSTRUCTIONS [IL034064ZU](#)

INSTALLATION VIDEOS [Eaton's electronic motor starter EMS2](#)

MANUALS AND USER GUIDES [eaton-electronic-motor-starter-ems2-manual-mn034003en-us.pdf](#)

MCAD MODEL [DA-CS-ems2_dos_ros_z_24_230v](#)
[DA-CD-ems2_dos_ros_z_24_230v](#)

SALES NOTES [eaton-ems2-electronic-motorstarter-flyer-fl034007en-en-us.pdf](#)

AGAINST ELECTRIC SHOCK	entire switchgear needs to be evaluated.
10.6 INCORPORATION OF SWITCHING DEVICES AND COMPONENTS	Does not apply, since the entire switchgear needs to be evaluated.
10.7 INTERNAL ELECTRICAL CIRCUITS AND CONNECTIONS	Is the panel builder's responsibility.
10.8 CONNECTIONS FOR EXTERNAL CONDUCTORS	Is the panel builder's responsibility.
10.9.2 POWER-FREQUENCY ELECTRIC STRENGTH	Is the panel builder's responsibility.
10.9.3 IMPULSE WITHSTAND VOLTAGE	Is the panel builder's responsibility.
10.9.4 TESTING OF ENCLOSURES MADE OF INSULATING MATERIAL	Is the panel builder's responsibility.
10.10 TEMPERATURE RISE	The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 SHORT-CIRCUIT RATING	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.12 ELECTROMAGNETIC COMPATIBILITY	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.13 MECHANICAL FUNCTION	The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

PROJECT NAME:
PROJECT NUMBER:
PREPARED BY:
DATE:



Eaton Corporation plc
Eaton House
30 Pembroke Road
Dublin 4, Ireland
Eaton.com

© 2025 Eaton. All Rights Reserved.

Follow us on social media to get the latest product and support information.

