

Specifications

Photo is representative

Eaton 197170

Eaton Moeller® series EMS2 DOL starter,
230 V AC, 1,5 - 6,5 (AC-53a), 9 (AC-51) A,
Screw terminals

General specifications

PRODUCT NAME	Eaton Moeller® series EMS2 DOL starter
CATALOG NUMBER	197170
MODEL CODE	EMS2-DO-Z-9-230VAC
EAN	4015080896111
PRODUCT LENGTH/DEPTH	114.5 mm
PRODUCT HEIGHT	99 mm
PRODUCT WIDTH	22.5 mm
PRODUCT WEIGHT	0.287 kg
CERTIFICATIONS	UL508 IEC/EN 60947-4-2 UL File No.: E29096 UL Category Control No.: NLDX, NLDX7 UL 60947-4-1 CSA-C22.2 No. 60947-4-1- 14 CE marking UL listed Certified by UL for use in Canada UL report applies to both US and Canada

Features & Functions

FUNCTIONS	Temperature
	compensated overload
	protection
	DOL starting
	Motor protection

Climatic environmental conditions

AMBIENT OPERATING TEMPERATURE - MIN	-25 °C
--	--------

AMBIENT OPERATING TEMPERATURE - MAX	70 °C
--	-------

AMBIENT STORAGE TEMPERATURE - MIN	40 °C
--------------------------------------	-------

AMBIENT STORAGE TEMPERATURE - MAX	80 °C
--------------------------------------	-------

General

CLASS	CLASS 10 A
-------	------------

CONNECTION TO SMARTWIRE-DT	No
-------------------------------	----

DEGREE OF PROTECTION	IP20 NEMA Other
----------------------	--------------------

MODEL	Direct starter
-------	----------------

MOUNTING METHOD	Top-hat rail fixing (according to IEC/EN 60715, 35 mm) Rail mounting possible
-----------------	--

MOUNTING POSITION	Motor feeder at bottom Vertical
-------------------	------------------------------------

OVERLOAD RELEASE CURRENT SETTING - MIN	1.5 A
---	-------

OVERLOAD RELEASE CURRENT SETTING - MAX	9 A
---	-----

PRODUCT CATEGORY	Electronic motor starter
------------------	--------------------------

TERMINAL CAPACITY	0.2 - 2.5 mm ² , Main cables 0.14 - 2.5 mm ² , Control circuit cables
-------------------	---

TERMINAL CAPACITY (AWG)	24 - 14, Main cables 26 - 14, Control circuit cables
----------------------------	--

TYPE	DOL starter (complete device)
------	----------------------------------

VOLTAGE TYPE	AC
--------------	----

Electro magnetic compatibility

RADIO INTERFERENCE CLASS	Class A (EN 61000-6-3, emitted interference, radiated) EN 55011
-----------------------------	--

Electrical rating

RATED ACTUATING CURRENT (IC)	7 mA
-------------------------------------	------

RATED CONDITIONAL SHORT-CIRCUIT CURRENT (IQ), TYPE 2, 380 V, 400 V, 415 V	0 A
--	-----

RATED CONTROL SUPPLY CURRENT IS	4 mA
--	------

RATED CONTROL SUPPLY VOLTAGE	85 - 253 V AC
-------------------------------------	---------------

RATED CONTROL VOLTAGE (UC)	230 V (Actuating circuit ON, L, R)
-----------------------------------	------------------------------------

RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 50 HZ - MIN	230 V
---	-------

RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 50 HZ - MAX	230 V
---	-------

RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 60 HZ - MIN	0 V
---	-----

RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 60 HZ - MAX	0 V
---	-----

RATED CONTROL SUPPLY VOLTAGE (US) AT DC - MIN	0 V
--	-----

RATED CONTROL SUPPLY VOLTAGE (US) AT DC - MAX	0 V
--	-----

RATED OPERATIONAL CURRENT (IE)	9 A
---------------------------------------	-----

RATED OPERATIONAL CURRENT (IE) AT AC-15, 220 V, 230 V, 240 V	3 A
---	-----

RATED OPERATIONAL CURRENT (IE) AT AC-3, 380 V, 400 V, 415 V	6.5 A
--	-------

RATED OPERATIONAL CURRENT (IE) AT AC-51	9 A
--	-----

RATED OPERATIONAL CURRENT (IE) AT AC-53A - MAX	6.5 A
---	-------

RATED OPERATIONAL CURRENT (IE) AT DC-13, 24 V	2 A
--	-----

RATED OPERATIONAL POWER AT AC-3, 220/230	1.5 kW
---	--------

Contacts

NUMBER OF AUXILIARY CONTACTS (NORMALLY CLOSED CONTACTS)	1
--	---

NUMBER OF AUXILIARY CONTACTS (NORMALLY OPEN CONTACTS)	1
--	---

NUMBER OF CONTACTS (CHANGE-OVER CONTACTS)	1
--	---

V, 50 HZ	
RATED OPERATIONAL POWER AT AC-3, 380/400 V, 50 HZ	3 kW
RATED OPERATIONAL POWER AT AC-53A, 380/400 V, 50 HZ	3 kW
RATED OPERATIONAL VOLTAGE	42 - 550 V 500 V AC
SWITCHING LEVEL	0 - 44 V AC, Switching level "Low", Actuating circuit (ON, L, R) 85 - 253 V AC, Switching level "High", Actuating circuit (ON, L, R)

Design verification

EQUIPMENT HEAT DISSIPATION, CURRENT-DEPENDENT PVID	16.1 W
HEAT DISSIPATION CAPACITY PDISS	0 W
HEAT DISSIPATION PER POLE, CURRENT-DEPENDENT PVID	0 W
RATED OPERATIONAL CURRENT FOR SPECIFIED HEAT DISSIPATION (IN)	9 A
STATIC HEAT DISSIPATION, NON-CURRENT-DEPENDENT PVS	1 W
HEAT DISSIPATION DETAILS	If necessary, Allow for derating
10.2.2 CORROSION RESISTANCE	Meets the product standard's requirements.
10.2.3.1 VERIFICATION OF THERMAL STABILITY OF ENCLOSURES	Meets the product standard's requirements.
10.2.3.2 VERIFICATION OF RESISTANCE OF INSULATING MATERIALS TO NORMAL HEAT	Meets the product standard's requirements.
10.2.3.3 RESIST. OF INSUL. MAT. TO ABNORMAL HEAT/FIRE BY INTERNAL ELECT. EFFECTS	Meets the product standard's requirements.
10.2.4 RESISTANCE TO ULTRA-VIOLET (UV) RADIATION	Meets the product standard's requirements.
10.2.5 LIFTING	Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 MECHANICAL IMPACT	Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 INSCRIPTIONS	Meets the product standard's requirements.
10.3 DEGREE OF PROTECTION OF ASSEMBLIES	Does not apply, since the entire switchgear needs to be evaluated.
10.4 CLEARANCES AND CREEPAGE DISTANCES	Meets the product standard's requirements.
10.5 PROTECTION	Does not apply, since the

Resources

APPLICATION NOTES	eaton-motor-starter-ems2-setting-motor-protection-twincat3-ap034001-en-us.pdf
BROCHURES	eaton-ems2-electronic-motorstarter-brochure-br034001en-en-us.pdf
CHARACTERISTIC CURVE	eaton-contactors-ems2-reversing-starter-characteristic-curve.eps eaton-contactors-ems2-reversing-starter-characteristic-curve-004.eps eaton-contactors-ems2-reversing-starter-characteristic-curve-002.eps
DECLARATIONS OF CONFORMITY	DA-DC-00003980.pdf DA-DC-00004192.pdf
DRAWINGS	eaton-contactors-ems2-reversing-starter-dimensions-002.eps eaton-contactors-ems2-reversing-starter-3d-drawing-002.eps
ECAD MODEL	DA-CE-ETN.EMS2-DO-Z-9-230VAC
INSTALLATION INSTRUCTIONS	IL034064ZU
INSTALLATION VIDEOS	Eaton's electronic motor starter EMS2
MANUALS AND USER GUIDES	eaton-electronic-motor-starter-ems2-manual-mn034003en-us.pdf
MCAD MODEL	DA-CS-ems2_dos_ros_z_24_230v DA-CD-ems2_dos_ros_z_24_230v
SALES NOTES	eaton-ems2-electronic-motorstarter-flyer-fl034007en-en-us.pdf

AGAINST ELECTRIC SHOCK	entire switchgear needs to be evaluated.
10.6 INCORPORATION OF SWITCHING DEVICES AND COMPONENTS	Does not apply, since the entire switchgear needs to be evaluated.
10.7 INTERNAL ELECTRICAL CIRCUITS AND CONNECTIONS	Is the panel builder's responsibility.
10.8 CONNECTIONS FOR EXTERNAL CONDUCTORS	Is the panel builder's responsibility.
10.9.2 POWER-FREQUENCY ELECTRIC STRENGTH	Is the panel builder's responsibility.
10.9.3 IMPULSE WITHSTAND VOLTAGE	Is the panel builder's responsibility.
10.9.4 TESTING OF ENCLOSURES MADE OF INSULATING MATERIAL	Is the panel builder's responsibility.
10.10 TEMPERATURE RISE	The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 SHORT-CIRCUIT RATING	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.12 ELECTROMAGNETIC COMPATIBILITY	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.13 MECHANICAL FUNCTION	The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

PROJECT NAME:
PROJECT NUMBER:
PREPARED BY:
DATE:



Eaton Corporation plc
Eaton House
30 Pembroke Road
Dublin 4, Ireland
Eaton.com

© 2025 Eaton. All Rights Reserved.

Follow us on social media to get the latest product and support information.

