


Tunnel terminal and cover, 3 poles

Part no. NZM4-XKA

Article no. 266836



Delivery programme

Rated current	I _n	A	≦ 1400
For use with			
For use with			NZM4, N(S)4
For use with			3 pole
Terminal capacities			
Type of conductor			
Cu/Al cable			Copper cable Al cable
Terminal capacities			
flexible		mm ²	1 x 50 - 240 4 x 50 - 240 1 x 50 - 240 4 x 50 - 240
AWG/kcmil			
flexible		mm ²	1 x 0 - 500 4 x 0 - 500 1 x 0 - 500 4 x 0 - 500
Notes			
Type contains parts for a terminal located at top or bottom for 3 or 4-pole circuit-breakers.			
A standard with control circuit terminal for 1 x 0.75 - 2.5 mm ² (18 - 14 AWG) or 2 x 0.75 - 1.5 mm ² (18 - 16 AWG) copper conductors.			
Can be fitted to circuit-breaker with screw termination			
Use with flexible and highly flexible conductors ferrules.			
Mounting of the cover NZM4 (-4)-XKSA obligatory (supplied).			
Notes			
The following applies for the rated current: The values have been determined conform to IEC/EN 60947 (switchgear standard) and generally relate to the max. defined cross-sections and are intended for the purpose of orientation.			
The engineering standards which apply in each case must be observed.			

Approbationen

Product Standards	UL489; CSA-C22.2 No. 5-09; IEC60947, CE marking
UL File No.	E31593
UL CCN	DIHS
CSA File No.	22086
CSA Class No.	1432-01
NA Certification	UL Listed, CSA certified
Suitable for	Refer to main component information

Technische Daten nach ETIM 4.0

Suitable for number of poles			3
Type			-

Dimensions

