## SIEMENS

## Data sheet

## 3LD2264-2TW53-0US2



SENTRON, Switch disconnector 3LD, emergency switching-off switch, 3pole, Iu: 32 A, operating power / at AC-23 A 400 V: 11.5 kW, molded-plastic encapsulation for inch screw connection 4 NO, rotary operating mechanism, red/yellow

| Model   |  |
|---|--|
| product brand name  | SENTRON  |
| product designation   | 3LD Switch disconnector                          |
| design of the product   | EMERGENCY-STOP switch                            |
| display version for switch position indicator manual operation                      | 1 ON - 0 OFF                                     |
| type of switch  | Molded-plastic enclosure for inch threaded joint |
| design of the actuating element   | Short rotary knob                                |
| color of the actuating element  | red  |
| design of handle  | rotary operating mechanism, red/yellow           |
| type of the driving mechanism motor drive   | No   |
| General technical data  |  |
| number of poles   | 3  |
| size of switch disconnector   | 2  |
| mechanical service life (operating cycles) typical                                  | 100 000  |
| electrical endurance (operating cycles)   |  |
| • at AC-23 A at 690 V   | 6 000  |
| operating frequency maximum   | 50 1/h   |
| degree of pollution   | 3  |
| Voltage   |  |
| insulation voltage rated value  | 690 V  |
| surge voltage resistance rated value  | 6 kV   |
| operating voltage   |  |
| <ul> <li>at AC rated value</li> </ul>   | 690 V  |
| operating frequency rated value   |  |
| • minimum   | 50 Hz  |
| • maximum   | 60 Hz  |
| Protection class  |  |
| protection class IP   | IP65   |
| degree of protection NEMA rating  | 1, 4X, 12  |
| protection class IP on the front  | IP65   |
| Dissipation   |  |
| power loss [W] for rated value of the current at AC in hot operating state per pole | 1.8 W  |
| Current   |  |
| operational current rated value   | 32 A   |
| operational current   |  |
| <ul> <li>at 40 °C rated value</li> </ul>  | 32 A   |
| • at 45 °C rated value  | 32 A   |
| <ul> <li>at 50 °C rated value</li> </ul>  | 32 A   |
| <ul> <li>at 55 °C rated value</li> </ul>  | 32 A   |

| <ul> <li>at AC rated value</li> </ul>  | 32 A   |
|--|--|
| Main circuit   |  |
| operational current  |  |
| at AC-21 at 690 V rated value  | 32 A   |
| • at AC-21 A at 240 V rated value  | 32 A   |
| • at AC-21 A at 400 V rated value  | 32 A   |
| • at AC-21 A at 440 V rated value  | 32 A   |
| • at AC-23 A at 400 V rated value  | 22 A   |
| operating power  |  |
| • at AC-23 A at 240 V rated value  | 6 kW   |
| • at AC-23 A at 400 V rated value  | 12 kW  |
| <ul> <li>at AC-23 A at 440 V rated value</li> </ul>  | 11.5 kW  |
| • at AC-23 A at 690 V rated value  | 12 kW  |
| <ul> <li>at AC-3 at 240 V rated value</li> </ul>   | 5.5 kW   |
| <ul> <li>at AC-3 at 400 V rated value</li> </ul>   | 10 kW  |
| <ul> <li>at AC-3 at 690 V rated value</li> </ul>   | 9.5 kW   |
| Auxiliary circuit  |  |
| number of CO contacts for auxiliary contacts   | 0  |
| number of NC contacts for auxiliary contacts   | 0  |
| number of NO contacts for auxiliary contacts   | 4  |
| operating voltage of auxiliary contacts at AC maximum  | 500 V  |
| continuous current of the auxiliary contact rated value  | 10 A   |
| insulation voltage of the auxiliary switch rated value   | 500 V  |
| Suitability  |  |
| suitability for use  |  |
| main switch  | Yes  |
| switch disconnector  | Yes  |
| EMERGENCY OFF switch   | Yes  |
| safety switch  | Yes  |
| maintenance/repair switch  | Yes  |
| Product details  |  |
| product feature can be locked into OFF position  | Yes  |
| accessories  |  |
| product extension optional   |  |
|  |  |
|  | No   |
| motor drive  | No   |
| <ul><li>motor drive</li><li>voltage trigger</li></ul>  | No   |
| motor drive  |  |
| <ul> <li>motor drive</li> <li>voltage trigger</li> <li>number of connectable NC contacts for auxiliary contacts</li> </ul>   | No   |
| <ul> <li>motor drive</li> <li>voltage trigger</li> <li>number of connectable NC contacts for auxiliary contacts attachable maximum</li> <li>number of connectable NO contacts for auxiliary contacts</li> </ul>  | No<br>2  |
| <ul> <li>motor drive</li> <li>voltage trigger</li> <li>number of connectable NC contacts for auxiliary contacts attachable maximum</li> <li>number of connectable NO contacts for auxiliary contacts attachable maximum</li> <li>number of connectable CO contacts for auxiliary contacts</li> </ul>   | No<br>2<br>3   |
| <ul> <li>motor drive</li> <li>voltage trigger</li> <li>number of connectable NC contacts for auxiliary contacts attachable maximum</li> <li>number of connectable NO contacts for auxiliary contacts attachable maximum</li> <li>number of connectable CO contacts for auxiliary contacts attachable maximum</li> </ul>  | No<br>2<br>3<br>0  |
| <ul> <li>motor drive</li> <li>voltage trigger</li> <li>number of connectable NC contacts for auxiliary contacts attachable maximum</li> <li>number of connectable NO contacts for auxiliary contacts attachable maximum</li> <li>number of connectable CO contacts for auxiliary contacts attachable maximum</li> <li>number of bracket locks maximum</li> </ul>   | No<br>2<br>3<br>0<br>3   |
| <ul> <li>motor drive</li> <li>voltage trigger</li> <li>number of connectable NC contacts for auxiliary contacts attachable maximum</li> <li>number of connectable NO contacts for auxiliary contacts attachable maximum</li> <li>number of connectable CO contacts for auxiliary contacts attachable maximum</li> <li>number of bracket locks maximum</li> <li>hasp thickness of the bracket locks</li> <li>Short circuit</li> <li>conditional short-circuit current with line-side fuse</li> </ul>  | No<br>2<br>3<br>0<br>3   |
| <ul> <li>motor drive</li> <li>voltage trigger</li> <li>number of connectable NC contacts for auxiliary contacts attachable maximum</li> <li>number of connectable NO contacts for auxiliary contacts attachable maximum</li> <li>number of connectable CO contacts for auxiliary contacts attachable maximum</li> <li>number of bracket locks maximum</li> <li>number of bracket locks maximum</li> <li>hasp thickness of the bracket locks</li> <li>Short circuit</li> <li>conditional short-circuit current with line-side fuse protection</li> </ul>  | No<br>2<br>3<br>0<br>3<br>4 8 mm   |
| <ul> <li>motor drive</li> <li>voltage trigger</li> <li>number of connectable NC contacts for auxiliary contacts attachable maximum</li> <li>number of connectable NO contacts for auxiliary contacts attachable maximum</li> <li>number of connectable CO contacts for auxiliary contacts attachable maximum</li> <li>number of bracket locks maximum</li> <li>number of bracket locks maximum</li> <li>hasp thickness of the bracket locks</li> <li>Short circuit</li> <li>conditional short-circuit current with line-side fuse protection</li> <li>at 690 V by gG fuse rated value</li> </ul>   | No<br>2<br>3<br>0<br>3   |
| <ul> <li>motor drive</li> <li>voltage trigger</li> <li>number of connectable NC contacts for auxiliary contacts attachable maximum</li> <li>number of connectable NO contacts for auxiliary contacts attachable maximum</li> <li>number of connectable CO contacts for auxiliary contacts attachable maximum</li> <li>number of bracket locks maximum</li> <li>number of bracket locks maximum</li> <li>hasp thickness of the bracket locks</li> <li>Short circuit</li> <li>conditional short-circuit current with line-side fuse protection</li> <li>at 690 V by gG fuse rated value</li> <li>let-through current with closed switch</li> </ul>   | No<br>2<br>3<br>0<br>3<br>4 8 mm<br>50 kA  |
| <ul> <li>motor drive</li> <li>voltage trigger</li> <li>number of connectable NC contacts for auxiliary contacts attachable maximum</li> <li>number of connectable NO contacts for auxiliary contacts attachable maximum</li> <li>number of connectable CO contacts for auxiliary contacts attachable maximum</li> <li>number of bracket locks maximum</li> <li>number of bracket locks maximum</li> <li>hasp thickness of the bracket locks</li> </ul> Short circuit conditional short-circuit current with line-side fuse protection <ul> <li>at 690 V by gG fuse rated value</li> <li>let-through current with closed switch</li> <li>at 240 V for combination switch + gG fuse maximum</li> </ul>   | No<br>2<br>3<br>0<br>3<br>4 8 mm<br>50 kA<br>4.5 kA  |
| <ul> <li>motor drive</li> <li>voltage trigger</li> <li>number of connectable NC contacts for auxiliary contacts attachable maximum</li> <li>number of connectable NO contacts for auxiliary contacts attachable maximum</li> <li>number of connectable CO contacts for auxiliary contacts attachable maximum</li> <li>number of bracket locks maximum</li> <li>number of bracket locks maximum</li> <li>hasp thickness of the bracket locks</li> <li>Short circuit</li> <li>conditional short-circuit current with line-side fuse protection         <ul> <li>at 690 V by gG fuse rated value</li> <li>let-through current with closed switch</li> <li>at 240 V for combination switch + gG fuse maximum</li> <li>at 440 V for combination switch + gG fuse maximum</li> </ul> </li> </ul>   | No<br>2<br>3<br>0<br>3<br>4 8 mm<br>50 kA<br>4.5 kA<br>4.5 kA  |
| <ul> <li>motor drive</li> <li>voltage trigger</li> <li>number of connectable NC contacts for auxiliary contacts attachable maximum</li> <li>number of connectable NO contacts for auxiliary contacts attachable maximum</li> <li>number of connectable CO contacts for auxiliary contacts attachable maximum</li> <li>number of bracket locks maximum</li> <li>number of bracket locks maximum</li> <li>hasp thickness of the bracket locks</li> </ul> Short circuit conditional short-circuit current with line-side fuse protection <ul> <li>at 690 V by gG fuse rated value</li> <li>let-through current with closed switch</li> <li>at 240 V for combination switch + gG fuse maximum</li> </ul>   | No<br>2<br>3<br>0<br>3<br>4 8 mm<br>50 kA<br>4.5 kA  |
| <ul> <li>motor drive</li> <li>voltage trigger</li> <li>number of connectable NC contacts for auxiliary contacts attachable maximum</li> <li>number of connectable NO contacts for auxiliary contacts attachable maximum</li> <li>number of connectable CO contacts for auxiliary contacts attachable maximum</li> <li>number of bracket locks maximum</li> <li>number of bracket locks maximum</li> <li>hasp thickness of the bracket locks</li> <li>Short circuit</li> <li>conditional short-circuit current with line-side fuse protection         <ul> <li>at 690 V by gG fuse rated value</li> <li>let-through current with closed switch</li> <li>at 240 V for combination switch + gG fuse maximum</li> <li>at 440 V for combination switch + gG fuse maximum</li> <li>at 690 V for combination switch + gG fuse maximum</li> </ul> </li> </ul>  | No<br>2<br>3<br>0<br>3<br>4 8 mm<br>50 kA<br>4.5 kA<br>4.5 kA  |
| <ul> <li>motor drive</li> <li>voltage trigger</li> <li>number of connectable NC contacts for auxiliary contacts attachable maximum</li> <li>number of connectable NO contacts for auxiliary contacts attachable maximum</li> <li>number of connectable CO contacts for auxiliary contacts attachable maximum</li> <li>number of connectable CO contacts for auxiliary contacts attachable maximum</li> <li>number of bracket locks maximum</li> <li>hasp thickness of the bracket locks</li> <li>Short circuit</li> <li>conditional short-circuit current with line-side fuse protection</li> <li>at 690 V by gG fuse rated value</li> <li>let-through current with closed switch</li> <li>at 240 V for combination switch + gG fuse maximum</li> <li>at 690 V for combination switch + gG fuse maximum</li> <li>at 690 V for combination switch + gG fuse maximum</li> </ul>  | No<br>2<br>3<br>0<br>3<br>4 8 mm<br>50 kA<br>4.5 kA<br>4.5 kA  |
| <ul> <li>motor drive</li> <li>voltage trigger</li> <li>number of connectable NC contacts for auxiliary contacts attachable maximum</li> <li>number of connectable NO contacts for auxiliary contacts attachable maximum</li> <li>number of connectable CO contacts for auxiliary contacts attachable maximum</li> <li>number of bracket locks maximum</li> <li>hasp thickness of the bracket locks</li> </ul> Short circuit conditional short-circuit current with line-side fuse protection <ul> <li>at 690 V by gG fuse rated value</li> <li>let-through current with closed switch</li> <li>at 240 V for combination switch + gG fuse maximum</li> <li>at 690 V for combination switch + gG fuse maximum</li> <li>at 690 V for combination switch + gG fuse maximum</li> <li>at 690 V for combination switch + gG fuse maximum <ul> <li>at 690 V for combination switch + gG fuse maximum</li> <li>at 690 V for combination switch + gG fuse maximum</li> </ul></li></ul>   | No<br>2<br>3<br>0<br>3<br>4 8 mm<br>50 kA<br>4.5 kA<br>4.5 kA<br>5 kA  |
| <ul> <li>motor drive</li> <li>voltage trigger</li> <li>number of connectable NC contacts for auxiliary contacts attachable maximum</li> <li>number of connectable NO contacts for auxiliary contacts attachable maximum</li> <li>number of connectable CO contacts for auxiliary contacts attachable maximum</li> <li>number of bracket locks maximum</li> <li>number of bracket locks maximum</li> <li>hasp thickness of the bracket locks</li> </ul> Short circuit conditional short-circuit current with line-side fuse protection <ul> <li>at 690 V by gG fuse rated value</li> <li>let-through current with closed switch</li> <li>at 240 V for combination switch + gG fuse maximum</li> <li>at 690 V for combination switch + gG fuse maximum</li> <li>at 690 V for combination switch + gG fuse maximum</li> <li>at 690 V for combination switch + gG fuse maximum <ul> <li>at 690 V for combination switch + gG fuse maximum</li> <li>at 690 V for combination switch + gG fuse maximum</li> <li>at 690 V for combination switch + gG fuse maximum</li> </ul></li></ul>   | No<br>2<br>3<br>0<br>3<br>4 8 mm<br>50 kA<br>4.5 kA<br>4.5 kA<br>5 kA<br>9 kA2.s                                 |
| <ul> <li>motor drive</li> <li>voltage trigger</li> <li>number of connectable NC contacts for auxiliary contacts attachable maximum</li> <li>number of connectable NO contacts for auxiliary contacts attachable maximum</li> <li>number of connectable CO contacts for auxiliary contacts attachable maximum</li> <li>number of bracket locks maximum</li> <li>number of bracket locks maximum</li> <li>hasp thickness of the bracket locks</li> </ul> Short circuit conditional short-circuit current with line-side fuse protection <ul> <li>at 690 V by gG fuse rated value</li> <li>let-through current with closed switch</li> <li>at 240 V for combination switch + gG fuse maximum</li> <li>at 690 V for combination switch + gG fuse maximum</li> <li>at 690 V for combination switch + gG fuse maximum</li> <li>at 690 V for combination switch + gG fuse maximum <ul> <li>at 690 V for combination switch + gG fuse maximum</li> <li>at 440 V for combination switch + gG fuse maximum</li> <li>at 240 V for combination switch + gG fuse maximum</li> <li>at 240 V for combination switch + gG fuse maximum</li> </ul></li></ul>  | No<br>2<br>3<br>0<br>3<br>4 8 mm<br>50 kA<br>4.5 kA<br>4.5 kA<br>5 kA<br>9 kA2.s                                 |
| <ul> <li>motor drive</li> <li>voltage trigger</li> <li>number of connectable NC contacts for auxiliary contacts attachable maximum</li> <li>number of connectable NO contacts for auxiliary contacts attachable maximum</li> <li>number of connectable CO contacts for auxiliary contacts attachable maximum</li> <li>number of bracket locks maximum</li> <li>number of bracket locks maximum</li> <li>hasp thickness of the bracket locks</li> </ul> Short circuit conditional short-circuit current with line-side fuse protection <ul> <li>at 690 V by gG fuse rated value</li> <li>let-through current with closed switch</li> <li>at 240 V for combination switch + gG fuse maximum</li> <li>at 690 V for combination switch + gG fuse maximum</li> <li>at 690 V for combination switch + gG fuse maximum</li> <li>at 440 V for combination switch + gG fuse maximum <ul> <li>at 240 V for combination switch + gG fuse maximum</li> <li>at 440 V for combination switch + gG fuse maximum</li> <li>at 240 V for combination switch + gG fuse maximum</li> <li>at 440 V for combination switch + gG fuse maximum</li> <li>at 440 V for combination switch + gG fuse maximum</li> <li>at 440 V for combination switch + gG fuse maximum</li> <li>at 440 V for combination switch + gG fuse maximum</li> <li>at 440 V for combination switch + gG fuse maximum</li> </ul></li></ul>  | No<br>2<br>3<br>0<br>3<br>4 8 mm<br>50 kA<br>4.5 kA<br>4.5 kA<br>5 kA<br>9 kA2.s                                 |
| <ul> <li>motor drive</li> <li>voltage trigger</li> <li>number of connectable NC contacts for auxiliary contacts attachable maximum</li> <li>number of connectable NO contacts for auxiliary contacts attachable maximum</li> <li>number of connectable CO contacts for auxiliary contacts attachable maximum</li> <li>number of bracket locks maximum</li> <li>hasp thickness of the bracket locks</li> </ul> Short circuit conditional short-circuit current with line-side fuse protection <ul> <li>at 690 V by gG fuse rated value</li> <li>let-through current with closed switch</li> <li>at 240 V for combination switch + gG fuse maximum</li> <li>at 690 V for combination switch + gG fuse maximum</li> <li>at 690 V for combination switch + gG fuse maximum</li> <li>at 690 V for combination switch + gG fuse maximum</li> <li>at 690 V for combination switch + gG fuse maximum</li> <li>at 690 V for combination switch + gG fuse maximum</li> <li>at 690 V for combination switch + gG fuse maximum</li> <li>at 690 V for combination switch + gG fuse maximum</li> <li>at 690 V for combination switch + gG fuse maximum</li> <li>at 690 V for combination switch + gG fuse maximum</li> <li>at 690 V for combination switch + gG fuse maximum</li> <li>at 690 V for combination switch + gG fuse maximum</li> <li>at 690 V for combination switch + gG fuse maximum</li> <li>at 690 V for combination switch + gG fuse maximum</li> </ul> | No<br>2<br>3<br>0<br>3<br>4 8 mm<br>50 kA<br>4.5 kA<br>4.5 kA<br>4.5 kA<br>5 kA<br>9 kA2.s<br>9 kA2.s<br>9 kA2.s |

| according UL  |  |  |
|---|--|--|
| operational current at AC according to UL 508/UL 60947-                       | 32 A   |  |
| 4-1 rated value<br>operating voltage at AC at 50/60 Hz according to UL        | 600 V  |  |
| 508/UL 60947-4-1 rated value  |  |  |
| active power [hp] at AC at 480 V according to UL 508/UL 60947-4-1 rated value | 20   |  |
| active power [hp] at AC at 600 V according to UL 508/UL 60947-4-1 rated value | 20   |  |
| short-time withstand current (SCCR) at 600 V according to UL 508/UL 60947-4-1 | 5 kA   |  |
| continuous current of upstream fuse according to UL rated value               | 80 A   |  |
| type of fuse according to UL  | RK5  |  |
| Connections   |  |  |
| AWG number as coded connectable conductor cross section solid                 |  |  |
| • maximum   | 8  |  |
| • minimum   | 14   |  |
| type of connectable conductor cross-sections for copper<br>conductor          |  |  |
| • solid   | 1x (1,516mm²)  |  |
| <ul> <li>finely stranded with core end processing</li> </ul>                  | 1x (1,510mm <sup>2</sup> )   |  |
| • stranded  | 1x (1,516mm²)  |  |
| type of connectable conductor cross-sections for auxiliary<br>contacts        |  |  |
| • solid   | lateral auxiliary switch 2x (0,75 2,5mm <sup>2</sup> ), 1x 4mm <sup>2</sup> ; front auxiliary switch 1x (0,75 2,5mm <sup>2</sup> ) |  |
| • finely stranded with core end processing                                    | lateral auxiliary switch 2x (0,75 1,5mm <sup>2</sup> ), 1x 2,5mm <sup>2</sup> ; front auxiliary switch 1x 2,5mm <sup>2</sup>       |  |
| • stranded  | lateral auxiliary switch 2x (0,75 2,5mm <sup>2</sup> ), 1x 4mm <sup>2</sup> ; front auxiliary switch 1x (0,75 2,5mm <sup>2</sup> ) |  |
| type of electrical connection   |  |  |
| <ul> <li>for main current circuit</li> </ul>                                  | box terminal   |  |
| <ul> <li>for auxiliary contacts</li> </ul>                                    | connection terminals   |  |
| Mechanical Design   |  |  |
| height  | 164 mm   |  |
| width   | 100 mm   |  |
| depth   | 118 mm   |  |
| type of device<br>fastening method  | fixed mounting<br>Complete unit in enclosure   |  |
| fastening method  |  |  |
| 4-hole front mounting   | No   |  |
| <ul> <li>front mounting with central attachment</li> </ul>                    | Yes  |  |
| • rail mounting   | No   |  |
| net weight  | 536.7 g  |  |
| Environmental conditions  |  |  |
| ambient temperature during operation  |  |  |
| • minimum   | -25 °C   |  |
| • maximum   | 55 °C  |  |
| ambient temperature during storage  |  |  |
| ● minimum<br>● maximum  | -25 °C<br>55 °C  |  |
| General Product Approval  |  |  |
| General Floudet Approval  |  |  |
| Confirmation<br>Confirmation  | Miscellaneous EFFE   |  |
| Declaration of Conformity Test Certificates Marine / Shipping                 |  |  |



Miscellaneous

Special Test Certificate **Miscellaneous** 



other

**Miscellaneous** 

**Confirmation** 

Environmental Confirmations

## Further information

Information on the packaging

https://support.industry.siemens.com/cs/ww/en/view/109813875

Information- and Downloadcenter (Catalogs, Brochures,...)

http://www.siemens.com/lowvoltage/catalogs

Industry Mall (Online ordering system)

https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3LD2264-2TW53-0US2

Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

https://support.industry.siemens.com/cs/ww/en/ps/3LD2264-2TW53-0US2

Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, ...)

http://www.automation.siemens.com/bilddb/cax\_en.aspx?mlfb=3LD2264-2TW53-0US2

**CAx-Online-Generator** 

http://www.siemens.com/cax

**Tender specifications** 

http://www.siemens.com/specifications







