SIEMENS

Data sheet

3RA2125-0HD23-0BB4

	Fuseless motor starter Direct start 600VAC Size S0 0.55-0.8A 24V DC screw
	connection For snapping onto 60 mm busbar systems Type of coordination 2 IQ = 150 KA Also full fills type Of coordination 1 1NO+1NC (MSP) 1NO+1NC (contactor)
product brand name	SIRIUS
product designation	non-fused motor starter 3RA2
design of the product	direct starter
manufacturer's article number	
of the supplied contactor	<u>3RT2023-1BB40</u>
 of the supplied circuit-breakers 	<u>3RV2011-0HA15</u>
 of the supplied busbar adapter 	<u>8US1251-5NT10</u>
of the supplied link module	<u>3RA2921-1BA00</u>
General technical data	
size of the circuit-breaker	S00
size of load feeder	SO
product extension auxiliary switch	Yes
insulation voltage with degree of pollution 3 at AC rated value	690 V
degree of pollution	3
surge voltage resistance rated value	6 kV
shock resistance according to IEC 60068-2-27	6g / 11 ms
mechanical service life (operating cycles) of contactor typical	10 000 000
type of assignment	2
Ambient conditions	
ambient temperature	
during operation	-20 +60 °C
during storage	-50 +80 °C
during transport	-55 +80 °C
Main circuit	
number of poles for main current circuit	3
number of poles for main current circuit design of the switching contact	
design of the switching contact	electromechanical
design of the switching contact adjustable current response value current of the current-	electromechanical
design of the switching contact adjustable current response value current of the current- dependent overload release	electromechanical
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage	electromechanical 0.55 0.8 A
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value	electromechanical 0.55 0.8 A 690 V
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum	electromechanical 0.55 0.8 A 690 V 690 V
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value	electromechanical 0.55 0.8 A 690 V 690 V 50 60 Hz
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value	electromechanical 0.55 0.8 A 690 V 690 V 50 60 Hz
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3	electromechanical 0.55 0.8 A 690 V 690 V 50 60 Hz 0.6 A
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value	electromechanical 0.55 0.8 A 690 V 690 V 50 60 Hz 0.6 A 180 W
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operating power at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value • at 500 V rated value • at 690 V rated value	electromechanical 0.55 0.8 A 690 V 690 V 50 60 Hz 0.6 A 180 W 250 W
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operating power at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value • at 690 V rated value • at 690 V rated value Control circuit/ Control	electromechanical 0.55 0.8 A 690 V 690 V 50 60 Hz 0.6 A 180 W 250 W
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operating power at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value • at 500 V rated value • at 690 V rated value	electromechanical 0.55 0.8 A 690 V 690 V 50 60 Hz 0.6 A 180 W 250 W 370 W
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operating power at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value • at 500 V rated value • at 690 V rated value	electromechanical 0.55 0.8 A 690 V 690 V 50 60 Hz 0.6 A 180 W 250 W 370 W 24 V
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operating power at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value • at 500 V rated value • at 690 V rated value • rated value • rated value • holding power of magnet coil at DC	electromechanical 0.55 0.8 A 690 V 690 V 50 60 Hz 0.6 A 180 W 250 W 370 W
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operating power at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value • at 500 V rated value • at 690 V rated value Control circuit/ Control control supply voltage at DC • rated value holding power of magnet coil at DC Auxiliary circuit	electromechanical 0.55 0.8 A 690 V 690 V 50 60 Hz 0.6 A 180 W 250 W 370 W 24 V 5.9 W
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operating power at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value • at 690 V rated value Control circuit/ Control control supply voltage at DC • rated value holding power of magnet coil at DC Auxiliary circuit number of NC contacts for auxiliary contacts	electromechanical 0.55 0.8 A 690 V 690 V 50 60 Hz 0.6 A 180 W 250 W 370 W 24 V 5.9 W
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operating prequency rated value operating prequency rated value operating prequency rated value operating power at AC-3 • at 400 V rated value • at 500 V rated value • at 690 V rated value Auxiliary control • rated value holding power of magnet coil at DC Auxiliary circuit number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts	electromechanical 0.55 0.8 A 690 V 690 V 50 60 Hz 0.6 A 180 W 250 W 370 W 24 V 5.9 W
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operating prequency rated value operating prequency rated value operating power at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value • at 500 V rated value • at 690 V rated value Control circuit/ Control control supply voltage at DC • rated value holding power of magnet coil at DC Auxiliary circuit number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts Protective and monitoring functions	electromechanical 0.55 0.8 A 690 V 690 V 50 60 Hz 0.6 A 180 W 250 W 370 W 24 V 5.9 W 2 2 2
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operating power at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value • at 500 V rated value • at 690 V rated value Control circuit/ Control control supply voltage at DC • rated value holding power of magnet coil at DC Auxiliary circuit number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts Protective and monitoring functions trip class	electromechanical 0.55 0.8 A 690 V 690 V 50 60 Hz 0.6 A 180 W 250 W 370 W 24 V 5.9 W 2 2 2 2 2
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operating power at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value • at 690 V rated value Control circuit/ Control control supply voltage at DC • rated value holding power of magnet coil at DC Auxiliary circuit number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts Protective and monitoring functions trip class design of the overload release	electromechanical 0.55 0.8 A 690 V 690 V 50 60 Hz 0.6 A 180 W 250 W 370 W 24 V 5.9 W 2 2 2 2 CLASS 10 thermal (bimetallic)
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operating power at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value • at 690 V rated value Potential circuit/ Control • at doule • at doule • at doule • bolding power of magnet coil at DC • uxiliary circuit number of NC contacts for auxiliary contacts protective and monitoring functions trip class design of the overload release response value current of instantaneous short-circuit trip unit	electromechanical 0.55 0.8 A 690 V 690 V 50 60 Hz 0.6 A 180 W 250 W 370 W 24 V 5.9 W 2 2 2 2 2
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operating power at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value • at 690 V rated value Control circuit/ Control control supply voltage at DC • rated value holding power of magnet coil at DC Auxiliary circuit number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts Protective and monitoring functions trip class design of the overload release	electromechanical 0.55 0.8 A 690 V 690 V 50 60 Hz 0.6 A 180 W 250 W 370 W 24 V 5.9 W 2 2 2 2 CLASS 10 thermal (bimetallic)

design of the short-circuit trip	magnetic
conditional short-circuit current (lq)	
• at 400 V according to IEC 60947-4-1 rated value	153 000 A
Installation/ mounting/ dimensions	
mounting position	vertical
fastening method	for snapping onto 60 mm busbar systems
height	260 mm
width	45 mm
depth	165 mm
required spacing	
 for grounded parts 	
— forwards	10 mm
— backwards	0 mm
— upwards	30 mm
— at the side	9 mm
— downwards	10 mm
 for live parts 	
— forwards	10 mm
— backwards	0 mm
— upwards	30 mm
— downwards	10 mm
— at the side	9 mm
Connections/ Terminals	
type of electrical connection for main current circuit	screw-type terminals
type of connectable conductor cross-sections for main contacts stranded	1 10 mm², 2x (2.5 6 mm²)
connectable conductor cross-section for main contacts finely stranded with core end processing	1 6 mm²
Safety related data	
B10 value with high demand rate according to SN 31920	1 000 000
proportion of dangerous failures with high demand rate according to SN 31920	73 %
protection class IP on the front according to IEC 60529	IP20
touch protection on the front according to IEC 60529	finger-safe, for vertical contact from the front
Certificates/ approvals	
General Product Approval For use in haza ous locations	ard- Declaration of Conformity other
Confirmation ERIC	Confirmation EG-Konf.

Dangerous Good

Transport Information

 Further information

 Siemens has decided to exit the Russian market (see here).

 https://press.siemens.com/global/en/pressrelease/siemens-wind-down-russian-business

 Siemens is working on the renewal of the current EAC certificates.

 Please contact your local Siemens office on the status of validity of the EAC certification if you intend to import or offer to supply these products to an EAC relevant market (other than the sanctioned EAEU member states Russia or Belarus).

 Information on the packaging

 https://support.industry.siemens.com/cs/ww/en/view/109813875

 Information- and Downloadcenter (Catalogs, Brochures,...)

 https://www.siemens.com/ic10

 Industry Mall (Online ordering system)

 https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3RA2125-0HD23-0BB4

 Cax online generator

 http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en&mlfb=3RA2125-0HD23-0BB4

Service&Support (Manuals, Certificates, Characteristics, FAQs,...) https://support.industry.siemens.com/cs/ww/en/ps/3RA2125-0HD23-0BB4 Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, EPLAN macros, ...) http://www.automation.siemens.com/bilddb/cax_de.aspx?mlfb=3RA2125-0HD23-0BB4&lang=en Characteristic: Tripping characteristics, I²t, Let-through current https://support.industry.siemens.com/cs/ww/en/ps/3RA2125-0HD23-0BB4/char Further characteristics (e.g. electrical endurance, switching frequency) http://www.automation.siemens.com/bilddb/index.aspx?view=Search&mlfb=3RA2125-0HD23-0BB4&objecttype=14&gridview=view1

last modified:

12/15/2020 🖸