## **SIEMENS**

## **Data sheet**

3RA2125-4AD26-0AK6

	FUSELESS MOTOR STARTER DIRECT START 600V AC SZ S0 11-16A 110/120V AC 50/60HZ SCREW CONNECTION FOR SNAPPING ONTO 60 MM BUSBAR SYSTEMS TYPE OF COORDINATION 2 IQ = 150 KA ALSO FULFILLS TYPE OF COORDINATION 1 1NO+1NC (MSP) 1NO+1NC (CONTACTOR)
product brand name	SIRIUS
product designation	non-fused motor starter 3RA2
design of the product	direct starter
manufacturer's article number	
<ul> <li>of the supplied contactor</li> </ul>	3RT2026-1AK60
<ul> <li>of the supplied circuit-breakers</li> </ul>	3RV2021-4AA15
<ul> <li>of the supplied busbar adapter</li> </ul>	<u>8US1251-5NT10</u>
<ul> <li>of the supplied link module</li> </ul>	3RA2921-1AA00
General technical data	
size of the circuit-breaker	S0
size of load feeder	S0
product extension auxiliary switch	Yes
insulation voltage with degree of pollution 3 at AC rated value	690 V
degree of pollution	3
surge voltage resistance rated value	6 kV
shock resistance according to IEC 60068-2-27	6g / 11 ms
mechanical service life (operating cycles) of contactor typical	10 000 000
type of assignment	2
Ambient conditions	
ambient temperature	
during operation	-20 +60 °C
during sporation     during storage	-50 +80 °C
during storage     during transport	-55 +80 °C
Main circuit	-55 100 °C
number of poles for main current circuit	3
design of the switching contact	electromechanical
adjustable current response value current of the current-	11 16 A
adjustable current response value current of the current- dependent overload release	
adjustable current response value current of the current- dependent overload release operating voltage	11 16 A
adjustable current response value current of the current- dependent overload release operating voltage • rated value	11 16 A 690 V
adjustable current response value current of the current- dependent overload release  operating voltage  • rated value  • at AC-3 rated value maximum	11 16 A 690 V 690 V
adjustable current response value current of the current- dependent overload release  operating voltage  • rated value  • at AC-3 rated value maximum  operating frequency rated value	11 16 A 690 V 690 V 50 60 Hz
adjustable current response value current of the current-dependent overload release  operating voltage  • rated value  • at AC-3 rated value maximum  operating frequency rated value  operational current at AC-3 at 400 V rated value	11 16 A 690 V 690 V
adjustable current response value current of the current-dependent overload release  operating voltage  • rated value  • at AC-3 rated value maximum  operating frequency rated value  operational current at AC-3 at 400 V rated value  operating power at AC-3	11 16 A 690 V 690 V 50 60 Hz 15.5 A
adjustable current response value current of the current-dependent overload release  operating voltage  • rated value  • at AC-3 rated value maximum  operating frequency rated value  operational current at AC-3 at 400 V rated value  operating power at AC-3  • at 400 V rated value	11 16 A  690 V  690 V  50 60 Hz  15.5 A  7 500 W
adjustable current response value current of the current-dependent overload release  operating voltage  • rated value  • at AC-3 rated value maximum  operating frequency rated value  operational current at AC-3 at 400 V rated value  operating power at AC-3  • at 400 V rated value  • at 500 V rated value	11 16 A 690 V 690 V 50 60 Hz 15.5 A
adjustable current response value current of the current-dependent overload release  operating voltage  • rated value  • at AC-3 rated value maximum  operating frequency rated value  operational current at AC-3 at 400 V rated value  operating power at AC-3  • at 400 V rated value  • at 500 V rated value  Control circuit/ Control	11 16 A  690 V  690 V  50 60 Hz  15.5 A  7 500 W
adjustable current response value current of the current-dependent overload release  operating voltage  • rated value  • at AC-3 rated value maximum  operating frequency rated value  operational current at AC-3 at 400 V rated value  operating power at AC-3  • at 400 V rated value  • at 500 V rated value  Control circuit/ Control  control supply voltage at AC	11 16 A  690 V  690 V  50 60 Hz  15.5 A  7 500 W  7 500 W
adjustable current response value current of the current-dependent overload release  operating voltage  • rated value  • at AC-3 rated value maximum  operating frequency rated value  operational current at AC-3 at 400 V rated value  operating power at AC-3  • at 400 V rated value  • at 500 V rated value  Control circuit/ Control  control supply voltage at AC  • at 50 Hz rated value	11 16 A  690 V  690 V  50 60 Hz  15.5 A  7 500 W  7 500 W
adjustable current response value current of the current-dependent overload release  operating voltage  • rated value  • at AC-3 rated value maximum  operating frequency rated value  operational current at AC-3 at 400 V rated value  operating power at AC-3  • at 400 V rated value  • at 500 V rated value  Control circuit/ Control  control supply voltage at AC  • at 50 Hz rated value  • at 50 Hz rated value	11 16 A  690 V  690 V  50 60 Hz  15.5 A  7 500 W  7 500 W
adjustable current response value current of the current-dependent overload release  operating voltage  • rated value  • at AC-3 rated value maximum  operating frequency rated value  operational current at AC-3 at 400 V rated value  operating power at AC-3  • at 400 V rated value  • at 500 V rated value  Control circuit/ Control  control supply voltage at AC  • at 50 Hz rated value  • at 50 Hz rated value  • at 60 Hz rated value	11 16 A  690 V  690 V  50 60 Hz  15.5 A  7 500 W  7 500 W  110 V  88 121 V  120 V
adjustable current response value current of the current-dependent overload release  operating voltage  • rated value • at AC-3 rated value maximum  operating frequency rated value  operational current at AC-3 at 400 V rated value  operating power at AC-3  • at 400 V rated value • at 500 V rated value  Control circuit/ Control  control supply voltage at AC  • at 50 Hz rated value  • at 60 Hz rated value  • at 60 Hz rated value  • at 60 Hz rated value	11 16 A  690 V  690 V  50 60 Hz  15.5 A  7 500 W  7 500 W  110 V  88 121 V  120 V  96 132 V
adjustable current response value current of the current-dependent overload release  operating voltage  • rated value • at AC-3 rated value maximum  operating frequency rated value  operational current at AC-3 at 400 V rated value  operating power at AC-3  • at 400 V rated value • at 500 V rated value  Control circuit/ Control  control supply voltage at AC  • at 50 Hz rated value  • at 50 Hz rated value  • at 60 Hz rated value  • at 60 Hz rated value  apparent holding power of magnet coil at AC	11 16 A  690 V  690 V  50 60 Hz  15.5 A  7 500 W  7 500 W  110 V  88 121 V  120 V  96 132 V  9.4 VA
adjustable current response value current of the current-dependent overload release  operating voltage  • rated value • at AC-3 rated value maximum  operating frequency rated value  operational current at AC-3 at 400 V rated value  operating power at AC-3  • at 400 V rated value • at 500 V rated value  Control circuit/ Control  control supply voltage at AC  • at 50 Hz rated value • at 50 Hz rated value  • at 60 Hz rated value  • at 60 Hz rated value  apparent holding power of magnet coil at AC  inductive power factor with the holding power of the coil	11 16 A  690 V  690 V  50 60 Hz  15.5 A  7 500 W  7 500 W  110 V  88 121 V  120 V  96 132 V
adjustable current response value current of the current-dependent overload release  operating voltage  • rated value  • at AC-3 rated value maximum  operating frequency rated value  operational current at AC-3 at 400 V rated value  operating power at AC-3  • at 400 V rated value  • at 500 V rated value  Control circuit/ Control  control supply voltage at AC  • at 50 Hz rated value  • at 50 Hz rated value  • at 60 Hz rated value  • at 60 Hz rated value  apparent holding power of magnet coil at AC  inductive power factor with the holding power of the coil  Auxiliary circuit	11 16 A  690 V  690 V  50 60 Hz  15.5 A  7 500 W  7 500 W  110 V  88 121 V  120 V  96 132 V  9.4 VA  0.28
adjustable current response value current of the current-dependent overload release  operating voltage  • rated value  • at AC-3 rated value maximum  operating frequency rated value  operational current at AC-3 at 400 V rated value  operating power at AC-3  • at 400 V rated value  • at 500 V rated value  Control circuit/ Control  control supply voltage at AC  • at 50 Hz rated value  • at 50 Hz rated value  • at 60 Hz rated value  • at 60 Hz rated value  apparent holding power of magnet coil at AC  inductive power factor with the holding power of the coil  Auxiliary circuit  number of NC contacts for auxiliary contacts	11 16 A  690 V  690 V  50 60 Hz  15.5 A  7 500 W  7 500 W  110 V  88 121 V  120 V  96 132 V  9.4 VA  0.28
adjustable current response value current of the current-dependent overload release  operating voltage  • rated value  • at AC-3 rated value maximum  operating frequency rated value  operational current at AC-3 at 400 V rated value  operating power at AC-3  • at 400 V rated value  • at 500 V rated value  Control circuit/ Control  control supply voltage at AC  • at 50 Hz rated value  • at 50 Hz rated value  • at 60 Hz rated value  at 60 Hz rated value  apparent holding power of magnet coil at AC  inductive power factor with the holding power of the coil  Auxiliary circuit  number of NC contacts for auxiliary contacts  number of NO contacts for auxiliary contacts	11 16 A  690 V  690 V  50 60 Hz  15.5 A  7 500 W  7 500 W  110 V  88 121 V  120 V  96 132 V  9.4 VA  0.28
adjustable current response value current of the current-dependent overload release  operating voltage  • rated value • at AC-3 rated value maximum  operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3  • at 400 V rated value • at 500 V rated value  Control circuit/ Control  control supply voltage at AC  • at 50 Hz rated value • at 50 Hz rated value • at 60 Hz rated value  • at 60 Hz rated value apparent holding power of magnet coil at AC inductive power factor with the holding power of the coil  Auxiliary circuit number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts	11 16 A  690 V  690 V  50 60 Hz  15.5 A  7 500 W  7 500 W  110 V  88 121 V  120 V  96 132 V  9.4 VA  0.28
adjustable current response value current of the current-dependent overload release  operating voltage  • rated value  • at AC-3 rated value maximum  operating frequency rated value  operational current at AC-3 at 400 V rated value  operating power at AC-3  • at 400 V rated value  • at 500 V rated value  Control circuit/ Control  control supply voltage at AC  • at 50 Hz rated value  • at 50 Hz rated value  • at 60 Hz rated value  at 60 Hz rated value  apparent holding power of magnet coil at AC  inductive power factor with the holding power of the coil  Auxiliary circuit  number of NC contacts for auxiliary contacts  number of NO contacts for auxiliary contacts	11 16 A  690 V  690 V  50 60 Hz  15.5 A  7 500 W  7 500 W  110 V  88 121 V  120 V  96 132 V  9.4 VA  0.28

response value current of instantaneous short-circuit trip unit	208 A
UL/CSA ratings	
full-load current (FLA) for 3-phase AC motor	
• at 480 V rated value	15.2 A
• at 600 V rated value	12.2 A
yielded mechanical performance [hp]	
for single-phase AC motor	
— at 110/120 V rated value	1 hp
— at 230 V rated value	2 hp
• for 3-phase AC motor	
— at 200/208 V rated value	3 hp
— at 220/230 V rated value	5 hp
— at 460/480 V rated value	10 hp
— at 575/600 V rated value	10 hp
Short-circuit protection	
product function short circuit protection	Yes
design of the short-circuit trip	magnetic
conditional short-circuit current (Iq)	
• at 400 V according to IEC 60947-4-1 rated value	153 000 A
at 500 V according to IEC 60947-4-1 rated value	100 000 A
Installation/ mounting/ dimensions	
mounting position	vertical
fastening method	for snapping onto 60 mm busbar systems
height	260 mm
width	45 mm
depth	155 mm
required spacing	100 11111
• for grounded parts	
— forwards	10 mm
— backwards	0 mm
— upwards	30 mm
— at the side	9 mm
— downwards	10 mm
• for live parts	10 11111
— forwards	10 mm
— backwards	0 mm
	30 mm
— upwards — downwards	10 mm
— at the side	9 mm
Connections/ Terminals	9 11111
	agray type terminals
type of electrical connection for main current circuit type of connectable conductor cross-sections for main contacts	screw-type terminals 1 10 mm², 2x (2.5 6 mm²)
stranded  connectable conductor cross-section for main contacts finely stranded with core end processing	1 6 mm²
Safety related data	
B10 value with high demand rate according to SN 31920	1 000 000
proportion of dangerous failures with high demand rate according to SN 31920	73 %
protection class IP on the front according to IEC 60529	IP20
touch protection on the front according to IEC 60529	finger-safe, for vertical contact from the front
Certificates/ approvals	inigor saio, for vertical contact from the front
Sertificates/ approvais-	For use in beyond
General Product Approval	For use in hazard- ous locations  Declaration of Conformity
Confirmation	











Test Certificates

Marine / Shipping

Type Test Certificates/Test Report

Special Test Certificate









Marine / Shipping other Railway







Confirmation

Vibration and Shock

## **Further information**

Siemens has decided to exit the Russian market (see here).

https://press.siemens.com/global/en/pressrelease/siemens-wind-down-russian-business

Siemens is working on the renewal of the current EAC certificates.

Please contact your local Siemens office on the status of validity of the EAC certification if you intend to import or offer to supply these products to an EAC relevant market (other than the sanctioned EAEU member states Russia or Belarus).

Information on the packaging

https://support.industry.siemens.com/cs/ww/en/view/109813875

Information- and Downloadcenter (Catalogs, Brochures,...)

https://www.siemens.com/ic10

Industry Mall (Online ordering system)

https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3RA2125-4AD26-0AK6

Cax online generator

http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en&mlfb=3RA2125-4AD26-0AK6

Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

https://support.industry.siemens.com/cs/ww/en/ps/3RA2125-4AD26-0AK6

Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, EPLAN macros, ...)

http://www.automation.siemens.com/bilddb/cax\_de.aspx?mlfb=3RA2125-4AD26-0AK6&lang=en

Characteristic: Tripping characteristics, I2t, Let-through current

https://support.industry.siemens.com/cs/ww/en/ps/3RA2125-4AD26-0AK6/char

Further characteristics (e.g. electrical endurance, switching frequency)

http://www.automation.siemens.com/bilddb/index.aspx?view=Search&mlfb=3RA2125-4AD26-0AK6&objecttype=14&gridview=view1

12/13/2020	last modified:	12/15/2020 🖸
------------	----------------	--------------