SIEMENS

Data sheet

3RA2125-4AD26-0AP6

	FUSELESS MOTOR STARTER DIRECT START 600V AC SZ S0 11-16A 220/240V AC 50/60HZ SCREW CONNECTION FOR SNAPPING ONTO 60 MM
	BUSBAR SYSTEMS TYPE OF COORDINATION 2 IQ = 150 KA ALSO FULFILLS TYPE OF COORDINATION 1 1NO+1NC (MSP) 1NO+1NC (CONTACTOR)
nyaduat byand nama	SIRIUS
product brand name	
product designation	non-fused motor starter 3RA2
design of the product	direct starter
manufacturer's article number	ODT0000 44 D00
of the supplied contactor	3RT2026-1AP60
of the supplied circuit-breakers	3RV2021-4AA15
of the supplied busbar adapter	8US1251-5NT10
of the supplied link module	3RA2921-1AA00
General technical data	
size of the circuit-breaker	S0
size of load feeder	S0
product extension auxiliary switch	Yes
insulation voltage with degree of pollution 3 at AC rated value	690 V
degree of pollution	3
surge voltage resistance rated value	6 kV
shock resistance according to IEC 60068-2-27	6g / 11 ms
mechanical service life (operating cycles) of contactor typical	10 000 000
type of assignment	2
Ambient conditions	
ambient temperature	
during operation	-20 +60 °C
during storage	-50 +80 °C
alcordon as form as a second	-55 +80 °C
during transport	30 100 °C
Main circuit	
Main circuit number of poles for main current circuit	3
Main circuit	3 electromechanical
Main circuit number of poles for main current circuit	3
Main circuit number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage	3 electromechanical
Main circuit number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value	3 electromechanical 11 16 A
Main circuit number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage	3 electromechanical 11 16 A 690 V 690 V
Main circuit number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value	3 electromechanical 11 16 A
Main circuit number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum	3 electromechanical 11 16 A 690 V 690 V
Main circuit number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value	3 electromechanical 11 16 A 690 V 690 V 50 60 Hz
mumber of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value	3 electromechanical 11 16 A 690 V 690 V 50 60 Hz
Main circuit number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3	3 electromechanical 11 16 A 690 V 690 V 50 60 Hz 15.5 A
Main circuit number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value	3 electromechanical 11 16 A 690 V 690 V 50 60 Hz 15.5 A
Main circuit number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value • at 500 V rated value	3 electromechanical 11 16 A 690 V 690 V 50 60 Hz 15.5 A
Main circuit number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value • at 500 V rated value Control circuit/ Control	3 electromechanical 11 16 A 690 V 690 V 50 60 Hz 15.5 A
Main circuit number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value • at 500 V rated value Control circuit/ Control control supply voltage at AC	3 electromechanical 11 16 A 690 V 690 V 50 60 Hz 15.5 A 7 500 W 7 500 W
Main circuit number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value • at 500 V rated value Control circuit/ Control control supply voltage at AC • at 50 Hz rated value	3 electromechanical 11 16 A 690 V 690 V 50 60 Hz 15.5 A 7 500 W 7 500 W
Main circuit number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value • at 500 V rated value Control circuit/ Control control supply voltage at AC • at 50 Hz rated value • at 50 Hz rated value	3 electromechanical 11 16 A 690 V 690 V 50 60 Hz 15.5 A 7 500 W 7 500 W
Main circuit number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value • at 500 V rated value Control circuit/ Control control supply voltage at AC • at 50 Hz rated value • at 60 Hz rated value • at 60 Hz rated value	3 electromechanical 11 16 A 690 V 690 V 50 60 Hz 15.5 A 7 500 W 7 500 W 220 V 176 242 V 240 V
Main circuit number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value • at 500 V rated value Control circuit/ Control control supply voltage at AC • at 50 Hz rated value • at 60 Hz rated value • at 60 Hz rated value • at 60 Hz rated value	3 electromechanical 11 16 A 690 V 690 V 50 60 Hz 15.5 A 7 500 W 7 500 W 220 V 176 242 V 240 V 192 264 V
Main circuit number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value • at 500 V rated value Control circuit/ Control control supply voltage at AC • at 50 Hz rated value • at 60 Hz rated value • at 60 Hz rated value apparent holding power of magnet coil at AC	3 electromechanical 11 16 A 690 V 690 V 50 60 Hz 15.5 A 7 500 W 7 500 W 220 V 176 242 V 240 V 192 264 V 9.4 VA
mumber of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value • at 500 V rated value Control circuit/ Control control supply voltage at AC • at 50 Hz rated value • at 60 Hz rated value • at 60 Hz rated value apparent holding power of magnet coil at AC inductive power factor with the holding power of the coil	3 electromechanical 11 16 A 690 V 690 V 50 60 Hz 15.5 A 7 500 W 7 500 W 220 V 176 242 V 240 V 192 264 V 9.4 VA
Main circuit number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value • at 500 V rated value Control circuit/ Control control supply voltage at AC • at 50 Hz rated value • at 50 Hz rated value • at 60 Hz rated value • at 60 Hz rated value apparent holding power of magnet coil at AC inductive power factor with the holding power of the coil Auxiliary circuit	3 electromechanical 11 16 A 690 V 690 V 50 60 Hz 15.5 A 7 500 W 7 500 W 220 V 176 242 V 240 V 192 264 V 9.4 VA 0.28
Main circuit number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value • at 500 V rated value Control circuit/ Control control supply voltage at AC • at 50 Hz rated value • at 60 Hz rated value • at 60 Hz rated value apparent holding power of magnet coil at AC inductive power factor with the holding power of the coil Auxiliary circuit number of NC contacts for auxiliary contacts	3 electromechanical 11 16 A 690 V 690 V 50 60 Hz 15.5 A 7 500 W 7 500 W 220 V 176 242 V 240 V 192 264 V 9.4 VA 0.28
Main circuit number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value • at 500 V rated value Control circuit/ Control control supply voltage at AC • at 50 Hz rated value • at 60 Hz rated value at 60 Hz rated value apparent holding power of magnet coil at AC inductive power factor with the holding power of the coil Auxiliary circuit number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts	3 electromechanical 11 16 A 690 V 690 V 50 60 Hz 15.5 A 7 500 W 7 500 W 220 V 176 242 V 240 V 192 264 V 9.4 VA 0.28

response value current of instantaneous short-circuit trip unit	208 A
UL/CSA ratings	
full-load current (FLA) for 3-phase AC motor	
• at 480 V rated value	15.2 A
• at 600 V rated value	12.2 A
yielded mechanical performance [hp]	
for single-phase AC motor	
— at 110/120 V rated value	1 hp
— at 230 V rated value	2 hp
• for 3-phase AC motor	
— at 200/208 V rated value	3 hp
— at 220/230 V rated value	5 hp
— at 460/480 V rated value	10 hp
— at 575/600 V rated value	10 hp
Short-circuit protection	
product function short circuit protection	Yes
design of the short-circuit trip	magnetic
conditional short-circuit current (Iq)	
• at 400 V according to IEC 60947-4-1 rated value	153 000 A
at 500 V according to IEC 60947-4-1 rated value	100 000 A
Installation/ mounting/ dimensions	
mounting position	vertical
fastening method	for snapping onto 60 mm busbar systems
height	260 mm
width	45 mm
depth	155 mm
required spacing	100 111111
• for grounded parts	
— forwards	10 mm
— backwards	0 mm
— upwards	30 mm
— upwards — at the side	9 mm
— downwards	10 mm
for live parts	10 111111
— forwards	10 mm
— backwards	0 mm
— upwards — downwards	30 mm
— at the side	10 mm 9 mm
Connections/ Terminals	V IIIII
	ecrew type terminals
type of electrical connection for main current circuit type of connectable conductor cross-sections for main contacts	screw-type terminals 1 10 mm², 2x (2.5 6 mm²)
stranded connectable conductor cross-section for main contacts finely stranded with core end processing	1 6 mm²
Safety related data	
B10 value with high demand rate according to SN 31920	1 000 000
proportion of dangerous failures with high demand rate according to SN 31920	73 %
protection class IP on the front according to IEC 60529	IP20
touch protection on the front according to IEC 60529	finger-safe, for vertical contact from the front
Certificates/ approvals	
General Product Approval	For use in hazard- Declaration of Conformity
General Floudet Approval	ous locations Declaration of Conformity
Confirmation	











Test Certificates

Marine / Shipping

Type Test Certificates/Test Report

Special Test Certificate









Marine / Shipping other Railway







Confirmation

Vibration and Shock

Further information

Siemens has decided to exit the Russian market (see here).

https://press.siemens.com/global/en/pressrelease/siemens-wind-down-russian-business

Siemens is working on the renewal of the current EAC certificates.

Please contact your local Siemens office on the status of validity of the EAC certification if you intend to import or offer to supply these products to an EAC relevant market (other than the sanctioned EAEU member states Russia or Belarus).

Information on the packaging

https://support.industry.siemens.com/cs/ww/en/view/109813875

Information- and Downloadcenter (Catalogs, Brochures,...)

https://www.siemens.com/ic10

Industry Mall (Online ordering system)

https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3RA2125-4AD26-0AP6

Cax online generator

http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en&mlfb=3RA2125-4AD26-0AP6

Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

https://support.industry.siemens.com/cs/ww/en/ps/3RA2125-4AD26-0AP6

Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, EPLAN macros, ...)

http://www.automation.siemens.com/bilddb/cax_de.aspx?mlfb=3RA2125-4AD26-0AP6&lang=en

Characteristic: Tripping characteristics, I2t, Let-through current

https://support.industry.siemens.com/cs/ww/en/ps/3RA2125-4AD26-0AP6/char

Further characteristics (e.g. electrical endurance, switching frequency)

http://www.automation.siemens.com/bilddb/index.aspx?view=Search&mlfb=3RA2125-4AD26-0AP6&objecttype=14&gridview=view1