## SIEMENS

## Data sheet

## 3RA2135-4EA35-0AP6

	Fuseless motor starter Direct start 600VAC Size S2 22-32A 220/240VAC 50/60HZ screw connection For screw mounting Or 35 mm rail-mounting Type of coordination 2 IQ = 100 KA Also full fills type Of coordination 1 1NO+1NC (MSP)			
	1NO+1NC (contactor)			
product brand name	SIRIUS			
product designation	non-fused motor starter 3RA2			
design of the product	direct starter			
manufacturer's article number				
<ul> <li>of the supplied contactor</li> </ul>	<u>3RT2035-1AP60</u>			
<ul> <li>of the supplied circuit-breakers</li> </ul>	<u>3RV2031-4EA15</u>			
<ul> <li>of the supplied link module</li> </ul>	<u>3RA2931-1AA00</u>			
General technical data				
size of the circuit-breaker	S2			
size of load feeder	S2			
product extension auxiliary switch	Yes			
insulation voltage with degree of pollution 3 at AC rated value	690 V			
degree of pollution	3			
surge voltage resistance rated value	6 kV			
shock resistance according to IEC 60068-2-27	6g / 11 ms			
mechanical service life (operating cycles) of contactor typical	10 000 000			
type of assignment	2			
Ambient conditions				
ambient temperature				
during operation	-20 +60 °C			
during storage	-50 +80 °C			
during transport	-55 +80 °C			
Main circuit				
number of noise for main surrout singuit	2			
numper of poles for main current circuit	3			
number of poles for main current circuit design of the switching contact	s electromechanical			
design of the switching contact adjustable current response value current of the current- dependent overload release				
design of the switching contact adjustable current response value current of the current- dependent overload release	electromechanical			
design of the switching contact adjustable current response value current of the current-	electromechanical			
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage	electromechanical 22 32 A			
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum	electromechanical 22 32 A 690 V 690 V			
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value	electromechanical 22 32 A 690 V			
design of the switching contact         adjustable current response value current of the current- dependent overload release         operating voltage         • rated value         • at AC-3 rated value maximum         operating frequency rated value         operational current at AC-3 at 400 V rated value	electromechanical 22 32 A 690 V 690 V 50 60 Hz			
design of the switching contact         adjustable current response value current of the current- dependent overload release         operating voltage         • rated value         • at AC-3 rated value maximum         operating frequency rated value         operational current at AC-3 at 400 V rated value         operating power at AC-3	electromechanical 22 32 A 690 V 690 V 50 60 Hz			
design of the switching contact         adjustable current response value current of the current- dependent overload release         operating voltage         • rated value         • at AC-3 rated value maximum         operating frequency rated value         operating grequency rated value         operating power at AC-3 at 400 V rated value         operating power at AC-3         • at 400 V rated value	electromechanical 22 32 A 690 V 690 V 50 60 Hz 29 A			
design of the switching contact         adjustable current response value current of the current- dependent overload release         operating voltage         • rated value         • at AC-3 rated value maximum         operating frequency rated value         operational current at AC-3 at 400 V rated value         operating power at AC-3         • at 400 V rated value         Control circuit/ Control	electromechanical 22 32 A 690 V 690 V 50 60 Hz 29 A			
design of the switching contact         adjustable current response value current of the current-         dependent overload release         operating voltage         • rated value         • at AC-3 rated value maximum         operating frequency rated value         operational current at AC-3 at 400 V rated value         operating power at AC-3         • at 400 V rated value         Control circuit/ Control         control supply voltage at AC	electromechanical 22 32 A 690 V 690 V 50 60 Hz 29 A 15 000 W			
design of the switching contact         adjustable current response value current of the current-         dependent overload release         operating voltage         • rated value         • at AC-3 rated value maximum         operating frequency rated value         operating prequency rated value         operating power at AC-3 at 400 V rated value         operating power at AC-3         • at 400 V rated value         Control circuit/ Control         control supply voltage at AC         • at 50 Hz rated value	electromechanical 22 32 A 690 V 690 V 50 60 Hz 29 A 15 000 W 220 V			
design of the switching contact         adjustable current response value current of the current- dependent overload release         operating voltage         • rated value         • at AC-3 rated value maximum         operating frequency rated value         operating prequency rated value         operating power at AC-3 at 400 V rated value         operating power at AC-3         • at 400 V rated value         Control circuit/ Control         control supply voltage at AC         • at 50 Hz rated value         • at 50 Hz rated value	electromechanical 22 32 A 690 V 690 V 50 60 Hz 29 A 15 000 W 220 V 176 242 V			
design of the switching contact         adjustable current response value current of the current-         dependent overload release         operating voltage         • rated value         • at AC-3 rated value maximum         operating frequency rated value         operating power at AC-3 at 400 V rated value         operating power at AC-3         • at 400 V rated value         Control circuit/ Control         control supply voltage at AC         • at 50 Hz rated value         • at 50 Hz rated value         • at 60 Hz rated value	electromechanical 22 32 A 690 V 690 V 50 60 Hz 29 A 15 000 W 220 V 176 242 V 240 V			
design of the switching contact         adjustable current response value current of the current-         dependent overload release         operating voltage         • rated value         • at AC-3 rated value maximum         operating frequency rated value         operating power at AC-3 at 400 V rated value         operating power at AC-3         • at 400 V rated value         Control circuit/ Control         control supply voltage at AC         • at 50 Hz rated value         • at 60 Hz rated value         • at 60 Hz rated value	electromechanical 22 32 A 690 V 690 V 50 60 Hz 29 A 15 000 W 220 V 176 242 V 240 V 192 264 V			
design of the switching contact         adjustable current response value current of the current-         dependent overload release         operating voltage         • rated value         • at AC-3 rated value maximum         operating frequency rated value         operating power at AC-3 at 400 V rated value         operating power at AC-3         • at 400 V rated value         Control circuit/ Control         control supply voltage at AC         • at 50 Hz rated value         • at 60 Hz rated value	electromechanical 22 32 A 690 V 690 V 50 60 Hz 29 A 15 000 W 220 V 176 242 V 240 V 192 264 V 16 VA			
design of the switching contact         adjustable current response value current of the current- dependent overload release         operating voltage         • rated value         • at AC-3 rated value maximum         operating frequency rated value         operating power at AC-3 at 400 V rated value         operating power at AC-3         • at 400 V rated value         Control circuit/ Control         control supply voltage at AC         • at 50 Hz rated value         • at 60 Hz rated value	electromechanical 22 32 A 690 V 690 V 50 60 Hz 29 A 15 000 W 220 V 176 242 V 240 V 192 264 V			
design of the switching contact         adjustable current response value current of the current- dependent overload release         operating voltage         • rated value         • at AC-3 rated value maximum         operating frequency rated value         operating prequency rated value         operating prequency rated value         operating prequency rated value         operating power at AC-3         • at 400 V rated value         Operating power at AC-3         • at 400 V rated value         Control circuit/ Control         control supply voltage at AC         • at 50 Hz rated value         • at 50 Hz rated value         • at 60 Hz rated value </td <td>electromechanical 22 32 A 690 V 690 V 50 60 Hz 29 A 15 000 W 220 V 176 242 V 240 V 192 264 V 16 VA 0.37</td>	electromechanical 22 32 A 690 V 690 V 50 60 Hz 29 A 15 000 W 220 V 176 242 V 240 V 192 264 V 16 VA 0.37			
design of the switching contact         adjustable current response value current of the current- dependent overload release         operating voltage         • rated value         • at AC-3 rated value maximum         operating frequency rated value         operating power at AC-3 at 400 V rated value         operating power at AC-3         • at 400 V rated value         Control circuit/ Control         control supply voltage at AC         • at 50 Hz rated value         • at 60 Hz rated value	electromechanical 22 32 A 690 V 690 V 50 60 Hz 29 A 15 000 W 220 V 176 242 V 240 V 192 264 V 16 VA 0.37			
design of the switching contact         adjustable current response value current of the current-         dependent overload release         operating voltage         • rated value         • at AC-3 rated value maximum         operating frequency rated value         operating power at AC-3 at 400 V rated value         operating power at AC-3         • at 400 V rated value         Control circuit/ Control         control supply voltage at AC         • at 50 Hz rated value         • at 60 Hz rated value         apparent holding power of magnet coil at AC         inductive power factor with the holding power of the coil         Auxiliary circuit         number of NC contacts for auxiliary contacts         number of NO contacts for auxiliary contacts	electromechanical 22 32 A 690 V 690 V 50 60 Hz 29 A 15 000 W 220 V 176 242 V 240 V 192 264 V 16 VA 0.37			
design of the switching contact         adjustable current response value current of the current- dependent overload release         operating voltage         • rated value         • at AC-3 rated value maximum         operating frequency rated value         operating prequency rated value         operating prequency rated value         operating power at AC-3         • at 400 V rated value         Control circuit/ Control         control supply voltage at AC         • at 50 Hz rated value         • at 50 Hz rated value         • at 60 Hz rated value         apparent holding power of magnet coil at AC         inductive power factor with the holding power of the coil         Auxiliary circuit         number of NC contacts for auxiliary contacts         number of NO contacts for auxiliary contacts         Protective and monitoring functions	electromechanical 22 32 A 690 V 690 V 50 60 Hz 29 A 15 000 W 220 V 176 242 V 240 V 192 264 V 16 VA 0.37			
design of the switching contact         adjustable current response value current of the current- dependent overload release         operating voltage         • rated value         • at AC-3 rated value maximum         operating frequency rated value         operating prequency rated value         operating prequency rated value         operating power at AC-3         • at 400 V rated value         Control circuit/ Control         control supply voltage at AC         • at 50 Hz rated value         • at 50 Hz rated value         • at 60 Hz rated value         apparent holding power of magnet coil at AC         inductive power factor with the holding power of the coil         Auxiliary circuit         number of NC contacts for auxiliary contacts         number of NO contacts for auxiliary contacts         Protective and monitoring functions         trip class	electromechanical 22 32 A 690 V 690 V 50 60 Hz 29 A 15 000 W 220 V 176 242 V 240 V 192 264 V 16 VA 0.37 2 2 2 2			
design of the switching contact         adjustable current response value current of the current- dependent overload release         operating voltage         • rated value         • at AC-3 rated value maximum         operating frequency rated value         operating prequency rated value         operating prequency rated value         operating power at AC-3         • at 400 V rated value         Control circuit/ Control         control supply voltage at AC         • at 50 Hz rated value         • at 60 Hz rated value         apparent holding power of magnet coil at AC         inductive power factor with the holding power of the coil         Auxiliary circuit         number of NC contacts for auxiliary contacts         Protective and monitoring functions	electromechanical 22 32 A 690 V 690 V 50 60 Hz 29 A 15 000 W 220 V 176 242 V 240 V 192 264 V 16 VA 0.37			

UL/CSA ratings				
full-load current (FLA) for 3-phase AC motor				
at 480 V rated value	32 A			
• at 600 V rated value	32 A			
yielded mechanical performance [hp]				
<ul> <li>for single-phase AC motor</li> </ul>				
— at 230 V rated value	5 hp			
<ul> <li>for 3-phase AC motor</li> </ul>				
— at 200/208 V rated value	10 hp			
— at 220/230 V rated value	10 hp			
— at 460/480 V rated value	25 hp			
— at 575/600 V rated value	30 hp			
Short-circuit protection				
product function short circuit protection	Yes			
design of the short-circuit trip	magnetic			
conditional short-circuit current (lg)				
• at 400 V according to IEC 60947-4-1 rated value	100 000 A			
Installation/ mounting/ dimensions				
mounting position	vertical			
fastening method	Snap-mounted to DIN rail or screw-mounted with additional push-in lug			
height	274 mm			
width	55 mm			
depth	150 mm			
required spacing				
for grounded parts				
— forwards	0 mm			
— backwards	0 mm			
— upwards	50 mm			
— at the side	10 mm			
— downwards	10 mm			
<ul> <li>for live parts</li> </ul>				
— forwards	0 mm			
— backwards	0 mm			
— upwards	50 mm			
downwards	10 mm			
— at the side	10 mm			
Connections/ Terminals				
type of electrical connection for main current circuit	screw-type terminals			
type of connectable conductor cross-sections for main contacts	1 35 mm², 2x (1 16 mm²)			
stranded				
connectable conductor cross-section for main contacts finely stranded with core end processing	1 25 mm²			
Safety related data				
B10 value with high demand rate according to SN 31920	1 000 000			
proportion of dangerous failures with high demand rate according to SN 31920	73 %			
protection class IP on the front according to IEC 60529	IP20			
touch protection on the front according to IEC 60529	finger-safe, for vertical contact from the front			
Certificates/ approvals				
General Product Approval	For use in hazard- ous locations Declaration of Conformity			
	UK CE			
Test Certificates Marine / Ship	ping			

<u>Special Test Certific-</u> <u>ate</u>	Type Test Certific- ates/Test Report	ABS	BUREAU VERITAS	Llovd's Register urs	PRS
Marine / Shipping			other	Railway	Dangerous Good
RINA	RMRS	DNV-GL EWELCOMM	<u>Confirmation</u>	Vibration and Shock	Transport Information
https://press.siemens.co Siemens is working or Please contact your loca EAC relevant market (of Information on the pac https://support.industry.si Information- and Down https://www.siemens.co Industry Mall (Online of https://mall.industry.sier Cax online generator https://support.automation Service&Support (Mar https://support.industry.si Image database (produ http://www.automation.s Characteristic: Trippin https://support.industry.si	siemens.com/cs/ww/en/view nloadcenter (Catalogs, Bro m/ic10	iemens-wind-down-ru nt EAC certificates. tus of validity of the E/ EU member states Ru <u>v/109813875</u> pochures,) mg/product?mlfb=3RA2 der/default.aspx?lang: teristics, FAQs,) RA2135-4EA35-0AP(6 drawings, 3D model aspx?mlfb=3RA2135- through current RA2135-4EA35-0AP(6	AC certification if you inter issia or Belarus). 2135-4EA35-0AP6 =en&mlfb=3RA2135-4EA3 3 s, device circuit diagran 4EA35-0AP6⟨=en 3/char	3 <u>5-0AP6</u>	ply these products to an

last modified:

12/15/2020 🖸