SIEMENS

Data sheet 3RA2155-4UA35-0NB3

	Functions makes attack Dispet start COOVAC City CO 22 40A 20 22V Ac/do acress
	Fuseless motor starter Direct start 600VAC Size S2 32-40A 20-33V Ac/dc screw connection For screw mounting Or 35 mm rail-mounting Type of coordination 2 IQ
	= 150 KA Also full fills type Of coordination 1 1NO+1NC (MSP) 1NO+1NC
	(contactor)
product brand name	SIRIUS
product designation	non-fused motor starter 3RA2
design of the product	direct starter
manufacturer's article number	
 of the supplied contactor 	3RT2035-1NB30
 of the supplied circuit-breakers 	3RV2032-4UA15
of the supplied link module	3RA2931-1AA00
General technical data	
size of the circuit-breaker	S2
size of load feeder	S2
product extension auxiliary switch	Yes
insulation voltage with degree of pollution 3 at AC rated value	690 V
degree of pollution	3
surge voltage resistance rated value	6 kV
shock resistance according to IEC 60068-2-27	6g / 11 ms
mechanical service life (operating cycles) of contactor typical	10 000 000
type of assignment	2
Ambient conditions	
ambient temperature	
 during operation 	-20 +60 °C
during storage	-50 +80 °C
during transport	-55 +80 °C
Main circuit	
number of poles for main current circuit	3
design of the switching contact	electromechanical
adjustable current response value current of the current-	32 40 A
dependent overload release	02 1 0 A
	VZ 40 /\
dependent overload release	690 V
dependent overload release operating voltage	
operating voltage • rated value	690 V
dependent overload release operating voltage • rated value • at AC-3 rated value maximum	690 V
dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value	690 V 690 V 50 60 Hz
dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value	690 V 690 V 50 60 Hz
dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3	690 V 690 V 50 60 Hz 35 A
dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value	690 V 690 V 50 60 Hz 35 A
dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value Control circuit/ Control	690 V 690 V 50 60 Hz 35 A
dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value Control circuit/ Control control supply voltage at AC	690 V 690 V 50 60 Hz 35 A 18 500 W
dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value Control circuit/ Control control supply voltage at AC • at 50 Hz rated value • at 50 Hz rated value	690 V 690 V 50 60 Hz 35 A 18 500 W
dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value Control circuit/ Control control supply voltage at AC • at 50 Hz rated value	690 V 690 V 50 60 Hz 35 A 18 500 W
dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value Control circuit/ Control control supply voltage at AC • at 50 Hz rated value • at 60 Hz rated value • at 60 Hz rated value • at 60 Hz rated value	690 V 690 V 50 60 Hz 35 A 18 500 W
dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value Control circuit/ Control control supply voltage at AC • at 50 Hz rated value • at 60 Hz rated value • at 60 Hz rated value	690 V 690 V 50 60 Hz 35 A 18 500 W
dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value Control circuit/ Control control supply voltage at AC • at 50 Hz rated value • at 60 Hz rated value • at 60 Hz rated value control supply voltage at DC	690 V 690 V 50 60 Hz 35 A 18 500 W 24 V 20 33 V 24 V 20 33 V
dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operating prequency rated value operating power at AC-3 • at 400 V rated value Control circuit/ Control control supply voltage at AC • at 50 Hz rated value • at 50 Hz rated value • at 60 Hz rated value • at 60 Hz rated value control supply voltage at DC • rated value • rated value • rated value • rated value	690 V 690 V 50 60 Hz 35 A 18 500 W 24 V 20 33 V 24 V 20 33 V
dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value Control circuit/ Control control supply voltage at AC • at 50 Hz rated value • at 50 Hz rated value • at 60 Hz rated value • at 60 Hz rated value control supply voltage at DC • rated value rated value • rated value • rated value • rated value inductive power factor with the holding power of the coil	690 V 690 V 50 60 Hz 35 A 18 500 W 24 V 20 33 V 24 V 20 33 V 24 V 20 33 V
dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value Control circuit/ Control control supply voltage at AC • at 50 Hz rated value • at 60 Hz rated value • at 60 Hz rated value control supply voltage at DC • rated value inductive power factor with the holding power of the coil holding power of magnet coil at DC	690 V 690 V 50 60 Hz 35 A 18 500 W 24 V 20 33 V 24 V 20 33 V
dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value Control circuit/ Control control supply voltage at AC • at 50 Hz rated value • at 50 Hz rated value • at 60 Hz rated value • at 60 Hz rated value control supply voltage at DC • rated value • rated value inductive power factor with the holding power of the coil holding power of magnet coil at DC Auxiliary circuit	690 V 690 V 50 60 Hz 35 A 18 500 W 24 V 20 33 V 24 V 20 33 V 24 V 20 33 V
dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operating prequency rated value operating power at AC-3 • at 400 V rated value Control circuit/ Control control supply voltage at AC • at 50 Hz rated value • at 50 Hz rated value • at 60 Hz rated value • at 60 Hz rated value control supply voltage at DC • rated value inductive power factor with the holding power of the coil holding power of magnet coil at DC Auxiliary circuit number of NC contacts for auxiliary contacts	690 V 690 V 50 60 Hz 35 A 18 500 W 24 V 20 33 V 24 V 20 33 V 24 V 20 33 V
dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operating prequency rated value operating power at AC-3 • at 400 V rated value Control circuit/ Control control supply voltage at AC • at 50 Hz rated value • at 60 Hz rated value • at 60 Hz rated value control supply voltage at DC • rated value • at 60 Hz rated value control supply voltage at DC inductive power factor with the holding power of the coil holding power of magnet coil at DC Auxiliary circuit number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts	690 V 690 V 50 60 Hz 35 A 18 500 W 24 V 20 33 V 24 V 20 33 V 24 V 20 33 V
dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operating prequency rated value operating power at AC-3 • at 400 V rated value Control circuit/ Control control supply voltage at AC • at 50 Hz rated value • at 50 Hz rated value • at 60 Hz rated value • at 60 Hz rated value control supply voltage at DC • rated value inductive power factor with the holding power of the coil holding power of magnet coil at DC Auxiliary circuit number of NC contacts for auxiliary contacts	690 V 690 V 50 60 Hz 35 A 18 500 W 24 V 20 33 V 24 V 20 33 V 24 V 20 33 V

design of the overload release	thermal (bimetallic)
response value current of instantaneous short-circuit trip unit	520 A
UL/CSA ratings	
full-load current (FLA) for 3-phase AC motor	
at 480 V rated value	40 A
at 600 V rated value	40 A
yielded mechanical performance [hp]	
 for single-phase AC motor 	
 at 110/120 V rated value 	3 hp
— at 230 V rated value	7.5 hp
• for 3-phase AC motor	
— at 200/208 V rated value	10 hp
— at 220/230 V rated value	15 hp
— at 460/480 V rated value	30 hp
— at 575/600 V rated value	40 hp
Short-circuit protection	
product function short circuit protection	Yes
design of the short-circuit trip	magnetic
conditional short-circuit current (Iq)	
at 400 V according to IEC 60947-4-1 rated value	150 000 A
nstallation/ mounting/ dimensions	
mounting position	vertical
fastening method	Snap-mounted to DIN rail or screw-mounted with additional push-in lug
height	274 mm
width	55 mm
depth	150 mm
required spacing	
for grounded parts	
— forwards	0 mm
— backwards	0 mm
— upwards	50 mm
— at the side	10 mm
— downwards	10 mm
• for live parts	
— forwards	0 mm
— backwards	0 mm
— upwards	50 mm
— downwards	10 mm
— at the side	10 mm
Connections/ Terminals	corrow type terminals
type of electrical connection for main current circuit type of connectable conductor cross-sections for main contacts stranded	screw-type terminals 1 50 mm², 2x (1 25 mm²)
connectable conductor cross-section for main contacts finely stranded with core end processing	1 35 mm²
Safety related data	
B10 value with high demand rate according to SN 31920	1 000 000
proportion of dangerous failures with high demand rate	73 %
according to SN 31920	
protection class IP on the front according to IEC 60529	IP20
touch protection on the front according to IEC 60529	finger-safe, for vertical contact from the front
Certificates/ approvals	
General Product Approval	For use in hazard- ous locations Declaration of Conformity
Confirmation EFI	Ex CE UK EG-Konf. CA

Test Certificates

Marine / Shipping

Type Test Certificates/Test Report

Special Test Certificate









Marine / Shipping other Railway Dangerous Good







<u>Confirmation</u> <u>Vibration and Shock</u> <u>Transport Information</u>

Further information

Siemens has decided to exit the Russian market (see here).

https://press.siemens.com/global/en/pressrelease/siemens-wind-down-russian-business

Siemens is working on the renewal of the current EAC certificates.

Please contact your local Siemens office on the status of validity of the EAC certification if you intend to import or offer to supply these products to an EAC relevant market (other than the sanctioned EAEU member states Russia or Belarus).

Information on the packaging

https://support.industry.siemens.com/cs/ww/en/view/109813875

Information- and Downloadcenter (Catalogs, Brochures,...)

https://www.siemens.com/ic10

Industry Mall (Online ordering system)

https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3RA2155-4UA35-0NB3

Cax online generator

http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en&mlfb=3RA2155-4UA35-0NB3

Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

https://support.industry.siemens.com/cs/ww/en/ps/3RA2155-4UA35-0NB3

Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, EPLAN macros, ...)

http://www.automation.siemens.com/bilddb/cax_de.aspx?mlfb=3RA2155-4UA35-0NB3&lang=en

Characteristic: Tripping characteristics, I2t, Let-through current

https://support.industry.siemens.com/cs/ww/en/ps/3RA2155-4UA35-0NB3/char

Further characteristics (e.g. electrical endurance, switching frequency)

http://www.automation.siemens.com/bilddb/index.aspx?view=Search&mlfb=3RA2155-4UA35-0NB3&objecttype=14&gridview=view1

last modified:	12/15/2020 🖸