

Pilot devices, Ø 22 mm – Accessories

Ordering table



Description	Order Code	Weight, kg
-------------	------------	------------

Filament bulbs

Type of current: AC/DC. A lamp changing tool is required for changing bulb.

Rated voltage, V	Rated current, mA	Rated output, W	Luminance mcd	Service life, h		
6	200	1.2	350	10 000	5911 086-11	0.002
12	100	1.2	230	10 000	5911 086-12	0.002
24	50	1.2	280	10 000	5911 086-13	0.002
30	40	1.2	250	10 000	5911 086- 4	0.002
48	42	2	500	6 000	5911 086- 5	0.002
60	20	1.2	190	5 000	5911 086-14	0.002
110	18	2	250	7 500	5911 086- 7	0.002
130	15	2	120	7 500	5911 086-15	0.002

LED

With one diode chip mounted on a BA 9s base. A lamp changing tool is required for changing bulb.

Choose the same colour for the LED and the lamp cap or else use a clear lamp cap.

For white light use white LED with clear lamp cap.

At DC the lamp base have to be connected to cathode (-) and the bottom contact to anode (+).

Rated voltage, V	Rated current, mA	Colour	Wave-length, nm	Luminance mcd		
Type of current: (AC)/DC ¹⁾ Service life >50 000 hours.						
24	15	Red	630	250	1SFA 616 921 R2021	0.005
24	15	Green	525	800	1SFA 616 921 R2022	0.005
24	15	Yellow	592	250	1SFA 616 921 R2023	0.005
24	15	Blue	470	400	1SFA 616 921 R2024	0.005
24	15	White	x=0.31 x=0.32	500	1SFA 616 921 R2025	0.005

¹⁾ At AC the luminance is decreased with 30 % and there is also a slight flickering

Description	Order Code	Weight, kg
-------------	------------	------------

Mounting tool

Used for tightening the nut of the attachment device in confined spaces.

1SFA 616 920 R8015	0.100
---------------------------	-------

Membrane of silicone

Of transparent, heat and cold resistant silicon rubber.

Does not harden at low temperature. Gives IP 67 degree of protection. When membrane is used, remove the gasket.

For operator with:

Flush button	1SFA 616 920 R8052	0.002
Extended button	1SFA 616 920 R8002	0.002
Double pushbutton	SK 616 503-4	0.002

Protective ring

To prevent inadvertent operation.

Not together with legend plate holder.

SK 615 512-1	0.002
---------------------	-------

Protective cover

For flush button. To prevent inadvertent operation.

Not together with legend plate holder.

1SFA 616 920 R8010

30 mm adaptor

For use when fitting the 22 mm pushbutton range in 30 mm mounting holes. (1.5–4 mm panels)

Note: Can not be used with emergency stop button

Black plastic	1SFA 616 920R8003	0.012
Metal	1SFA 616 920R8004	0.037

Lamp changing tool

For LED and for bulbs

6880 311-1	0.005
-------------------	-------