



Non-reversing contactors 3 pole, AC & DC operated



A9-30-10



A26-30-10



A50-30-00



A95-30-00

General purpose current		Motor switching current	Maximum motor horsepower ratings  				Standard Aux. contacts		AC operated		DC operated	
AC oper.	DC oper.		208V	240V	480V	575/600V	N.O.	N.C.	Catalog number	List price	Catalog number	List price
AC1	AC1	AC3	UL rated									
21	—	9	2	2	5	7.5	1 0	0 1	A9-30-10-84 A9-30-01-84		BC9-30-10-04 BC9-30-01-04	
25	—	11	3	3	7.5	10	1 0	0 1	A12-30-10-84 A12-30-01-84		— —	— —
30	21	17	5	5	10	15	1 0	0 1	A16-30-10-84 A16-30-01-84		BC16-30-10-04 BC16-30-01-04	
40	33	28	7.5	10	20	25	1 0	0 1	A26-30-10-84 A26-30-01-84		BC25-30-10-04 BC25-30-01-04	
50	45	32	10	10	25	30	1 0 0 2	0 1 0 2	A30-30-10-84 A30-30-01-84 — —	— — — —	BC30-30-00-04 BC30-30-22-04	— —
60	—	41	10	15	30	40	1 0	0 1	A40-30-10-84 A40-30-01-84		— —	—
80	—	54	15	20	40	50	0 1	0 1	A50-30-00-84 A50-30-11-84		AE50-30-00-04 AE50-30-11-04	
90	—	65	20	25	50	60	0 1	0 1	A63-30-00-84 A63-30-11-84		AE63-30-00-04 AE63-30-11-04	
105	—	80	25	30	60	75	0 1	0 1	A75-30-00-84 A75-30-11-84		AE75-30-00-04 AE75-30-11-04	
125	—	95	30	30	60	75	0 1	0 1	A95-30-00-84 A95-30-11-84		AE95-30-00-04 AE95-30-11-04	
140	—	110	30	40	75	100	0 1	0 1	A110-30-00-84 A110-30-11-84		AE110-30-00-04 AE110-30-11-04	
NEMA rated												
NEMA size	Continuous current											
00	9	1.5	1.5	2	2	1	0		A9N00-30-10-84		BC9N00-30-10-04	
0	18	3	3	5	5	1	0		A16N0-30-10-84		BC16N0-30-10-04	
1	27	7.5	7.5	10	10	1	0		A26N1-30-10-84		BC25N1-30-10-04	
2	45	10	15	25	25	1	1		A50N2-30-11-84		AE50N2-30-11-04	
3	90	25	30	50	50	1	1		A75N3-30-11-84		AE75N3-30-11-04	

Coil voltage selection

All AC operated catalog numbers include a 120VAC coil. All DC operated catalog numbers include a 110VDC coil. To select other coil voltages, substitute the code from the Coil Voltage Selection Chart for the two digits after the last dash in the catalog number.

Ex.: A 240V coil is required for an A75 contactor: A75-30-00-**80**

Auxiliary contact blocks

For additional auxiliary contact blocks, see catalog number explanation on page 1.2. Add \$ 20 to list price for each additional auxiliary, and see page 1.18 for available combinations.

Coil voltage selection chart

Hz	Cntr type	Volts															
		12	24	48	110	120	125	208	220	240	277	380	415	440	480	500	600
60	A		81	83	84	84		34	75	80	42	48	86	86	51	53	55
50	A		81	83	84				80			85	86				55
DC	BC	07	01	16	04		27		05	33							
DC	AE	80	81	83	86		87		88	89							

For other voltages, see page 1.13