


Non-reversing contactors 4 pole, AC & DC operated



A9-40-00



A26-40-00



A75-40-00

4 Pole

UL general purpose current		Standard		AC operated		DC operated	
AC operated	DC operated	Auxiliary contacts		Catalog number	List price	Catalog number	List price
21	—	0	0	A9-40-00-84		BC9-40-00-04	
30	21	0	0	A16-40-00-84		BC16-40-00-04	
40	30	0	0	A26-40-00-84		BC25-40-00-04	
65	—	0	0	A45-40-00-84		AE45-40-00-04	
80	—	0	0	A50-40-00-84		AE50-40-00-04	
105	—	0	0	A75-40-00-84		AE75-40-00-04	

4 Pole – 2 N.O. & 2 N.C. power poles

UL general purpose current		Standard		AC operated		DC operated	
AC operated	DC operated	Auxiliary contacts		Catalog number	List price	Catalog number	List price
21	—	0	0	A9-22-00-84		BC9-22-00-04	
30	21	0	0	A16-22-00-84		BC16-22-00-04	
40	30	0	0	A26-22-00-84		BC25-22-00-04	
65	—	0	0	A45-22-00-84		AE45-22-00-04	
105	—	0	0	A75-22-00-84		AE75-22-00-04	

Coil voltage selection

All AC operated catalog numbers include a 120VAC coil. All DC operated catalog numbers include a 110VDC coil. To select other coil voltages, substitute the code from the Coil Voltage Selection Chart for the two digits after the last dash in the catalog number.

Ex.: A 240V coil is required for an A75 contactor:

A75-22-00-80

Auxiliary contact blocks

For additional auxiliary contact blocks, see catalog number explanation on page 1.2. Add \$20 to list price for each additional auxiliary, and see page 1.18 for available combinations.

Coil voltage selection chart

Hz	Cntr type	Volts															
		12	24	48	110	120	125	208	220	240	277	380	415	440	480	500	600
60	A		81	83	84	84		34	75	80	42	48	86	86	51	53	55
50	A		81	83	84				80			85	86			55	
DC	BC	07	01	16	04		27		05	33							
DC	AE	80	81	83	86		87		88	89							

For other voltages, see page 1.13