


AF40R ... AF96R 3-pole reversing contactors

30 to 60 hp at 480 V AC

AC / DC operated



AF40M-30-22



Power bus diagram

Description

- AF40R ... AF96R reversing contactors are mainly used for directionally controlling 3-phase motor circuits up to 690V AC. These devices include two 3-pole contactors, a mechanical interlock, side-mounted auxiliary contacts for electrical interlocking, power bus (see diagram to the left), and are assembled using fixing clips.
- **Note: for mechanically and electrically interlocked devices without power bus, replace the R in the catalog number with an M (ie. AF40R-30-22-13 becomes AF40M-30-22-13).**
- Control circuit: AC or DC operated with electronic coil interface accepting a wide control voltage range (e.g. 100...250 V AC and DC), only 4 control voltage ranges covering 24...500V 50/60 Hz and 20...500 V DC
- can manage large control voltage variations
- reduced panel energy consumption
- very distinct closing and opening.
- Built-in surge suppression
- Add-on auxiliary contact blocks for front or side mounting and a wide range of accessories.


Ordering details

IEC	UL / CSA	Rated control circuit voltage	Auxiliary contacts fitted	Catalog number	Global reference code (2)	Weight
Rated operational power	3-phase motor rating	Uc min. ... Uc max.				Pkg (1 pce)
400 V AC-3 kW	480 V	V 50/60 Hz V DC				kg
18.5	30	24...60 -	2 2	AF40R-30-22-41		2.283
		24...60 20...60 (1)	2 2	AF40R-30-22-11		2.283
		48...130 48...130	2 2	AF40R-30-22-12		2.283
		100...250 100...250	2 2	AF40R-30-22-13		2.263
		250...500 250...500	2 2	AF40R-30-22-14		2.263
22	40	24...60 -	2 2	AF52R-30-22-41		2.283
		24...60 20...60 (1)	2 2	AF52R-30-22-11		2.283
		48...130 48...130	2 2	AF52R-30-22-12		2.283
		100...250 100...250	2 2	AF52R-30-22-13		2.263
		250...500 250...500	2 2	AF52R-30-22-14		2.263
30	50	24...60 -	2 2	AF65R-30-22-41		2.283
		24...60 20...60 (1)	2 2	AF65R-30-22-11		2.283
		48...130 48...130	2 2	AF65R-30-22-12		2.283
		100...250 100...250	2 2	AF65R-30-22-13		2.263
		250...500 250...500	2 2	AF65R-30-22-14		2.263
37	60	24...60 -	2 2	AF80R-30-22-41		2.858
		24...60 20...60 (1)	2 2	AF80R-30-22-11		2.858
		48...130 48...130	2 2	AF80R-30-22-12		2.858
		100...250 100...250	2 2	AF80R-30-22-13		2.758
		250...500 250...500	2 2	AF80R-30-22-14		2.758
45	60	24...60 -	2 2	AF96R-30-22-41		2.858
		24...60 20...60 (1)	2 2	AF96R-30-22-11		2.858
		48...130 48...130	2 2	AF96R-30-22-12		2.858
		100...250 100...250	2 2	AF96R-30-22-13		2.758
		250...500 250...500	2 2	AF96R-30-22-14		2.758


(1) AF..-30-...-11 not suitable for direct control by PLC-output.

(2) Available in the US and Canada only.

Mounting dimensions mm, inches



AF40R, AF52R, AF65R



AF80R, AF96R