

Voltage code table

The below tables indicate the available coil voltages and corresponding digits for order codes. When placing an order, please give either type or order code. Select a standard contactor from ordering detail pages. Change the **coil voltage code** in the type or in the order code according to the table below. Example: for contactor AS09-30-10 and coil 42 V 50/60 Hz, type is AS09-30-10-**21** and order code is 1SBL101001R**21**10.

3-pole contactors

4

Type

AS16 - 30 - 10 - 26

Auxiliary contacts

N.O. N.C.

N.O. N.C.

Main contacts

AS

ASL

Contactor type

AC operated

DC operated

Order code

1SBL121001R 26 10

AC coil code

50 Hz 60 Hz

20 24 V 24 V

21 42 V 42 V

22 48 V 48 V

23 110 V 110 V

24 115 V 115 V

16 - 120 V

25 220 V 220 V

26 230 V 230 V

27 240 V 240 V

17 - 277 V

13 380 V -

28 400 V 400 V

29 415 V 415 V

DC coil code

80 12 V

81 24 V

83 48 V

84 60 V

86 110 V

87 125 V

88 220 V

89 240 V

3-pole reversing contactors

Type

VAS12 S EM - 26 M

Surge suppressor

VAS

VASL

Contactor type

AC operated

DC operated

Order code

1SBK113800M 26 00

AC coil code

50 Hz 60 Hz

20 24 V 24 V

21 42 V 42 V

22 48 V 48 V

23 110 V 110 V

24 115 V 115 V

16 - 120 V

25 220 V 220 V

26 230 V 230 V

27 240 V 240 V

17 - 277 V

13 380 V -

28 400 V 400 V

29 415 V 415 V

DC coil code

80 12 V (1)

81 24 V

83 48 V

84 60 V

86 110 V

87 125 V

88 220 V

89 240 V

(1) Not for VASL...SEM

Contactor relays

Type

NS 40 E - 26

Number contacts

N.O. N.C.

NS

NSL

Contactor type

AC operated

DC operated

Order code

1SBH101001R 26 40

AC coil code

50 Hz 60 Hz

20 24 V 24 V

21 42 V 42 V

22 48 V 48 V

23 110 V 110 V

24 115 V 115 V

16 - 120 V

25 220 V 220 V

26 230 V 230 V

27 240 V 240 V

17 - 277 V

13 380 V -

28 400 V 400 V

29 415 V 415 V

DC coil code

80 12 V

81 24 V

83 48 V

84 60 V

86 110 V

87 125 V

88 220 V

89 240 V