

Pre-wired Connector Models (M12)

Appearance		Sensing distance			Output configuration		Model	
							Operation mode	
							NO	NC
	M12	 2 mm			DC 2-wire, (3)-(4) pin arrangement		E2EZ-X2D1-M1J 0.3M	—
					DC 2-wire, (1)-(4) pin arrangement		E2EZ-X2D1-M1GJ 0.3M	—
	M18	 4 mm			DC 2-wire, (3)-(4) pin arrangement		E2EZ-X4D1-M1J 0.3M	—
					DC 2-wire, (1)-(4) pin arrangement		E2EZ-X4D1-M1GJ 0.3M	—
					DC 3-wire, PNP		E2EZ-X4B1-M1J 0.3M	—
	M30	 8 mm			DC 2-wire, (3)-(4) pin arrangement		E2EZ-X8D1-M1J 0.3M	—
					DC 2-wire, (1)-(4) pin arrangement		E2EZ-X8D1-M1GJ 0.3M	—
					DC 3-wire, PNP		E2EZ-X8B1-M1J 0.3M	—

Accessories (Order Separately)

Sensor I/O Connectors (M12, Sockets on One Cable End)

(Models for Pre-wired Connectors: A Connector is not provided with the Sensor. Be sure to order a Connector separately.) [Refer to Dimensions on XS2, XS5.]

Appearance	Cable length	Sensor I/O Connector model number	Applicable Proximity Sensor model number
Straight 	2 m	XS2F-D421-DD0	E2EZ-X□D1-M1J
	5 m	XS2F-D421-GD0	
L-shape 	2 m	XS2F-D422-DD0	
	5 m	XS2F-D422-GD0	
Straight 	2 m	XS2F-D421-DA0-F	E2EZ-X□D1-M1GJ
	5 m	XS2F-D421-GA0-F	
L-shape 	2 m	XS2F-D422-DA0-F	
	5 m	XS2F-D422-GA0-F	
Straight 	2 m	XS2F-D421-DC0-F	E2EZ-X□B1-M1J
	5 m	XS2F-D421-GC0-F	
L-shape 	2 m	XS2F-D422-DC0-F	
	5 m	XS2F-D422-GC0-F	
Smartclick Connector Straight 	2 m	XS5F-D421-D80-F	E2EZ-X□D1-M1TJ E2EZ-X□D1-M1TGJ
	5 m	XS5F-D421-G80-F	

Mounting Brackets

Protective Covers

Sputter Protective Covers

Refer to Y92□ for details.