


IORR..MT contactors

Power circuit up to 1000 V AC

Control circuit 120V 50/60 Hz



IORR1400-20-MT

Description

IORR..MT contactors are used for controlling AC power circuits from 500 up to 1000 V AC.

These contactors are designed with:

- variable number of poles according to the application
- control circuit: AC operated
- 2 NO + 2 NC auxiliary contacts available, as standard

Ordering details

AC-3				AC-1	Number of poles	Rated control circuit voltage Uc (1) V 50/60 Hz	Auxiliary contacts fitted (2)	Type	Order code	Weight
Rated operational power (3)		current	θ ≤ 40 °C	Pkg (1 pce)						
690 V	1000 V	≤ 690 V								kg
kW	kW	A	A							
80	80	85	85	2	120V	2 2	IORR63-20-MT	FPL7125216R2113		4.2
				3		2 2	IORR63-30-MT	FPL7125386R2113		5.2
				4		2 2	IORR63-40-MT	FPL7125416R2113		6.2
150	150	160	170	2	120V	2 2	IORR125-20-MT	FPL7425215R2113		6.2
				3		2 2	IORR125-30-MT	FPL7425315R2113		8.2
				4		2 2	IORR125-40-MT	FPL7425415R2113		10.2
240	250	260	260	2	120V	2 2	IORR200-20-MT	FPL7625215R2113		9.6
				3		2 2	IORR200-30-MT	FPL7625315R2113		12.6
				4		2 2	IORR200-40-MT	FPL7625415R2113		15.6
400	400	400	400	2	120V	2 2	IORR400-20-MT	FPL9425215R2113		19.2
				3		2 2	IORR400-30-MT	FPL9425315R2113		25
				4		2 2	IORR400-40-MT	FPL9425415R2113		30.8
540	550	550	550	2	120V	2 2	IORR500-20-MT	FPL8325215R2113		19.7
				3		2 2	IORR500-30-MT	FPL8325315R2113		25.5
				4		2 2	IORR500-40-MT	FPL8325415R2113		31.3
780	850	800	800	2	120V	2 2	IORR800-20-MT	FPL8625215R2113		40
				3		2 2	IORR800-30-MT	FPL8625315R2113		51
				4		2 2	IORR800-40-MT	FPL8625415R2113		62
1000	900	970	1250	2	120V	2 2	IORR1400-20-MT	FPL6125215R2113		42
				3		2 2	IORR1400-30-MT	FPL6125315R2113		52
				4		2 2	IORR1400-40-MT	FPL6125415R2113		65
1200	1000	1170	1650	2	120V	2 2	IORR1700-20-MT	FPL6225215R2113		47
				3		2 2	IORR1700-30-MT	FPL6225315R2113		61
				4		2 2	IORR1700-40-MT	FPL6225415R2113		74
1300	1200	1270	1850	2	120V	2 2	IORR2100-20-MT	FPL6325215R2113		52
				3		2 2	IORR2100-30-MT	FPL6325315R2113		68
				4		2 2	IORR2100-40-MT	FPL6325415R2113		82
-	-	-	2200	2	120V	2 2	IORR2500-20-MT	FPL6725215R2113		71
				3		2 2	IORR2500-30-MT	FPL6725315R2113		On request
				4		2 2	IORR2500-40-MT	FPL6725415R2113		
-	-	-	3000	2	120V	2 2	IORR3200-20-MT	FPL6525215R2113		83
				3		2 2	IORR3200-30-MT	FPL6525315R2113		On request
-	-	-	3500	2	120V	2 2	IORR3800-20-MT	FPL6625215R2113		95
				3		2 2	IORR3800-30-MT	FPL6625001R2113		On request
-	-	-	4000	2	120V	2 2	IORR4500-20-MT	FPL6825215R2113		On request
				3		2 2	IORR4500-30-MT	FPL6825002R2113		
-	-	-	4500	2	120V	2 2	IORR5100-20-MT	FPL6925001R2113		On request
				3		2 2	IORR5100-30-MT	FPL6925002R2113		

(1) Other control voltages, please contact us.

(2) Other auxiliary contact arrangements, please contact us.

(3) Power circuit above 1000 V AC, please contact us.