

Specifications



Eaton 184122

Eaton Moeller series IZMX/INX - ACB. Eaton Moeller series IZMX/INX - ACB. Reset remote, 24VDC, Acc

General specifications

PRODUCT NAME	Eaton Moeller series IZMX/INX remote reset
CATALOG NUMBER	184122
MODEL CODE	+IZMX-RR24DC-40-1
EAN	4015081796502
PRODUCT LENGTH/DEPTH	150 mm
PRODUCT HEIGHT	100 mm
PRODUCT WIDTH	100 mm
PRODUCT WEIGHT	0.125 kg
COMPLIANCES	RoHS conform
GLOBAL CATALOG	184122

Product specifications

USED WITH	IZMX40...F IZMX40...W
ELECTRIC CONNECTION TYPE	Flat plug-in connection
RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 50 HZ - MAX	0 V
RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 50 HZ - MIN	0 V
RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 60 HZ - MAX	0 V
RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 60 HZ - MIN	0 V
RATED CONTROL SUPPLY VOLTAGE (US) AT DC - MAX	24 V
RATED CONTROL SUPPLY VOLTAGE (US) AT DC - MIN	24 V
ACCESSORY/SPARE PART TYPE	Trip indication / Reset options
ADJUSTMENT RANGE UNDELAYED SHORT-CIRCUIT RELEASE (END VALUE) - MAX	0 A
AMBIENT OPERATING TEMPERATURE - MAX	70 °C
AMBIENT OPERATING TEMPERATURE - MIN	-25 °C
INITIAL VALUE OF THE UNDELAYED SHORT-CIRCUIT RELEASE - MIN	0 A
NUMBER OF CONTACTS (CHANGE-OVER CONTACTS)	0
NUMBER OF CONTACTS (NORMALLY CLOSED CONTACTS)	0
NUMBER OF CONTACTS (NORMALLY OPEN CONTACTS)	0
VOLTAGE TYPE	DC
CONTROL VOLTAGE OPERATING RANGE	24 V DC

Resources

CATALOGS	eaton-acb-izm63-catalog-ca0135003en-en-us.pdf
ECAD MODEL	DA-CE-ETN. IZMX-RR24DC-40-1
INSTALLATION INSTRUCTIONS	eaton-izmx16-izmx40-pop-out-trip-indicators-il0131126en-us.pdf
INSTALLATION VIDEOS	Air Circuit Breakers Series IZMX

TYPE	Accessory
SPECIAL FEATURES	• The circuit-breaker is equipped with a mechanical trip indicator (red pin). • After the remote reset coil is electrically actuated, the reclosing lockout can be reset. • Cannot be combined with remote reset.
SUITABLE FOR	Power circuit breaker Off-load switch

PROJECT NAME:
PROJECT NUMBER:
PREPARED BY:
DATE:



Eaton Corporation plc
Eaton House
30 Pembroke Road
Dublin 4, Ireland
Eaton.com

© 2025 Eaton. All Rights Reserved.

Follow us on social media to get the latest product and support information.

