

SIMOTICS GP - 132 M - IM B5 - 4p

Client order no.	Item-No.	Offer no.
Order no.	Consignment no.	Project

Remarks

Safe Area

U	Δ / Y	f	P	P	I	n	M	η ³⁾			cosφ ³⁾			I _A /I _N	M _A /M _N	M _K /M _N	IE-CL
[V]		[Hz]	[kW]	[hp]	[A]	[1/min]	[Nm]	4/4	3/4	2/4	4/4	3/4	2/4	I _I /I _N	T _I /T _N	T _B /T _N	
DOL duty (S1) - 155(F) to 130(B)																	
230	Δ	50	7.50	-/-	26.00	1465	49.0	90.4	90.7	90.4	0.80	0.74	0.63	8.5	3.0	3.8	IE3
400	Y	50	7.50	-/-	15.00	1465	49.0	90.4	90.7	90.4	0.80	0.74	0.63	8.5	3.0	3.8	IE3
460	Y	60	8.60	-/-	14.90	1765	46.5	89.5	90.0	89.4	0.81	0.76	0.65	8.8	3.0	3.8	IE2
460	Y	60	7.50	10.00	13.00	1770	40.5	91.7	91.6	90.6	0.79	0.73	0.61	9.8	3.4	4.3	MG1
IM B5 / IM 3001			FS 132 M		CC032A		IP55	UKCA		IEC/EN 60034		IEC, EN, UL, CSA, NEMA MG1-12			kVA Code: N		
Environmental conditions : -20 °C - +40 °C / 1,000 m									Locked rotor time (hot / cold) : 14.8 s 20.1 s								

Sound level (SPL / SWL) at 50Hz 60Hz	72 / 80 dB(A) ^{2) 3)}	68 / 76 dB(A) ^{2) 3)}	Vibration severity grade	A
Moment of inertia	0.0334 kg m²		Thermal class	F
Bearing DE NDE	6208 2Z C3	6208 2Z C3	Duty type	S1
bearing lifetime			Direction of rotation	bidirectional
L _{10mh} F _{Rad min} for coupling operation 50 60Hz ¹⁾	40000 h	32000 h	Frame material	aluminum
Regreasing device	Without		Net weight of the motor (IM B3)	61 kg
Grease nipple	-/-		Coating (paint finish)	Standard paint finish C2
Type of bearing	Preloaded bearing DE		Color, paint shade	RAL7030
Condensate drainage holes	Without		Motor protection	(A) without (Standard)
External earthing terminal	Without		Method of cooling	IC411 - self ventilated, surface cooled

Terminal box position	top	Max. cross-sectional area	6 mm²
Material of terminal box	Aluminium	Cable diameter from ... to ...	11 mm - 21 mm
Type of terminal box	TB1 H00	Cable entry	2xM32x1,5
Contact screw thread	M4	Cable gland	2 plugs

Notes:

I_R/I_N = locked rotor current / current nominal	1) L10mh according to DIN ISO 281 10/2010	3) Value is valid only for DOL operation with motor design IC411
M_R/M_N = locked rotor torque / torque nominal	2) at rated power / at full load	
M_b/M_N = break down torque / nominal torque		

responsible dep. DI MC LVM	technical reference	created by DT Configurator	approved by	Technical data are subject to change! There may be discrepancies between calculated and rating plate values.		Link documents	
	document type datasheet	document status released					
	title 1LE1023-1CB22-2FA4						
© Siemens AG 2023				rev. 943	creation date 2023-05-03	language en	Page 1/1