# Eaton 230116

# Catalog Number: 230116

Eaton Moeller® series DILM Replacement coil, Tool-less plug connection, RDC 60: 48 - 60 V DC, DC, For use with: DILM115, DILM150, DILM170

# General specifications



Eaton Moeller® series DILM

Product Length/Depth

51 mm

**Product Width** 

63.2 mm

Certifications

UL File No.: E29096 CSA File No.: 012528 CSA-C22.2 No. 14-05

UL 508

UL Category Control No.: NLDX CSA Class No.: 2411-03, 3211-04

UL CE CSA

IEC/EN 60947-4-1



replacement coil

EAN 4015082301163

**Product Height** 

Catalog Number

110 mm

230116

**Product Weight** 

0.245 kg





#### General

Accessories

Individual coils

**Product category** 

Accessories

Voltage type

DC

# Climatic environmental conditions

Ambient operating temperature - min

-25 °C

Ambient operating temperature - max

60 °C

# Magnet system

Rated control supply voltage (Us) at AC, 50 Hz - min

0 V

Rated control supply voltage (Us) at AC, 50 Hz - max

0 V

Rated control supply voltage (Us) at AC, 60 Hz - min

0 V

Rated control supply voltage (Us) at AC, 60 Hz - max

0 V

Rated control supply voltage (Us) at DC - min

48 V

Rated control supply voltage (Us) at DC - max

60 V

# Design verification

#### 10.2.2 Corrosion resistance

Meets the product standard's requirements.

10.2.3.1 Verification of thermal stability of enclosures

Meets the product standard's requirements.

10.2.3.2 Verification of resistance of insulating materials to normal heat

Meets the product standard's requirements.

10.2.3.3 Resist. of insul. mat. to abnormal heat/fire by internal elect. effects

Meets the product standard's requirements.

# 10.2.5 Lifting

Does not apply, since the entire switchgear needs to be evaluated.

#### 10.2.6 Mechanical impact

Does not apply, since the entire switchgear needs to be

#### Resources

# Catalogs

Product Range Catalog Switching and protecting motors

eat on-product-overview-for-machinery-catalogue-ca 08103003 zen-enus.pdf

SmartWire-DT Catalog

# Drawings

eaton-contactors-dilm-replacement-coil-3d-drawing.eps

# eCAD model

ETN.230116.edz

Installation instructions

IL03407042Z

# Installation videos

WIN-WIN with push-in technology

#### evaluated.

# 10.2.7 Inscriptions

Meets the product standard's requirements.

# 10.3 Degree of protection of assemblies

Does not apply, since the entire switchgear needs to be evaluated.

#### 10.4 Clearances and creepage distances

Meets the product standard's requirements.

#### 10.5 Protection against electric shock

Does not apply, since the entire switchgear needs to be evaluated.

# 10.6 Incorporation of switching devices and components

Does not apply, since the entire switchgear needs to be evaluated.

#### 10.7 Internal electrical circuits and connections

Is the panel builder's responsibility.

#### 10.8 Connections for external conductors

Is the panel builder's responsibility.

# 10.9.2 Power-frequency electric strength

Is the panel builder's responsibility.

#### 10.9.3 Impulse withstand voltage

Is the panel builder's responsibility.

# 10.9.4 Testing of enclosures made of insulating material

Is the panel builder's responsibility.

# 10.11 Short-circuit rating

Is the panel builder's responsibility. The specifications for the switchgear must be observed.

# 10.12 Electromagnetic compatibility

Is the panel builder's responsibility. The specifications for the switchgear must be observed.

# 10.13 Mechanical function

The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.



Eaton Corporation plc Eaton House 30 Pembroke Road Dublin 4, Ireland Eaton.com

Reserved.

Eaton is a registered trademark.

All other trademarks are © 2024 Eaton. All Rights property of their respective owners.



Eaton.com/socialmedia