

Product datasheet

Specifications



PILOT LIGHT 28V 30MM TYPE K +OPTIONS

9001KP35

⚠ Discontinued on: 4 Aug 2021

EAN Code: 3389118041318

⚠ Discontinued

Main

Range of product	Harmony 9001K
Product or component type	Head for pilot light
Device short name	K

Complementary

Bezel material	Metal
Mounting diameter	30 mm
Cap/operator or lens colour	Without cap
Bulb base	BA 9s
Light block supply	Full voltage 24 V Full voltage 28 V
Shape of screw head	Round
Light source	Incandescent bulb
Operating mode	Normal
[Us] rated supply voltage	24...28 V
Light block supply	Full voltage
Size	30 mm

Environment

Product certifications	CSA LR25490 class 3211 03 UL listed file E42259 CCN NKCR CE
NEMA degree of protection	NEMA 1/2/3/3R/4/6/12/13

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	4.826 cm
Package 1 Width	5.842 cm
Package 1 Length	9.398 cm
Package 1 Weight	131.542 g

Contractual warranty

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Warranty

18 months

Sustainability



Green Premium™ label is Schneider Electric’s commitment to delivering products with best-in-class environmental performance. Green Premium promises compliance with the latest regulations, transparency on environmental impacts, as well as circular and low-CO₂ products.

Guide to assessing product sustainability is a white paper that clarifies global eco-label standards and how to interpret environmental declarations.

[Learn more about Green Premium >](#)

[Guide to assess a product’s sustainability >](#)

Well-being performance

 Mercury Free	
 Rohs Exemption Information	Yes
Reach Regulation	REACH Declaration
Eu Rohs Directive	Pro-active compliance (Product out of EU RoHS legal scope)
China Rohs Regulation	China RoHS declaration
Weee	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins