



Siemens Low Voltage Residential Generators Standby power (Generators) -
Generators: Accessories are Residential Enclosures Standby power (Generators).
Sub Brand: Standby Power Systems Type: Manual Transfer Interlock Kit
Application: For use on load centers or meter combinations that will accept 2-pole
circuit breakers opposite one another Standard: UL/NEMA 1/3R Amperage Rating:
225A Mounting: Flush or Surface Length: 3.6 Width: 5.1 Height: 12.9

| General technical data | |
|---------------------------------------|---|
| fastening method | Flush or Surface |
| suitability for operation | For use on load centers or meter combinations that will accept 2-pole circuit breakers opposite one another |
| Electricity | |
| operational current at AC rated value | 225 A |
| Model | |
| product brand name | Siemens |
| product sub brand name | Standby Power Systems |
| product type designation | Manual Transfer Interlock Kit |
| Mechanical Design | |
| depth [in] | 3.6 in |
| height [in] | 12.9 in |
| width [in] | 5.1 in |
| General product approval | |
| certificate of suitability | UL/NEMA 1/3R |

last modified:

1/6/2021 

