

Siemens Low Voltage Residential Generators Standby power (Generators) -
Generators: Accessories are Residential Enclosures Standby power (Generators).
Sub Brand: Standby Power Systems Type: Manual Transfer Interlock Kit
Application: For use on load centers or meter combinations that will accept two
QNR/MD-TR frame circuit breakers side by side OR will accept two QN/MD-T
circuit breakers side by side Standard: UL/NEMA 1/3R Amperage Rating: 225A
Mounting: Flush or Surface Length: 1 Width: 3 Height: 4



| General technical data | |
|---------------------------------------|---|
| fastening method | Flush or Surface |
| suitability for operation | For use on load centers or meter combinations that will accept two QNR/MD-TR frame circuit breakers side by side OR will accept two QN/MD-T circuit breakers side by side |
| Electricity | |
| operational current at AC rated value | 225 A |
| Model | |
| product brand name | Siemens |
| product sub brand name | Standby Power Systems |
| product type designation | Manual Transfer Interlock Kit |
| Mechanical Design | |
| depth [in] | 1 in |
| height [in] | 4 in |
| width [in] | 3 in |
| General product approval | |
| certificate of suitability | UL/NEMA 1/3R |

last modified:

1/6/2021 

