

Pushbutton Selectors (Assembled)

Part Numbers: Pushbutton Selectors

Style		Terminal Style	
		Solder Tab	PCB
	2 Position	HA1R-2C6-①	HA1R-2C2V-①
	3 Position	HA1R-3C6-①	HA1R-3C2V-①

① Button Color Code

Color	Code
Black	B
Green	G
Red	R
Blue	S
Yellow	Y



1. In place of ① specify Button Color Code.
2. PCB terminal models also available with silver contacts (change "1" or "2" to "5" or "6" respectively, ie HA1R-2C2V-① becomes HA1R-2C6V-①).

Contact Operation

Style	Operator Position					
	Left		Center		Right	
	Normal	Depressed	Normal	Depressed	Normal	Depressed
2 Position			—	—		
3 Position				Blocked		

Lever Switch (Assembled)

Part Numbers: Lever Switches

Style	Operation			Contacts	Terminal Type	
					Solder Tab	PCB
	2-Position	Maintained		DPDT	LA1T-2C6	LA1T-2C2V
		Spring return from top		DPDT	LA1T-21C6	LA1T-21C2V
		Spring Return from bottom		DPDT	LA1T-22C6	LA1T-22C2V
	3-Position	Maintained		DPDT	LA1T-3C6	LA1T-3C2V
		Spring return from top		DPDT	LA1T-31C6	LA1T-31C2V
		Spring return from bottom		DPDT	LA1T-32C6	LA1T-32C2V
		Spring return from both		DPDT	LA1T-33C6	LA1T-33C2V



PCB terminal models also available with silver contacts (change "1" or "2" to "5" or "6" respectively, ie LA1T-2C2V becomes LA1T-2C6V).

Contact Operation

Contacts		Operator Position & Contact Operation		
		Down	Center	Up
2-pos. (DPDT)	Maintained Spring from Top			
2-pos (DPDT).	Spring Return from Bottom			
3-pos. (DPDT)	All models			



As viewed from front of switch.