



FULL-VOLTAGE NON-REVERSING IEC STARTER UNFUSED TYPE 12

LE1D123A72OG70

Main

Product or component type	Full voltage starter
Range of product	Instakits
Starter Type	Non reversing

Complementary

Control Circuit Voltage	120 V AC 50/60 Hz
Current Rating	12 A
Horsepower Rating	0.5 hp 120 V AC, 1 phase
	2 hp 240 V AC, 1 phase
	3 hp 208 V AC, 3 phases
	3 hp 230 V AC, 3 phases
	7.5 hp 460 V AC, 3 phases
	10 hp 575 V AC, 3 phases
Maximum Voltage Rating	600 V AC
Auxiliary Contacts	1 NO + 1 NC
Location of connection	Line

Environment

Enclosure Type	NEMA 12 steel	
Product certifications	UL IEC CSA	

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	10.600 in (26.924 cm)
Package 1 Width	9.200 in (23.368 cm)
Package 1 Length	14.400 in (36.576 cm)
Package 1 Weight	10.360 lb(US) (4.699 kg)



Green PremiumTM label is Schneider Electric's commitment to delivering products with best-inclass environmental performance. Green Premium promises compliance with the latest regulations, transparency on environmental impacts, as well as circular and low-CO₂ products.

Guide to assessing product sustainability is a white paper that clarifies global eco-label standards and how to interpret environmental declarations.

Learn more about Green Premium >

Guide to assess a product's sustainability >



RoHS/REACh

Well-being performance

②	Reach Free Of Svhc
⊘	Toxic Heavy Metal Free
⊘	Mercury Free
⊘	Rohs Exemption Information Yes
⊘	Pvc Free

Certifications & Standards

Reach Regulation	REACh Declaration
Eu Rohs Directive	Compliant EU RoHS Declaration
China Rohs Regulation	China RoHS declaration
Circularity Profile	No need of specific recycling operations