



FULL-VOLTAGE NON-REVERSING IEC STARTER UNFUSED TYPE 1

LE1D403A62OG70

Main

Product or component type	Full voltage starter
Range of product	Instakits
Starter Type	Non reversing

Complementary

Control Circuit Voltage	120 V AC 50/60 Hz
Current Rating	40 A
Horsepower Rating	5 hp 240 V AC, 1 phase 10 hp 208 V AC, 3 phases 10 hp 230 V AC, 3 phases 3 hp 120 V AC, 1 phase 30 hp 460 V AC, 3 phases 30 hp 575 V AC, 3 phases
Maximum Voltage Rating	600 V AC
Auxiliary Contacts	1 NO + 1 NC
Protection type	Switch-disconnector fuse
Location of connection	Line

Environment

Product certifications	CSA IEC UL	
Enclosure Type	NEMA 1 steel	

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	10.6 in (26.9 cm)
Package 1 Width	13.0 in (33.0 cm)
Package 1 Length	18.4 in (46.7 cm)
Package 1 Weight	19.03 lb(US) (8.63 kg)



Green PremiumTM label is Schneider Electric's commitment to delivering products with best-inclass environmental performance. Green Premium promises compliance with the latest regulations, transparency on environmental impacts, as well as circular and low-CO₂ products.

Guide to assessing product sustainability is a white paper that clarifies global eco-label standards and how to interpret environmental declarations.

Learn more about Green Premium >

Guide to assess a product's sustainability >



RoHS/REACh

Well-being performance

②	Reach Free Of Svhc
⊘	Toxic Heavy Metal Free
⊘	Mercury Free
⊘	Rohs Exemption Information Yes
⊘	Pvc Free

Certifications & Standards

Reach Regulation	REACh Declaration
Eu Rohs Directive	Compliant EU RoHS Declaration
China Rohs Regulation	China RoHS declaration
Circularity Profile	No need of specific recycling operations