

# Control terminal block, TeSys Ultra, for reversing motor starter

LU9MR1

#### Main

Range	TeSys
Device short name	LU9MR
product or component type	Control terminal block
Product compatibility	LU6MB0

## Complementary

net weight	0.03 kg
Tightening torque	Control circuit: 0.81.2 N.m flat screwdriver 5 mm
	Control circuit: 0.81.2 N.m Philips No 2 screwdriver 5 mm
	Power circuit: 1.92.5 N.m flat screwdriver 6 mm
	Power circuit: 1.92.5 N.m Philips No 2 screwdriver 6 mm
	Power circuit: 1.9 2.5 N m pozidriv No 2 screwdriver 6 mm

## **Packing Units**

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	3.0 cm
Package 1 Width	3.5 cm
Package 1 Length	5.0 cm
Package 1 Weight	26.0 g
Unit Type of Package 2	S01
Number of Units in Package 2	30
Package 2 Height	15.0 cm
Package 2 Width	15.0 cm
Package 2 Length	40.0 cm
Package 2 Weight	970.0 g

## **Contractual warranty**

Warranty 18 months

## Sustainability

**Green Premium<sup>TM</sup> label** is Schneider Electric's commitment to delivering products with best-inclass environmental performance. Green Premium promises compliance with the latest regulations, transparency on environmental impacts, as well as circular and low-CO<sub>2</sub> products.

**Guide to assessing product sustainability** is a white paper that clarifies global eco-label standards and how to interpret environmental declarations.

Learn more about Green Premium >

Guide to assess a product's sustainability >

## Well-being performance

Reach Free Of Svhc	
Toxic Heavy Metal Free	
Mercury Free	
Rohs Exemption Information	Yes
Reach Regulation	REACh Declaration
Eu Rohs Directive	Compliant EU RoHS Declaration
China Rohs Regulation	China RoHS declaration  Pro-active China RoHS declaration (out of China RoHS legal scope)
Weee	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins