



## H7CC-R11

Digital counter, plug-in, 11-pin, 48x48 mm, IP66, 6 count digits, tachometer, SPDT 3 A relay output, 100-240 VAC supply, 12 VDC aux. supply

# Specifications

|                           |                        |
|---------------------------|------------------------|
| Type                      | Pre-set counter        |
| Size                      | 1/16 DIN (48 x 48 mm)  |
| Counting functions        | Tachometer             |
| Counting range            | 0 - 999999             |
| LCD backlight             | With backlight         |
| Number of digits          | 6                      |
| Body color                | Black                  |
| Installation type         | Socket                 |
| Terminal type             | Plug-in                |
| Output type               | Relay                  |
| Relay output              | 1                      |
| Transistor output         | 0                      |
| Inputs                    | DC voltage, No-voltage |
| Supply voltage AC         | 100-240 V              |
| Speed                     | 10000 Hz               |
| Product Width (unpacked)  | 48 mm                  |
| Product Height (unpacked) | 48 mm                  |
| Product Depth (unpacked)  | 63.7 mm                |

## Accessories



**P2CF-11-E**

Socket, DIN rail/surface mounting, 11-pin, screw terminals



**P3GA-11**

Socket, back-connecting, 11-pin, screw terminals



**Y92A-48**

Protective cover for DIN48x48mm device, hard plastic (shallow)



**Y92A-48F1**

Protective cover for DIN 48 x 48 mm timer and counter, soft plastic



**Y92F-30**

Flush panel mounting adapter for DIN 48x48 mm device



**Y92F-45**

Panel adaptor, 48 x 48 device into 67 x 67 hole

## Downloads

[CAD Library](#)



**H7CC Digital Counter/Digital Tachometer**

**Brochure**

**EN** PDF 3.65 MB



**H7CC Digital Counter/Tachometer**

**Datasheet**

**EN** PDF 16 MB



**H7CC-R\_**  
**Instruction Manual**

**EN** PDF 2.82 MB

