

Key Selector Switches

Part No.	<b>LBW</b> ① <b>K</b> - ② ③ <b>T</b> ④ ⑤ - ⑥						
	<b>Wave Key</b>				<b>Disc Tumbler Key</b>		
	Round / Black Bezel	Square / Black Bezel	Round / Metallic Bezel	Square / Metallic Bezel	Round / Metallic Bezel	Square / Metallic Bezel	
① Style	② Operator Position		⑤ Key Removable Position	⑥ Contact	Part No.		
					Gold Contact	Silver Contact	
Black bezel	90° 2-position	Maintained	A: Key removable in all positions		SPDT	<b>LBW</b> ① <b>K</b> -2 <b>ST</b> 1 <b>A</b>	<b>LBW</b> ① <b>K</b> -2 <b>ST</b> 5 <b>A</b>
					DPDT	<b>LBW</b> ① <b>K</b> -2 <b>ST</b> 2 <b>A</b>	<b>LBW</b> ① <b>K</b> -2 <b>ST</b> 6 <b>A</b>
	45° 3-position	Maintained	A: Key removable in all positions		DPDT	<b>LBW</b> ① <b>K</b> -3 <b>ST</b> 2 <b>A</b>	<b>LBW</b> ① <b>K</b> -3 <b>ST</b> 6 <b>A</b>
					3PDT	<b>LBW</b> ① <b>K</b> -3 <b>ST</b> 3 <b>A</b>	<b>LBW</b> ① <b>K</b> -3 <b>ST</b> 7 <b>A</b>
Metallic bezel	90° 2-position	Maintained	A: Key removable in all positions		SPDT	<b>LBW</b> ① <b>K</b> -2 <b>ST</b> 1 <b>A</b>	<b>LBW</b> ① <b>K</b> -2 <b>ST</b> 5 <b>A</b>
					DPDT	<b>LBW</b> ① <b>K</b> -2 <b>ST</b> 2 <b>A</b>	<b>LBW</b> ① <b>K</b> -2 <b>ST</b> 6 <b>A</b>
	45° 3-position	Maintained	A: Key removable in all positions		DPDT	<b>LBW</b> ① <b>K</b> -3 <b>ST</b> 2 <b>A</b>	<b>LBW</b> ① <b>K</b> -3 <b>ST</b> 6 <b>A</b>
					3PDT	<b>LBW</b> ① <b>K</b> -3 <b>ST</b> 3 <b>A</b>	<b>LBW</b> ① <b>K</b> -3 <b>ST</b> 7 <b>A</b>

- For operator position, see Part Number Interpretation below.
- For key removable position, see Part Number Interpretation below. The key cannot be removed in a spring returned position.
- Two keys are supplied.
- Besides the standard key (key number 0H), six other keys are available.
- Disc tumbler keys also available. Only the standard key is available. To specify, see Part Number Interpretation below.
- PC board terminals available for gold contacts. To specify, see Part Number Interpretation below.
- For contact operation, see 593.

Part Number Interpretation

**LBW** ① **K**- ② ③ **T** ④ ⑤ - ⑥



To be used for interpreting part numbers only, not for part number development.

① Style

Code	Shape
6	Round / Black Bezel
7	Square / Black Bezel
6M	Round / Metallic Bezel
7M	Square / Metallic Bezel

② Operator Position

Code	Operator Position
2	90° 2-position maintained
3	45° 3-position maintained
33	45°-3-position spring return two-way

③ Key Style

Code	Key Style
S	Wave key
Blank	Disc tumbler key

④ Contacts

Code	Contact
1	Gold/SPDT (90° 2-position only)
2	Gold/DPDT
3	Gold/3PDT
5	Silver/SPDT (90° 2-position only)
6	Silver/DPDT
7	Silver/3PDT

⑤ Key Removal Position

2-position Key Removable Position	
A: Key removable in all positions 	B: Key removable at left position only 

3-position Key Removable Position	
A: Key removable in all positions 	D: Key removable at center only 

⑥ Key Number (for wave keys only)

Code	
0H or Blank	Standard key
1H to 2H	Reversible key
3H to 6H	Non-reversible key

Others

Code	Specification	Part No. Example
Blank	Solder/Tab Terminal	—
V	PC Board Terminal (Gold Contact Only)	LBW6K-2T1VA


3-position

Spring return two-way



- Key removable at L, C, R.
- Key retained at L, R.

Key Selector Switches (Sub-assembled)



Contact Block

Terminal Style	Material	Contact	Part Number	
	Solder/Tab	Silver	SPDT	LB-T5
			DPDT	LB-T6
			3PDT	LB-T7
	PCB	Gold	SPDT	LB-T1V
			DPDT	LB-T2V
			3PDT	LB-T3V

Operator

Style	Shape	Position	Function	Key Style	Key Remove Position	Part number	
	Round	2	90° 2-position maintained	Disc tumbler key	All positions	LBW6K-2A	
					Left	LBW6K-2B	
				Wave key	All positions	LBW6K-2SA	
		Left			LBW6K-2SB		
		3		45° 3-position maintained	Disc tumbler key	All positions	LBW6K-3A
						Center	LBW6K-3D
	Wave key		All positions		LBW6K-3SA		
		Center	LBW6K-3SD				
	3	45°-3-position spring return two-way	Disc tumbler key	All positions	LBW6K-33D		
				Wave key	Center	LBW6K-33SD	
			Wave key	Center	LBW6K-33SD		
	Square	2		90° 2-position maintained	Disc tumbler key	All positions	LBW7K-2A
			Left			LBW7K-2B	
			Wave key		All positions	LBW7K-2SA	
		Left			LBW7K-2SB		
		3	45° 3-position maintained		Disc tumbler key	All positions	LBW7K-3A
						Center	LBW7K-3D
	Wave key			All positions	LBW7K-3SA		
Center		LBW7K-3SD					
Wave key	45°-3-position spring return two-way	Disc tumbler key	Center	LBW7K-33D			
			Wave key	Center	LBW7K-33SD		

Style	Shape	Position	Function	Key Style	Key Remove Position	Part number	
	Round	2	90° 2-position maintained	Disc tumbler key	All positions	LBW6MK-2A	
					Left	LBW6MK-2B	
				Wave key	All positions	LBW6MK-2SA	
		Left			LBW6MK-2SB		
		3		45° 3-position maintained	Disc tumbler key	All positions	LBW6MK-3A
						Center	LBW6MK-3D
	Wave key		All positions		LBW6MK-3SA		
		Center	LBW6MK-3SD				
	3	45°-3-position spring return two-way	Disc tumbler key	Center	LBW6MK-33D		
				Wave key	Center	LBW6MK-33SD	
			Wave key	Center	LBW6MK-33SD		
	Square	2		90° 2-position maintained	Disc tumbler key	All positions	LBW7MK-2A
Left			LBW7MK-2B				
Wave key			All positions		LBW7MK-2SA		
		Left	LBW7MK-2SB				
3		45° 3-position maintained	Disc tumbler key		All positions	LBW7MK-3A	
					Center	LBW7MK-3D	
	Wave key		All positions	LBW7MK-3SA			
Center		LBW7MK-3SD					
Wave key	45°-3-position spring return two-way	Disc tumbler key	Center	LBW7MK-33D			
			Wave key	Center	LBW7MK-33SD		

Switches & Pilot Devices

Signaling Lights

Relays & Sockets

Timers

Contactors

Terminal Blocks

Circuit Breakers